

A Lambda Calculus for Density Matrices with Classical and Probabilistic Controls

Alejandro Díaz-Caro*

Universidad Nacional de Quilmes & CONICET
Roque Sáenz Peña 352, B1876BXD Bernal, Buenos Aires, Argentina
`alejandro.diaz-caro@unq.edu.ar`

Abstract. In this paper we present two flavors of a quantum extension to the lambda calculus. The first one, λ_ρ , follows the approach of classical control/quantum data, where the quantum data is represented by density matrices. We provide an interpretation for programs as density matrices and functions upon them. The second one, λ_ρ° , takes advantage of the density matrices presentation in order to follow the mixed trace of programs in a kind of generalised density matrix. Such a control can be seen as a weaker form of the quantum control and data approach.

Keywords: lambda calculus, quantum computing, density matrices, classical control

1 Introduction

In the last decade several quantum extensions to lambda calculus have been investigated, e.g. [5, 6, 10, 18, 21, 22, 30]. In all of those approaches, the language chosen to represent the quantum state are vectors in a Hilbert space. However, an alternative formulation of quantum mechanics can be made using density matrices. Density matrices provide a way to describe a quantum system in which the state is not fully known. More precisely, density matrices describe quantum systems in a mixed state, that is, a statistical set of several quantum states. All the postulates of quantum mechanics can be described in such a formalism, and hence, also quantum computing can be done using density matrices.

The first postulate states that a quantum system can be fully described by a density matrix ρ , which is a positive operator with trace (tr) one. If a system is in state ρ_i with probability p_i , then the density matrix of the system is $\sum_i p_i \rho_i$. The second postulate states that the evolution of a quantum system ρ is described with a unitary operator U by $U\rho U^\dagger$, where U^\dagger is the adjoint operator of U . The third postulate states that the measurement is described by a set of measurement operators $\{\pi_i\}_i$ with $\sum_i \pi_i^\dagger \pi_i = \mathbb{1}$, so that the output of the measurement is i , with probability $\text{tr}(\pi_i^\dagger \pi_i \rho)$, leaving the state of the system

* Supported by projects STIC-AmSud 16STIC05 FoQCoSS, PICT 2015-1208 and the Laboratoire International Associé “INFINIS”.

as $\frac{\pi_i \rho \pi_i^\dagger}{\text{tr}(\pi_i^\dagger \pi_i \rho)}$. The fourth postulate states that from two systems ρ and ρ' , the composed one can be described by the tensor product of those $\rho \otimes \rho'$.

Naturally, if we want to use the output of a measurement as a condition in the classical control, we need to know that output. However, density matrices can still be used as a way to compare processes before running them. For example the process of tossing a coin, and according to its result, applying Z or not to a balanced superposition, and the process of tossing a coin and not looking at its result, may look quite different in most quantum programming languages. Yet both processes output the same density matrix, and so they are indistinguishable.

In [19], Selinger introduced a language of quantum flow charts, and an interpretation of his language into a CPO of density matrices. After this paper, the language of density matrices has been widely used in quantum programming, e.g. [9, 13, 14, 24, 27]. Indeed, the book “Foundations of Quantum Programming” [26] is entirely written in the language of density matrices. Yet, as far as we know, no lambda calculus for density matrix have been proposed.

Apart from the distinction of languages by how they treat the quantum states (vectors in a Hilbert space or density matrices), we also can distinguish the languages on how the control is considered: either quantumly or classically. The idea of quantum data / classical control stated by Selinger in [19] induced a quantum lambda calculus in this paradigm [21]. Later, this calculus was the base to construct the programming language Quipper [15], an embedded, scalable, functional programming language for quantum computing. The concept of quantum data / classical control declares that quantum computers will run in a specialized device attached to a classical computer, and it is the classical computer which will instruct the quantum computer what operations to perform over which qubits, and then read the classical result after a measurement. It is a direct consequence from the observation that quantum circuits are classical (i.e. one cannot superpose circuits or measure them). Several studies have been done under this paradigm, e.g. [2, 15, 18, 21, 30].

Dually to the quantum data / classical control paradigm, there is what we can call the quantum data and control paradigm. The idea is to provide a computational definition of the notions of vector space and bilinear functions. In the realm of quantum walks, quantum control is not uncommon (e.g. [1, 3]). Also, several high-level languages on quantum control have been proposed in the past (e.g. [2, 8, 28, 29]), however, up to now, no complete lambda-calculus with quantum control have been proposed. We benefit, though, from the long line of works in this direction [4–7, 12].

In this paper, we propose a quantum extension to the lambda calculus, λ_ρ , in the quantum data / classical control paradigm, where the quantum data is given by density matrices, as first suggested by Selinger’s interpretation of quantum flow charts [19]. Then, we propose a modification of such a calculus, called λ_ρ° , in which we generalise the density matrices to the classical control: That is, after a measurement, we take all the possible outcomes in a kind of generalised density matrix of arbitrary terms. The control does not become quantum, since it is not possible to superpose programs in the quantum sense. However, we consider

the density matrix of the mixed state of programs arising from a measurement. Therefore, this can be considered as a kind of probabilistic control, or even another way, perhaps weaker, of quantum control.

Outline of the Paper. In Section 2 we introduce the typed calculus λ_ρ , which manipulates density matrices, and we give two interpretations of the calculus. One where the terms are interpreted into a generalisation of mixed states, and another where the terms are interpreted into density matrices. Then we prove some properties of those interpretations. In Section 3 we introduce a modification of λ_ρ , called λ_ρ° , where the output of a measurement produce a sum with all the possible outputs. We then extend the interpretation of λ_ρ to accommodate λ_ρ° , and prove its basic properties. In Section 4 we prove the Subject Reduction (Theorem 4.4) and Progress (Theorem 4.7) properties for both calculi. In Section 5 we give two interesting examples, in both calculi. Finally, in Section 6, we conclude and discuss some future work.

2 Classical-control calculus with probabilistic rewriting

2.1 Definitions

The grammar of terms, given in Table 1, have been divided in three categories.

1. Standard lambda calculus terms: Variables from a set `Vars`, abstractions and applications.
2. The four postulates of quantum mechanics, with the measurement postulate restricted to measurements in the computational basis¹: ρ^n to represent the density matrix of a quantum system. $U^n t$ to describe its evolution. $\pi^n t$ to measure it. $t \otimes t$ to describe the density matrix of a composite system (that is, a non entangled system composed of two subsystems).
3. Two constructions for the classical control: a pair (b^m, ρ^n) , where b^m is the output of a measurement in the computational basis and ρ^n is the resulting density matrix, and the conditional `letcase` construction reading the output of the measurement.

The rewrite system, given in Table 2, is described by the relation \longrightarrow_p , which is a probabilistic relation where p is the probability of occurrence. If U^m is applied to ρ^n , with $m \leq n$, we write $\overline{U^m}$ for $U^m \otimes I^{n-m}$. Similarly, we write $\overline{\pi^m}$ when we apply this measurement operator to ρ^n for $\{\pi_0 \otimes I^{n-m}, \dots, \pi_{2^m-1} \otimes I^{n-m}\}$. If the unitary U^m needs to be applied, for example, to the last m qubits of ρ^n instead of the first m , we will need to use the unitary transformation $\overline{I^{n-m} \otimes U^m}$ instead. And if it is applied to the qubits k to $k+m$, then, we can use $\overline{I^{k-1} \otimes U^m}$.

¹ A generalisation to any arbitrary measurement can be considered in a future, however, for the sake of simplicity in the classical control, we consider only measurements in the computational basis, which is a common practice in quantum lambda calculi [10, 16, 18, 20, 21, 30].

$(\lambda x.t)r \longrightarrow_1 t[r/x]$			
$U^m \rho^n \longrightarrow_1 \rho'^n$	with $\rho'^n = \overline{U^m} \rho^n \overline{U^m}^\dagger$		
$\pi^m \rho^n \longrightarrow_{p_i} (i, \rho_i^n)$	with $\begin{cases} p_i = \text{tr}(\overline{\pi_i}^\dagger \pi_i \rho^n) \\ \rho_i^n = \frac{\overline{\pi_i} \rho^n \pi_i^\dagger}{p_i} \end{cases}$		
$\rho \otimes \rho' \longrightarrow_1 \rho''$	with $\rho'' = \rho \otimes \rho'$		
$\text{letcase } x = (b^m, \rho^n) \text{ in } \{t_0, \dots, t_{2^m-1}\} \longrightarrow_1 t_{b^m}[\rho^n/x]$			
$\frac{t \longrightarrow_p r}{\lambda x.t \longrightarrow_p \lambda x.r}$	$\frac{t \longrightarrow_p r}{ts \longrightarrow_p rs}$	$\frac{t \longrightarrow_p r}{st \longrightarrow_p sr}$	$\frac{t \longrightarrow_p r}{U^n t \longrightarrow_p U^n r}$
$\frac{t \longrightarrow_p r}{\pi^n t \longrightarrow_p \pi^n r}$	$\frac{t \longrightarrow_p r}{t \otimes s \longrightarrow_p r \otimes s}$	$\frac{t \longrightarrow_p r}{s \otimes t \longrightarrow_p s \otimes r}$	
$\frac{t \longrightarrow_p r}{\text{letcase } x = t \text{ in } \{s_0, \dots, s_n\} \longrightarrow_p \text{letcase } x = r \text{ in } \{s_0, \dots, s_n\}}$			

Table 2: Rewrite system for λ_ρ .

$\llbracket \cdot \rrbracket$, is a more fine-grained interpretation, interpreting terms into a generalisation of mixed states. In particular, we want $\llbracket \pi^n \rho^n \rrbracket = \left\{ \left(\text{tr}(\overline{\pi_i}^\dagger \pi_i \rho^n), \frac{\overline{\pi_i} \rho^n \pi_i^\dagger}{\text{tr}(\overline{\pi_i}^\dagger \pi_i \rho^n)} \right) \right\}_i$, while $\llbracket \pi^n \rho \rrbracket = \sum_i \pi_i \rho^n \pi_i^\dagger$. However, since the `letcase` construction needs also to distinguish each possible result of a measurement, we will carry those results in the interpretation $\llbracket \cdot \rrbracket$, making it a set of triplets instead of a set of tuples.

Let $\mathbb{N}^\varepsilon = \mathbb{N}_0 \cup \{\varepsilon\}$, so terms are interpreted into sets of triplets (p, b, e) with $p \in \mathbb{R}_+^{\leq 1}$, representing the probability, $b \in \mathbb{N}^\varepsilon$, representing the output of a measurement if it occurred, and $e \in \llbracket A \rrbracket$ for some type A and an interpretation $\llbracket \cdot \rrbracket$ on types yet to define. In addition, we consider that the sets $\{\dots, (p, b, e), (q, b, e), \dots\}$ and $\{\dots, (p+q, b, e), \dots\}$ are equal. Finally, we define the weight function as $w(\{(p_i, b_i, e_i)\}_i) = \sum_i p_i$. We are interested in sets S such that $w(S) = 1$.

The interpretation of types is given in Table 4. \mathcal{D}_n is the set of density matrices of n -qubits, that is $\mathcal{D}_n = \{\rho \mid \rho \in \mathcal{M}_{2^n \times 2^n}^+ \text{ such that } \text{tr}(\rho) = 1\}$, where $\mathcal{M}_{2^n \times 2^n}^+$ is the set of positive matrices of size $2^n \times 2^n$. $P(b, A)$ is the following property: $[A = (m, n) \implies b \neq \varepsilon]$. We also establish the convention that $P(\{(p_i, b_i, e_i)\}_i, A) = \bigwedge_i P(b_i, A)$. Finally, we write $\text{trd}(S) = \{e \mid (p, b, e) \in S\}$.

Let $E = \bigcup_{A \in \text{Types}} \llbracket A \rrbracket$. We denote by θ to a valuation $\text{Vars} \rightarrow \mathbb{N}^\varepsilon \times E$. Then, we define the interpretation of terms with respect to a given valuation θ in Table 5.

Definition 2.2. $\theta \models \Gamma$ if and only if, for all $x : A \in \Gamma$, $\theta(x) = (b, e)$ with $e \in \llbracket A \rrbracket$, and $P(b, A)$.

Lemma 2.3 states that a term with type (m, n) will be the result of a measurement, and hence, its interpretation will carry the results $b_i \neq \varepsilon$.

$A := n \mid (m, n) \mid A \multimap A$	
where $m \leq n \in \mathbb{N}$.	
$\frac{}{\Gamma, x : A \vdash x : A} \text{ax}$	$\frac{\Gamma, x : A \vdash t : B}{\Gamma \vdash \lambda x.t : A \multimap B} \multimap_i$
	$\frac{\Gamma \vdash t : A \multimap B \quad \Delta \vdash r : A}{\Gamma, \Delta \vdash tr : B} \multimap_e$
$\frac{}{\Gamma \vdash \rho^n : n} \text{ax}_\rho$	$\frac{\Gamma \vdash t : n}{\Gamma \vdash U^m t : n} \text{u}$
	$\frac{\Gamma \vdash t : n}{\Gamma \vdash \pi^m t : (m, n)} \text{m}$
	$\frac{\Gamma \vdash t : n \quad \Delta \vdash r : m}{\Gamma, \Delta \vdash t \otimes r : n + m} \otimes$
$\frac{}{\Gamma \vdash (b^m, \rho^n) : (m, n)} \text{ax}_{\text{am}}$	$\frac{x : n \vdash t_0 : A \quad \dots \quad x : n \vdash t_{2^m-1} : A \quad \Gamma \vdash r : (m, n)}{\Gamma \vdash \text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^m-1}\} : A} \text{lc}$

Table 3: Type system for λ_ρ .

$\llbracket n \rrbracket = \mathcal{D}_n$
$\llbracket (m, n) \rrbracket = \mathcal{D}_n$
$\llbracket A \multimap B \rrbracket = \{f \mid \forall e \in \llbracket A \rrbracket, \forall b \in \mathbb{N}^\varepsilon \text{ s.t. } P(b, A),$
$\text{trd}(f(b, e)) \subseteq \llbracket B \rrbracket, w(f(b, e)) = 1 \text{ and } P(f(b, e), B)\}$

Table 4: Interpretation of types

Lemma 2.3. *Let $\Gamma \vdash t : (m, n)$, $\theta \models \Gamma$, and $\llbracket t \rrbracket_\theta$ be well-defined. Then, $\llbracket t \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$ with $b_i \neq \varepsilon$ and $e_i \in \mathcal{D}_n$.*

Proof. By induction on the type derivation (cf. Appendix A.1). □

Lemma 2.4 states that the interpretation of a typed term is well-defined.

Lemma 2.4. *If $\Gamma \vdash t : A$ and $\theta \models \Gamma$, then $w(\llbracket t \rrbracket_\theta) = 1$, and $\text{trd}(\llbracket t \rrbracket_\theta) \subseteq \llbracket A \rrbracket$.*

Proof. By induction on t (cf. Appendix A.2). □

Since the interpretation $\llbracket \cdot \rrbracket$ of a term is morally a mixed state, the interpretation $\langle \cdot \rangle$, which should be the density matrix of such a state, is naturally defined using the interpretation $\llbracket \cdot \rrbracket$.

Definition 2.5. *Let $e \in \llbracket A \rrbracket$ for some A , θ a valuation, and t be a term such that $\llbracket t \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$. We state the convention that $(\mathbf{b}, \mathbf{e}) \mapsto \sum_i p_i e_i = \sum_i p_i ((\mathbf{b}, \mathbf{e}) \mapsto e_i)$. We define $\langle e \rangle$ and $\langle t \rangle_\theta$ by mutual recursion as follows:*

$$\begin{aligned} \langle \rho \rangle &= \rho \\ \langle (\mathbf{b}, \mathbf{e}) \mapsto \llbracket t \rrbracket_{\theta, x=(\mathbf{b}, \mathbf{e})} \rangle &= (\mathbf{b}, \mathbf{e}) \mapsto \langle t \rangle_{\theta, x=(\mathbf{b}, \mathbf{e})} \\ \langle t \rangle_\theta &= \sum_i p_i \langle e_i \rangle \end{aligned}$$

$\begin{aligned} \llbracket x \rrbracket_\theta &= \{(1, b, e)\} \text{ where } \theta(x) = (b, e) \\ \llbracket \lambda x. t \rrbracket_\theta &= \{(1, \varepsilon, (\mathbf{b}, \mathbf{e}) \mapsto \llbracket t \rrbracket_{\theta, x=(\mathbf{b}, \mathbf{e})})\} \\ \llbracket tr \rrbracket_\theta &= \{(p_i q_j h_{ijk}, b''_{ijk}, g_{ijk}) \mid \llbracket r \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i, \\ &\quad \llbracket t \rrbracket_\theta = \{(q_j, b'_j, f_j)\}_j \text{ and} \\ &\quad f_j(b_i, e_i) = \{(h_{ijk}, b''_{ijk}, g_{ijk})\}_k\} \\ \llbracket \rho^n \rrbracket_\theta &= \{(1, \varepsilon, \rho^n)\} \\ \llbracket U^n t \rrbracket_\theta &= \{(p_i, \varepsilon, \overline{U^n \rho_i \overline{U^n}^\dagger}) \mid \llbracket t \rrbracket_\theta = \{(p_i, b_i, \rho_i)\}_i\} \\ \llbracket \pi^m t \rrbracket_\theta &= \{(p_j \text{tr}(\overline{\pi_i}^\dagger \overline{\pi_i} \rho_j), i, \frac{\overline{\pi_i} \rho_j \overline{\pi_i}^\dagger}{\text{tr}(\overline{\pi_i}^\dagger \overline{\pi_i} \rho_j)}) \mid \llbracket t \rrbracket_\theta = \{(p_j, b_j, \rho_j)\}_j\} \\ \llbracket t \otimes r \rrbracket_\theta &= \{(p_i q_j, \varepsilon, \rho_i \otimes \rho'_j) \mid \llbracket t \rrbracket_\theta = \{(p_i, b_i, \rho_i)\}_i \text{ and} \\ &\quad \llbracket r \rrbracket_\theta = \{(q_j, b'_j, \rho'_j)\}_j\} \\ \llbracket (b^m, \rho^n) \rrbracket_\theta &= \{(1, b^m, \rho^n)\} \\ \llbracket \text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^m-1}\} \rrbracket_\theta &= \{(p_i q_{ij}, b'_{ij}, e_{ij}) \mid \\ &\quad \llbracket r \rrbracket_\theta = \{(p_i, b_i, \rho_i)\}_i \text{ and} \\ &\quad \llbracket t_{b_i} \rrbracket_{\theta, x=(\varepsilon, \rho_i)} = \{(q_{ij}, b'_{ij}, e_{ij})\}_j\} \end{aligned}$

Table 5: Interpretation of terms

Lemma 2.6 (Substitution). *Let $\llbracket r \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$, then*

$$\llbracket t[r/x] \rrbracket_\theta = \sum_i p_i \llbracket t \rrbracket_{\theta, x=(b_i, e_i)}$$

Proof. By induction on t . However, we enforce the hypothesis by also showing that if $\llbracket t \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, b'_{ij}, \rho_{ij})\}_j$, then $\llbracket t[r/x] \rrbracket_\theta = \{(p_i q_{ij}, b'_{ij}, \rho_{ij})\}_{ij}$. We use five auxiliary results (cf. Appendix A.3). \square

Theorem 2.7 shows how the interpretation $\llbracket \cdot \rrbracket$ of a term relates to all its reducts.

Theorem 2.7. *If $\Gamma \vdash t : A$, $\theta \models \Gamma$ and $t \longrightarrow_{p_i} r_i$, with $\sum_i p_i = 1$, then $\llbracket t \rrbracket_\theta = \sum_i p_i \llbracket r_i \rrbracket_\theta$.*

Proof. By induction on the relation \longrightarrow_p (cf. Appendix A.4). \square

3 Probabilistic-control calculus with no-probabilistic rewriting

3.1 Definitions

In the previous sections we have presented an extension to lambda calculus to handle density matrices. The calculus could have been done using just vectors,

$t := x \mid \lambda x.t \mid tt$	(Standard lambda calculus)
$\mid \rho^n \mid U^n t \mid \pi^n t \mid t \otimes t$	(Quantum postulates)
$\mid \sum_{i=1}^n p_i t_i \mid \text{letcase}^\circ x = r \text{ in } \{t, \dots, t\}$	(Probabilistic control)

where $p_i \in (0, 1]$, $\sum_{i=1}^n p_i = 1$, and \sum is considered modulo associativity and commutativity (cf. for example [6]).

Table 6: Grammar of terms of λ_ρ° .

because the output of a measurement is not given by the density matrix of the produced mixed state, instead each possible output is given with its probability. In this section, we give an alternative presentation, named λ_ρ° , where we can make the most of the density matrices setting.

In Table 6 we give a modified grammar of terms for λ_ρ° in order to allow for linear combination of terms. We follow the grammar of the algebraic lambda-calculi [6, 7, 23].

The new rewrite system is given by the non-probabilistic relation \rightsquigarrow , described in Table 7. The measurement does not reduce, unless it is the parameter of a letcase° . Therefore, if only a measurement is needed, we can encode it as:

$$\text{letcase}^\circ x = \pi^m \rho^n \text{ in } \{x, \dots, x\} \rightsquigarrow \sum_i p_i \rho_i^n \rightsquigarrow \rho'$$

where $\rho' = \sum_i \overline{\pi_i} \rho^n \overline{\pi_i}^\dagger$. The rationale is that in this version of the calculus, we can never look at the result of a measurement. It will always produce the density matrix of a mixed-state. As a consequence, the letcase° constructor rewrites to a sum of terms.

The type system for λ_ρ° , including the grammar of types and the derivation rules, is given in Table 8. The only difference with the type system of λ_ρ (cf. Table 3), is that rule ax_{am} is no longer needed, since (b^m, ρ^n) is not in the grammar of λ_ρ° , and there is a new rule (+) typing the generalised mixed states. We use the symbol \Vdash for λ_ρ° to distinguish it from \vdash used in λ_ρ .

Example 3.1. The teleportation algorithm expressed in λ_ρ in Example 2.1, is analogous for λ_ρ° , only changing the term letcase by letcase° . Also, the type derivation is analogous. The difference is in the reduction. Let ρ be the density matrix of a given quantum state (mixed or pure). Let

$$\rho_0^3 = \rho \otimes \beta_{00}, \quad \rho_1^3 = (\text{Cnot} \otimes I) \rho_0^3, \quad \text{and} \quad \rho_2^3 = (\text{H} \otimes I \otimes I) \rho_1^3$$

The trace of the teleportation of ρ in λ_ρ is the following:

$$\begin{aligned} & (\lambda x. \text{letcase } y = \pi^2(\text{H}^1(\text{Cnot}^2(x \otimes \beta_{00}))) \text{ in } \{y, Z_3 y, X_3 y, Z_3 X_3 y\}) \rho \\ & \longrightarrow_1 \text{letcase } y = \pi^2(\text{H}^1(\text{Cnot}^2(\rho \otimes \beta_{00}))) \text{ in } \{y, Z_3 y, X_3 y, Z_3 X_3 y\} \end{aligned}$$

$(\lambda x.t)r \rightsquigarrow t[r/x]$			
$\text{letcase}^\circ x = \pi^m \rho^n \text{ in } \{t_0, \dots, t_{2^m-1}\} \rightsquigarrow \sum_i p_i t_i [\rho_i^n / x]$	with $\begin{cases} \rho_i^n = \frac{\overline{\pi_i} \rho^n \overline{\pi_i}^\dagger}{p_i} \\ p_i = \text{tr}(\overline{\pi_i}^\dagger \overline{\pi_i} \rho^n) \end{cases}$		
$U^m \rho^n \rightsquigarrow \rho'^m$	with $\overline{U^m} \rho^n \overline{U^m}^\dagger = \rho'^m$		
$\rho \otimes \rho' \rightsquigarrow \rho''$	with $\rho'' = \rho \otimes \rho'$		
$\sum_i p_i \rho_i \rightsquigarrow \rho'$	with $\rho' = \sum_i p_i \rho_i$		
$\sum_i p_i t \rightsquigarrow t$			
$(\sum_i p_i t_i)r \rightsquigarrow \sum_i p_i (t_i r)$			
$\frac{t \rightsquigarrow r}{\lambda x.t \rightsquigarrow \lambda x.r}$	$\frac{t \rightsquigarrow r}{ts \rightsquigarrow rs}$	$\frac{t \rightsquigarrow r}{st \rightsquigarrow sr}$	$\frac{t \rightsquigarrow r}{U^n t \rightsquigarrow U^n r}$
$\frac{t \rightsquigarrow r}{\pi^n t \rightsquigarrow \pi^n r}$	$\frac{t \rightsquigarrow r}{t \otimes s \rightsquigarrow r \otimes s}$	$\frac{t \rightsquigarrow r}{s \otimes t \rightsquigarrow s \otimes r}$	
$\frac{t_j \rightsquigarrow r_j}{\sum_{i=1}^n p_i t_i \rightsquigarrow \sum_{i=1}^n p_i r_i} \quad (\forall i \neq j, t_i = r_j)$			
$\frac{t \rightsquigarrow r}{\text{letcase}^\circ x = t \text{ in } \{s_0, \dots, s_{2^m-1}\} \rightsquigarrow \text{letcase}^\circ x = r \text{ in } \{s_0, \dots, s_{2^m-1}\}}$			

Table 7: Rewrite system of λ_ρ° .

$$\begin{aligned}
 &\longrightarrow_1 \text{letcase } y = \pi^2(\text{H}^1(\text{Cnot}^2 \rho_0^3)) \text{ in } \{y, Z_3 y, X_3 y, Z_3 X_3 y\} \\
 &\longrightarrow_1 \text{letcase } y = \pi^2(\text{H}^1 \rho_1^3) \text{ in } \{y, Z_3 y, X_3 y, Z_3 X_3 y\} \\
 &\longrightarrow_1 \text{letcase } y = \pi^2 \rho_2^3 \text{ in } \{y, Z_3 y, X_3 y, Z_3 X_3 y\}
 \end{aligned} \tag{1}$$

From (1), there are four possible reductions. For $i = 0, 1, 2, 3$, let $p_i = \text{tr}(\overline{\pi_i}^\dagger \overline{\pi_i} \rho_2^3)$ and $\rho_{3i}^3 = \frac{\overline{\pi_i} \rho_2^3 \overline{\pi_i}^\dagger}{p_i}$. Then,

- (1) \longrightarrow_{p_0} letcase $y = (0, \rho_{30}^3)$ in $\{y, Z_3 y, X_3 y, Z_3 X_3 y\} \longrightarrow_1 \rho_{30}^3 = \rho$.
- (1) \longrightarrow_{p_1} letcase $y = (1, \rho_{31}^3)$ in $\{y, Z_3 y, X_3 y, Z_3 X_3 y\} \longrightarrow_1 Z_3 \rho_{31}^3 \longrightarrow_1 \rho$.
- (1) \longrightarrow_{p_2} letcase $y = (2, \rho_{32}^3)$ in $\{y, Z_3 y, X_3 y, Z_3 X_3 y\} \longrightarrow_1 X_3 \rho_{32}^3 \longrightarrow_1 \rho$.
- (1) \longrightarrow_{p_3} letcase $y = (3, \rho_{33}^3)$ in $\{y, Z_3 y, X_3 y, Z_3 X_3 y\} \longrightarrow_1 Z_3 X_3 \rho_{33}^3 \longrightarrow_1 \rho$.

On the other hand, the trace of the same term, in λ_ρ° , would be analogous until (1), just using \rightsquigarrow instead of \longrightarrow_1 . Then:

$$(1) \rightsquigarrow p_0 \rho + p_1 Z_3 \rho_{31}^3 + p_2 X_3 \rho_{32}^3 + p_3 Z_3 X_3 \rho_{33}^3 \rightsquigarrow^* \sum_{i=0}^3 p_i \rho_{3i}^3 \rightsquigarrow \left(\sum_{i=0}^3 p_i \right) \rho \rightsquigarrow \rho$$

$A := n \mid (m, n) \mid A \multimap A$	
where $m \leq n \in \mathbb{N}$.	
$\frac{}{\Gamma, x : A \Vdash x : A}$ ax	$\frac{\Gamma, x : A \Vdash t : B}{\Gamma \Vdash \lambda x.t : A \multimap B}$ \multimap_i
	$\frac{\Gamma \Vdash t : A \multimap B \quad \Delta \Vdash r : A}{\Gamma, \Delta \Vdash tr : B}$ \multimap_e
$\frac{}{\Gamma \Vdash \rho^n : n}$ ax $_\rho$	$\frac{\Gamma \Vdash t : n}{\Gamma \Vdash U^m t : n}$ u
	$\frac{\Gamma \Vdash t : n}{\Gamma \Vdash \pi^m t : (m, n)}$ m
	$\frac{\Gamma \Vdash t : n \quad \Delta \Vdash r : m}{\Gamma, \Delta \Vdash t \otimes r : n + m}$ \otimes
$\frac{x : n \Vdash t_0 : A \quad \dots \quad x : n \Vdash t_{2^m-1} : A \quad \Gamma \Vdash r : (m, n)}{\Gamma \Vdash \text{letcase}^\circ x = r \text{ in } \{t_0, \dots, t_{2^m-1}\} : A}$ lc	
$\frac{\Gamma \Vdash t_1 : A \quad \dots \quad \Gamma \Vdash t_n : A \quad \sum_{i=1}^n p_i = 1}{\Gamma \Vdash \sum_{i=1}^n p_i t_i : A}$ +	

Table 8: Type system for λ_ρ° .

3.2 Interpretation

The interpretation of λ_ρ given in Section 2.2 considers already all the traces. Hence, the interpretation of λ_ρ° can be obtained from a small modification of it. We only need to drop the interpretation of the term that no longer exists, (b^m, ρ^n) , and add an interpretation for the new term $\sum_i p_i t_i$ as follows:

$$\llbracket \sum_i p_i t_i \rrbracket_\theta = \{(p_i q_{ij}, b_{ij}, e_{ij}) \mid \llbracket t_i \rrbracket_\theta = \{(q_{ij}, b_{ij}, e_{ij})\}_j\}$$

The interpretation of letcase° is the same as the interpretation of letcase .

Then, we can prove a theorem (Theorem 3.4) for λ_ρ° analogous to Theorem 2.7.

We need the following auxiliary Lemmas.

Lemma 3.2. *If $\Gamma \Vdash t : A$ and $\theta \models \Gamma$, then $\llbracket \sum_i p_i t_i \rrbracket_\theta = \sum_i p_i \llbracket t_i \rrbracket_\theta$*

Proof. Let $\llbracket t_i \rrbracket_\theta = \{(q_{ij}, b_{ij}, e_{ij})\}_j$. Then, we have $\llbracket \sum_i p_i t_i \rrbracket_\theta = \sum_{ij} p_i q_{ij} e_{ij} = \sum_i p_i \sum_j q_{ij} e_{ij} = \sum_i p_i \llbracket t_i \rrbracket_\theta$. \square

Lemma 3.3. *Let $\llbracket r \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$, then $\llbracket t[r/x] \rrbracket_\theta = \sum_i p_i \llbracket t \rrbracket_{\theta, x=(b_i, e_i)}$.*

Proof. The proof of the analogous Lemma 2.6 in λ_ρ follows by induction on t . Since the definition of $\llbracket \cdot \rrbracket$ is the same for λ_ρ than for λ_ρ° , we only need to check the only term of λ_ρ° which is not a term of λ_ρ : $\sum_j q_j t_j$. Using Lemma 3.2, and the induction hypothesis, we have $\llbracket (\sum_j q_j t_j)[r/x] \rrbracket_\theta = \llbracket \sum_j q_j (t_j[r/x]) \rrbracket_\theta = \sum_j q_j \llbracket t_j[r/x] \rrbracket_\theta = \sum_j q_j \sum_i p_i \llbracket t_j \rrbracket_{\theta, x=(b_i, e_i)} = \sum_i p_i \llbracket \sum_j q_j t_j \rrbracket_{\theta, x=(b_i, e_i)}$. \square

Theorem 3.4. *If $\Gamma \Vdash t : A$, $\theta \models \Gamma$ and $t \rightsquigarrow r$, then $\llbracket t \rrbracket_\theta = \llbracket r \rrbracket_\theta$.*

Proof. By induction on the relation \rightsquigarrow . Rules $(\lambda x.t)r \rightsquigarrow t[r/x]$, $U^m \rho^n \rightsquigarrow \rho'$ and $\rho \otimes \rho' \rightsquigarrow \rho''$ are also valid rules for relation \rightarrow_1 , and hence the proof of these cases are the same than in Theorem 2.7. \square

4 Subject Reduction and Progress

In this section we state and prove the subject reduction and progress properties on both, λ_ρ and λ_ρ° (Theorems 4.4 and 4.7 respectively).

Lemma 4.1 (Weakening).

- If $\Gamma \vdash t : A$ and $x \notin FV(t)$, then $\Gamma, x : B \vdash t : A$.
- If $\Gamma \Vdash t : A$ and $x \notin FV(t)$, then $\Gamma, x : B \Vdash t : A$.

Proof. By a straightforward induction on the derivation of $\Gamma \vdash t : A$ and on $\Gamma \Vdash t : A$. \square

Lemma 4.2 (Strengthening).

- If $\Gamma, x : A \vdash t : B$ and $x \notin FV(t)$, then $\Gamma \vdash t : B$.
- If $\Gamma, x : A \Vdash t : B$ and $x \notin FV(t)$, then $\Gamma \Vdash t : B$.

Proof. By a straightforward induction on the derivation of $\Gamma, x : A \vdash t : B$ and $\Gamma, x : A \Vdash t : B$. \square

Lemma 4.3 (Substitution).

- If $\Gamma, x : A \vdash t : B$ and $\Delta \vdash r : A$ then $\Gamma, \Delta \vdash t[r/x] : B$.
- If $\Gamma, x : A \Vdash t : B$ and $\Delta \Vdash r : A$ then $\Gamma, \Delta \Vdash t[r/x] : B$.

Proof. By induction on t (cf. Appendix C.1). \square

Theorem 4.4 (Subject reduction).

- If $\Gamma \vdash t : A$, and $t \longrightarrow_p r$, then $\Gamma \vdash r : A$.
- If $\Gamma \Vdash t : A$, and $t \rightsquigarrow r$, then $\Gamma \Vdash r : A$.

Proof. By induction on the relations \longrightarrow_p and \rightsquigarrow (cf. Appendix C.2). \square

Definition 4.5 (Values).

- A value in λ_ρ is a term v defined by the following grammar:

$$\begin{aligned} w &:= x \mid \lambda x.v \mid w \otimes w \\ v &:= w \mid \rho^n \mid (b^m, \rho^n) \end{aligned}$$

- A value in λ_ρ° (or value°) is a term v defined by the following grammar:

$$\begin{aligned} w &:= x \mid \lambda x.v \mid w \otimes w \mid \sum_i p_i w_i \text{ with } w_i \neq w_j \text{ if } i \neq j \\ v &:= w \mid \rho^n \end{aligned}$$

Lemma 4.6.

1. If v is a value, then there is no t such that $v \longrightarrow_p t$ for any p .
2. If v is a value° , then there is no t such that $v \rightsquigarrow t$.

Proof. By induction on v in both cases (cf. Appendix C.3). \square

Theorem 4.7 (Progress).

1. If $\Gamma \vdash t : A$, then either t is a value or there exist n, p_1, \dots, p_n , and r_1, \dots, r_n such that $t \xrightarrow{p_i} r_i$.
2. If $\Gamma \Vdash t : A$ and $A \neq (m, n)$, then either t is a value^o or there exists r such that $t \rightsquigarrow r$.

Proof. We relax the hypotheses and prove the theorem for open terms as well. That is:

1. If $\Gamma \vdash t : A$, then either t is a value, there exist n, p_1, \dots, p_n , and r_1, \dots, r_n such that $t \xrightarrow{p_i} r_i$, or t contains a free variable, and t does not rewrite.
2. If $\Gamma \Vdash t : A$, then either t is a value^o, there exists r such that $t \rightsquigarrow r$, or t contains a free variable, and t does not rewrite.

In both cases, we proceed by induction on the type derivation (cf. Appendix C.4). \square

5 Examples

Example 5.1. Consider the following experiment: Measure some ρ and then toss a coin to decide whether to return the result of the measurement, or to give the result of tossing a new coin.

The experiment in λ_ρ . This experiment can be implemented in λ_ρ as follows:

$$\begin{aligned} & (\text{letcase } y = \pi^1|+\rangle\langle+| \text{ in } \{\lambda x.x, \lambda x.\text{letcase } w = \pi^1|+\rangle\langle+| \text{ in } \{w, w\}\}) \\ & \qquad \qquad \qquad (\text{letcase } z = \pi^1\rho \text{ in } \{z, z\}) \end{aligned}$$

Trace: We give one possible probabilistic trace. Notice that, by using different strategies, we would get different derivation trees. We will not prove confluence in this setting (cf. [11] for a full discussion on the notion of confluence of probabilistic rewrite systems), but we conjecture that such a property is met.

We use the following notations:

$$\begin{aligned} s &= \pi^1|+\rangle\langle+| \\ t_0 &= \lambda x.x \\ t_1 &= \lambda x.\text{letcase } w = s \text{ in } \{w, w\} \\ \rho &= \frac{3}{4}|0\rangle\langle 0| + \frac{\sqrt{3}}{4}|0\rangle\langle 1| + \frac{\sqrt{3}}{4}|1\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1| \\ r_1 &= \text{letcase } y = s \text{ in } \{t_0, t_1\} \\ r_2 &= \text{letcase } z = \pi^1\rho \text{ in } \{z, z\} \\ l_x &= \text{letcase } y = (x, |x\rangle\langle x|) \text{ in } \{y, y\} \text{ with } x = 0, 1 \\ r_1^x &= \text{letcase } y = (x, |x\rangle\langle x|) \text{ in } \{t_0, t_1\} \text{ with } x = 0, 1 \end{aligned}$$

Using this notation, the probabilistic trace is given by the tree in Table 9. Therefore, with probability $\frac{5}{8}$ we get $|0\rangle\langle 0|$, and with probability $\frac{3}{8}$ we get $|1\rangle\langle 1|$. Thus, the density matrix of this mixed state is $\frac{5}{8}|0\rangle\langle 0| + \frac{3}{8}|1\rangle\langle 1|$.

$$\begin{aligned}
\llbracket t_1 \rrbracket_{y=(\varepsilon, |1\rangle\langle 1|)} &= \{(1, \varepsilon, (\mathbf{b}, \mathbf{e}) \mapsto \{(\frac{1}{2}, \varepsilon, |0\rangle\langle 0|), (\frac{1}{2}, \varepsilon, |1\rangle\langle 1|)\})\} \\
\llbracket r_1 \rrbracket_\emptyset &= \{(\frac{1}{2}, \varepsilon, (\mathbf{b}, \mathbf{e}) \mapsto \{(\frac{1}{2}, \varepsilon, |0\rangle\langle 0|), (\frac{1}{2}, \varepsilon, |1\rangle\langle 1|)\}), (\frac{1}{2}, \varepsilon, (\mathbf{b}, \mathbf{e}) \mapsto \{(1, \mathbf{b}, \mathbf{e})\})\} \\
\llbracket \pi^1 \rho \rrbracket_\emptyset &= \{(\frac{3}{4}, 0, |0\rangle\langle 0|), (\frac{1}{4}, 1, |1\rangle\langle 1|)\} \\
\llbracket r_2 \rrbracket_\emptyset &= \{(\frac{3}{4}, \varepsilon, |0\rangle\langle 0|), (\frac{1}{4}, \varepsilon, |1\rangle\langle 1|)\}
\end{aligned}$$

Then,

$$\begin{aligned}
\llbracket r_1 r_2 \rrbracket_\emptyset &= \{(\frac{3}{16}, \varepsilon, |0\rangle\langle 0|), (\frac{1}{16}, \varepsilon, |0\rangle\langle 0|), (\frac{3}{16}, \varepsilon, |1\rangle\langle 1|), \\
&\quad (\frac{1}{16}, \varepsilon, |1\rangle\langle 1|), (\frac{3}{8}, \varepsilon, |0\rangle\langle 0|), (\frac{1}{8}, \varepsilon, |1\rangle\langle 1|)\}
\end{aligned}$$

Hence,

$$\begin{aligned}
\langle r_1 r_2 \rangle_\emptyset &= \frac{3}{16}|0\rangle\langle 0| + \frac{1}{16}|0\rangle\langle 0| + \frac{3}{16}|1\rangle\langle 1| + \frac{1}{16}|1\rangle\langle 1| + \frac{3}{8}|0\rangle\langle 0| + \frac{1}{8}|1\rangle\langle 1| \\
&= \frac{5}{8}|0\rangle\langle 0| + \frac{3}{8}|1\rangle\langle 1|
\end{aligned}$$

The experiment in λ_ρ° . In λ_ρ° , the example becomes:

$$\begin{aligned}
t := (\text{letcase}^\circ y = \pi^1|+\rangle\langle +| \text{ in } \{\lambda x.x, \lambda x.\text{letcase}^\circ w = \pi^1|+\rangle\langle +| \text{ in } \{w, w\}\}) \\
\quad (\text{letcase}^\circ z = \pi^1\rho \text{ in } \{z, z\})
\end{aligned}$$

Trace: In this case the trace is not a tree, because the relation \rightsquigarrow is not probabilistic. We use the same ρ as before: $\frac{3}{4}|0\rangle\langle 0| + \frac{\sqrt{3}}{4}|1\rangle\langle 0| + \frac{\sqrt{3}}{4}|0\rangle\langle 1| + \frac{1}{4}|1\rangle\langle 1|$.

$$\begin{aligned}
t &\rightsquigarrow (\text{letcase}^\circ y = \pi^1|+\rangle\langle +| \text{ in } \{\lambda x.x, \lambda x.\text{letcase}^\circ w = \pi^1|+\rangle\langle +| \text{ in } \{w, w\}\}) \\
&\quad (\frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|) \\
&\rightsquigarrow (\frac{1}{2}\lambda x.x + \frac{1}{2}\lambda x.\text{letcase}^\circ w = \pi^1|+\rangle\langle +| \text{ in } \{w, w\})(\frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|) \\
&\rightsquigarrow (\frac{1}{2}\lambda x.x + \frac{1}{2}(\lambda x.\frac{1}{2}|0\rangle\langle 0| + \frac{1}{2}|1\rangle\langle 1|))(\frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|) \\
&\rightsquigarrow \frac{1}{2}((\lambda x.x)(\frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|)) \\
&\quad + \frac{1}{2}((\lambda x.\frac{1}{2}|0\rangle\langle 0| + \frac{1}{2}|1\rangle\langle 1|)(\frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|)) \\
&\rightsquigarrow \frac{1}{2}((\lambda x.x)(\frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|)) + \frac{1}{2}(\frac{1}{2}|0\rangle\langle 0| + \frac{1}{2}|1\rangle\langle 1|) \\
&\rightsquigarrow \frac{1}{2}(\frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|) + \frac{1}{2}(\frac{1}{2}|0\rangle\langle 0| + \frac{1}{2}|1\rangle\langle 1|)
\end{aligned}$$

$$\rightsquigarrow \frac{5}{8}|0\rangle\langle 0| + \frac{3}{8}|1\rangle\langle 1|$$

Typing and Interpretation: Since t does not contain sums, its typing is analogous to the term in λ_ρ , as well as the interpretation.

Example 5.2. In [17, p 371] there is an example of the freedom in the operator-sum representation by showing two quantum operators, which are actually the same. One is the process of tossing a coin and, according to its results, applying I or Z to a given qubit. The second is the process performing a projective measurement with unknown outcome to the same qubit. These operations can be encoded in λ_ρ by:

$$\begin{aligned} O_1 &= \lambda y.\text{letcase } x = \pi^1|+\rangle\langle +| \text{ in } \{y, Zy\} \\ O_2 &= \lambda y.\text{letcase } x = \pi^1y \text{ in } \{x, x\} \end{aligned}$$

with $\pi^1 = \{|0\rangle\langle 0|, |1\rangle\langle 1|\}$.

Let us apply those operators to the qubit $\rho = \frac{3}{4}|0\rangle\langle 0| + \frac{\sqrt{3}}{4}|0\rangle\langle 1| + \frac{\sqrt{3}}{4}|1\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|$. We can check that the terms $O_1\rho$ and $O_2\rho$ have different interpretations $\llbracket \cdot \rrbracket$. Let $\rho^- = Z\rho Z^\dagger$, then

$$\begin{aligned} \llbracket (\lambda y.\text{letcase } x = \pi^1|+\rangle\langle +| \text{ in } \{y, Zy\})\rho \rrbracket_\emptyset &= \left\{ \left(\frac{1}{2}, \varepsilon, \rho \right), \left(\frac{1}{2}, \varepsilon, \rho^- \right) \right\} \\ \llbracket (\lambda y.\text{letcase } x = \pi^1y \text{ in } \{x, x\})\rho \rrbracket_\emptyset &= \left\{ \left(\frac{3}{4}, \varepsilon, |0\rangle\langle 0| \right), \left(\frac{1}{4}, \varepsilon, |1\rangle\langle 1| \right) \right\} \end{aligned}$$

However, they have the same interpretation $\langle \cdot \rangle$.

$$\begin{aligned} &\langle (\lambda y.\text{letcase } x = \pi^1|+\rangle\langle +| \text{ in } \{y, Zy\})\rho \rangle_\emptyset \\ &= \frac{1}{2}\rho + \frac{1}{2}\rho^- \\ &= \frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1| \\ &= \langle (\lambda y.\text{letcase } x = \pi^1y \text{ in } \{x, x\})\rho \rangle_\emptyset \end{aligned}$$

The trace of $O_1\rho$ is given in Table 10, and the trace of $O_2\rho$ in Table 11. The first term produces ρ , with probability $\frac{1}{2}$, and ρ^- , with probability $\frac{1}{2}$, while the second term produces either $|0\rangle\langle 0|$ with probability $\frac{3}{4}$ or $|1\rangle\langle 1|$, with probability $\frac{1}{4}$.

However, if we encode the same terms in λ_ρ° , we can get both programs to produce the same density matrix:

$$\begin{aligned} O_1^\circ &= \lambda y.\text{letcase}^\circ x = \pi^1|+\rangle\langle +| \text{ in } \{y, Zy\} \\ O_2^\circ &= \lambda y.\text{letcase}^\circ x = \pi^1y \text{ in } \{x, x\} \end{aligned}$$




Table 10: Trace of the terms $O_1\rho$ from Example 5.2 in λ_ρ .

The traces of $O_1^\circ\rho$ and $O_2^\circ\rho$ are as follow:

$$\begin{array}{l}
 O_1^\circ\rho \\
 = (\lambda y.\text{letcase}^\circ x = \pi^1|+\rangle\langle+| \text{ in } \{y, Zy\})\rho \\
 \rightsquigarrow \text{letcase}^\circ x = \pi^1|+\rangle\langle+| \text{ in } \{\rho, Z\rho\} \\
 \rightsquigarrow (\frac{1}{2}\rho) + (\frac{1}{2}Z\rho) \\
 \rightsquigarrow (\frac{1}{2}\rho) + (\frac{1}{2}\rho^-) \\
 \rightsquigarrow \frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|
 \end{array}
 \left|
 \begin{array}{l}
 O_2^\circ\rho \\
 = (\lambda y.\text{letcase}^\circ x = \pi^1 y \text{ in } \{x, x\})\rho \\
 \rightsquigarrow \text{letcase}^\circ x = \pi^1 \rho \text{ in } \{x, x\} \\
 \rightsquigarrow (\frac{3}{4}|0\rangle\langle 0|) + (\frac{1}{4}|1\rangle\langle 1|) \\
 \rightsquigarrow \frac{3}{4}|0\rangle\langle 0| + \frac{1}{4}|1\rangle\langle 1|
 \end{array}
 \right.$$

6 Conclusions

In this paper we have presented the calculus λ_ρ , which is a quantum data / classical control extension to the lambda calculus where the data is manipulated by density matrices. The main importance of this calculus is its interpretation into density matrices, which can equate programs producing the same density matrices. Then, we have given a second calculus, λ_ρ° , where the density matrices are generalised to accommodate arbitrary terms, and so, programs producing the same density matrices, rewrite to such a matrix, thus, coming closer to its interpretation. The control of λ_ρ° is not classical nor quantum, however it can be seen as a weaker version of the quantum control approach. It is indeed not classical control because a generalised density matrix of terms is allowed ($\sum_i p_i t_i$). It is not quantum control because superposition of programs are not allowed (indeed, the previous sum is not a quantum superposition since all the p_i are positive and so no interference can occur). However, it is quantum in the sense that programs in a kind of generalised mixed-states are considered. We preferred to call it *probabilistic control*.




Table 11: Trace of the term $O_2\rho$ from Example 5.2 in λ_ρ .

As depicted in Example 5.2, the calculus λ_ρ° allows to represent the same operator in different ways. Understanding when two operators are equivalent is important from a physical point of view: it gives insights on when two different physical processes produce the same dynamics. To the best of our knowledge, it is the first lambda calculus for density matrices.

Future work and open questions

As pointed out by Bădescu and Panangaden [8], one of the biggest issues with quantum control is that it does not accommodate well with traditional features from functional programming languages like recursion. Ying [25] went around this problem by introducing a recursion based on second quantisation. Density matrices are DCPOs with respect to the Löwner order. Is the form of weakened quantum control suggested in this paper monotone? Can it be extended with recursion? Could this lead to a concrete quantum programming language, like Quipper [15]?

All these open questions are promising new lines of research that we are willing to follow. In particular, we have four ongoing works trying to answer some of these questions:

- The most well studied quantum lambda calculus is, without doubt, Selinger-Valiron’s λ_q [21]. Hence, we are working on the mutual simulations between λ_ρ and λ_q , and between λ_ρ° and a generalisation of λ_q into mixed states.
- We are also working on a first prototype of an implementation of λ_ρ° .
- We are studying extensions to both λ_ρ and λ_ρ° with recursion and with polymorphism.
- Finally, we are studying a more sophisticated denotational semantics for both calculi than the one given in this paper. We hope such a semantics to be adequate and fully abstract.

Acknowledgements We want to thank the anonymous reviewer for some important references and suggestions on future lines of work.

References

1. Aharonov, D., Ambainis, A., Kempe, J., Vazirani, U.: Quantum walks on graphs. In: Proceedings of the Thirty-third Annual ACM Symposium on Theory of Computing. pp. 50–59. STOC '01, ACM (2001)
2. Altenkirch, T., Grattage, J.J.: A functional quantum programming language. In: Proceedings of LICS-2005. pp. 249–258. IEEE Computer Society (2005)
3. Ambainis, A., Bach, E., Nayak, A., Vishwanath, A., Watrous, J.: One-dimensional quantum walks. In: Proceedings of the Thirty-third Annual ACM Symposium on Theory of Computing. pp. 37–49. STOC '01, ACM (2001)
4. Arrighi, P., Díaz-Caro, A.: A System F accounting for scalars. *Logical Methods in Computer Science* 8(1:11) (2012)
5. Arrighi, P., Díaz-Caro, A., Valiron, B.: The vectorial λ -calculus. *Information and Computation* 254(1), 105–139 (2017)
6. Arrighi, P., Dowek, G.: Lineal: A linear-algebraic lambda-calculus. *Logical Methods in Computer Science* 13(1:8) (2017)
7. Assaf, A., Díaz-Caro, A., Perdrix, S., Tasson, C., Valiron, B.: Call-by-value, call-by-name and the vectorial behaviour of the algebraic λ -calculus. *Logical Methods in Computer Science* 10(4:8) (2014)
8. Bădescu, C., Panangaden, P.: Quantum alternation: Prospects and problems. In: Heunen, C., Selinger, P., Vicary, J. (eds.) Proceedings of QPL-2015. *Electronic Proceedings in Theoretical Computer Science*, vol. 195, pp. 33–42 (2015)
9. D’Hondt, E., Panangaden, P.: Quantum weakest preconditions. *Mathematical Structures in Computer Science* 16, 429–451 (2006)
10. Díaz-Caro, A., Dowek, G.: Typing quantum superpositions and measurements (2017)
11. Díaz-Caro, A., Martínez, G.: Confluence in probabilistic rewriting. To appear in LSFA (2017)
12. Díaz-Caro, A., Petit, B.: Linearity in the non-deterministic call-by-value setting. In: Ong, L., de Queiroz, R. (eds.) Proceedings of WoLLIC 2012. LNCS, vol. 7456, pp. 216–231 (2012)
13. Feng, Y., Duan, R., Ying, M.: Bisimulation for quantum processes. *ACM SIGPLAN Notices (POPL’11)* 46(1), 523–534 (2011)
14. Feng, Y., Yu, N., Ying, M.: Model checking quantum markov chains. *Journal of Computer and System Sciences* 79(7), 1181–1198 (2013)
15. Green, A.S., Lumsdaine, P.L., Ross, N.J., Selinger, P., Valiron, B.: Quipper: a scalable quantum programming language. *ACM SIGPLAN Notices (PLDI’13)* 48(6), 333–342 (2013)
16. Lago, U.D., Masini, A., Zorzi, M.: Confluence results for a quantum lambda calculus with measurements. *Electronic Notes in Theoretical Computer Science* 270(2), 251 – 261 (2011)
17. Nielsen, M., Chuang, I.: *Quantum Computation and Quantum Information*. Cambridge University Press. (2000)
18. Pagani, M., Selinger, P., Valiron, B.: Applying quantitative semantics to higher-order quantum computing. *ACM SIGPLAN Notices (POPL’14)* 49(1), 647–658 (2014)
19. Selinger, P.: Towards a quantum programming language. *Mathematical Structures in Computer Science* 14(4), 527–586 (2004)
20. Selinger, P., Valiron, B.: Quantum lambda calculus. In: Gay, S., Mackie, I. (eds.) *Semantic Techniques in Quantum Computation*, chap. 9, pp. 135–172. Cambridge University Press (2009)

21. Selinger, P., Valiron, B.: A lambda calculus for quantum computation with classical control. *Mathematical Structures in Computer Science* 16(3), 527–552 (2006)
22. van Tonder, A.: A lambda calculus for quantum computation. *SIAM Journal on Computing* 33, 1109–1135 (2004)
23. Vaux, L.: The algebraic lambda calculus. *Mathematical Structures in Computer Science* 19, 1029–1059 (2009)
24. Ying, M.: Floyd–hoare logic for quantum programs. *ACM Transactions on Programming Languages and Systems* 33(6), 19:1–19:49 (2011)
25. Ying, M.: Quantum recursion and second quantisation. [arXiv:1405.4443](https://arxiv.org/abs/1405.4443) (2014)
26. Ying, M.: *Foundations of Quantum Programming*. Elsevier (2016)
27. Ying, M., Ying, S., Wu, X.: Invariants of quantum programs: characterisations and generation. *ACM SIGPLAN Notices (POPL'17)* 52(1), 818–832 (2017)
28. Ying, M., Yu, N., Feng, Y.: Defining quantum control flow. [arXiv:1209.4379](https://arxiv.org/abs/1209.4379) (2012)
29. Ying, M., Yu, N., Feng, Y.: Alternation in quantum programming: from superposition of data to superposition of programs. [arXiv:1402.5172](https://arxiv.org/abs/1402.5172) (2014)
30. Zorzi, M.: On quantum lambda calculi: a foundational perspective. *Mathematical Structures in Computer Science* 26(7), 1107–1195 (2016)

A Detailed Proofs of Section 2.2

A.1 Proof of Lemma 2.3

By induction on the type derivation.

- Let $\Gamma, x : (m, n) \vdash x : (m, n)$ as a consequence of rule **ax**. Since $\theta \vDash \Gamma, x : (m, n)$, we have $\theta(x) = (b, e)$ with $e \in \mathcal{D}_n$ and $b \neq \varepsilon$. Hence, $\llbracket x \rrbracket_\theta = \{(1, b, e)\}$.
- Let $\Gamma, \Delta \vdash tr : (m, n)$ as a consequence of $\Gamma \vdash t : \vec{A} \multimap (m, n)$, $\Delta \vdash r : A$ and rule \multimap_e . Since $\theta \vDash \Gamma, \Delta$, we have $\theta \vDash \Gamma$. Since $\llbracket tr \rrbracket_\theta$ is well-defined, we have $\llbracket r \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$, $\llbracket t \rrbracket_\theta = \{(q_j, b'_j, f_j)\}_i$, and $f_j(b_i, e_i) = \{(h_{ijk}, b''_{ijk}, g_{ijk})\}_k$, and hence $\llbracket tr \rrbracket_\theta = \{(p_i q_j h_{ijk}, b''_{ijk}, g_{ijk})\}_{ijk}$. By the induction hypothesis, $f_i \in \llbracket \vec{A} \multimap (m, n) \rrbracket$, so, by definition, $b''_{ijk} \neq \varepsilon$ and $g_{ijk} \in \mathcal{D}_n$.
- Let $\Gamma \vdash \pi^m t : (m, n)$ as a consequence of $\Gamma \vdash t : n$ and rule **m**. Then we have that $\llbracket \pi^m t \rrbracket_\theta$ is equal to $\{p_j \text{tr}(\overline{\pi_i^\dagger \pi_i} \rho_j), i, \frac{\overline{\pi_i \rho_j \pi_i^\dagger}}{\text{tr}(\overline{\pi_i^\dagger \pi_i} \rho_j)} \mid \llbracket t \rrbracket_\theta = \{(p_j, \varepsilon, \rho_j)\}_j\}$, with $i \neq \varepsilon$. Notice that $\frac{\overline{\pi_i \rho_j \pi_i^\dagger}}{\text{tr}(\overline{\pi_i^\dagger \pi_i} \rho_j)} \in \mathcal{D}_n$.
- Let $\Gamma \vdash (b^m, \rho^n) : (m, n)$ as a consequence of rule **ax_{am}**. Then, $\llbracket (b^m, \rho^n) \rrbracket_\theta = \{(1, b^m, \rho^n)\}$. Notice that $\rho^n \in \mathcal{D}_n$.
- Let $\Gamma \vdash \text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^{m'}-1}\} : (m, n)$ as a consequence of $x : n' \vdash t_k : (m, n)$, for $k = 0, \dots, 2^{m'} - 1$, $\Gamma \vdash r : (m', n')$ and rule **lc**. Since $\llbracket \text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^{m'}-1}\} \rrbracket_\theta$ is well-defined, $\llbracket r \rrbracket_\theta = \{(p_i, b_i, \rho_i^n)\}_i$, $\llbracket t_i \rrbracket_{\theta, x=(\varepsilon, \rho_i^n)} = \{(q_{ij}, b'_{ij}, e_{ij})\}_j$ and $\llbracket \text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^{m'}-1}\} \rrbracket_\theta = \{(p_i q_{ij}, b'_{ij}, e_{ij})\}_{ij}$. By the induction hypothesis, $b'_{ij} \neq \varepsilon$ and $e_{ij} \in \mathcal{D}_n$. \square

A.2 Proof of Lemma 2.4

By induction on t .

- Let $t = x$. Then $x : A \in \Gamma$. $\llbracket x \rrbracket_\theta = \{(1, b, e)\}$, with $\theta(x) = (b, e)$. Since $\theta \vDash \Gamma$ we have $e \in \llbracket A \rrbracket$.
- Let $t = \lambda x.r$. Then $A = B \multimap C$, $\Gamma, x : B \vdash r : C$ and $\llbracket \lambda x.r \rrbracket_\theta = \{(1, \varepsilon, (b, e)) \mapsto \llbracket r \rrbracket_{\theta, x=(b, e)}\}$. Let $e \in \llbracket B \rrbracket$ and $b \in \mathbb{N}^\varepsilon$ such that $P(b, B)$. Then, since $\theta \vDash \Gamma$, we have $\theta, x = (b, e) \vDash \Gamma, x : B$. Hence, by the induction hypothesis, $\text{trd}(\llbracket r \rrbracket_{\theta, x=(b, e)}) \subseteq \llbracket C \rrbracket$. Therefore, $(b, e) \mapsto \llbracket r \rrbracket_{\theta, x=(b, e)} \in \llbracket B \multimap C \rrbracket$.
- Let $t = rs$. Then $\Gamma = \Gamma_1, \Gamma_2$, with $\Gamma_1 \vdash r : B \multimap A$ and $\Gamma_2 \vdash s : B$. Since $\theta \vDash \Gamma$, we have $\theta \vDash \Gamma_1$ and $\theta \vDash \Gamma_2$, so by the induction hypothesis, $\llbracket s \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$, $\sum_i p_i = 1$ and $e_i \in \llbracket B \rrbracket$. Similarly, $\llbracket r \rrbracket_\theta = \{(q_j, b'_j, f_j)\}_j$, $\sum_j q_j = 1$ and $f_j \in \llbracket B \multimap A \rrbracket$. Let $f_j(b_i, e_i) = \{(h_{ijk}, b''_{ijk}, g_{ijk})\}_k$. Then, $\llbracket rs \rrbracket_\theta = \{(p_i q_j h_{ijk}, b''_{ijk}, g_{ijk})\}_{ijk}$. By Lemma 2.3, we have $P(b, B)$, so by definition of $\llbracket B \multimap A \rrbracket$, we have $\{g_{ijk}\} = \text{trd}(f_j(b_i, e_i)) \subseteq \llbracket A \rrbracket$ and $w(f_j(b_i, e_i)) = 1$. Notice that $\sum_{ijk} p_i q_j h_{ijk} = \sum_i p_i \sum_j q_j \sum_k h_{ijk} = 1$.
- Let $t = \rho^n$. Then $A = n$ and $\llbracket \rho^n \rrbracket_\theta = \{(1, \varepsilon, \rho^n)\}$. Notice that $\rho^n \in \mathcal{D}_n = \llbracket A \rrbracket$.

- Let $t = U^m r$. Then $A = n$ and $\Gamma \vdash r : n$. By the induction hypothesis, $\llbracket r \rrbracket_\theta = \{(p_i, b_i, \rho_i^n)\}_i$, with $\sum_i p_i = 1$ and $\rho_i^n \in \mathcal{D}_n$. Then, $\overline{U^m \rho^n U^{m\dagger}} \in \mathcal{D}_n = \llbracket A \rrbracket$, and $\llbracket U^m r \rrbracket_\theta = \{(p_i, \varepsilon, \overline{U^m \rho^n U^{m\dagger}})\}$.
- Let $t = \pi^m r$. Then $A = (m, n)$ and $\Gamma \vdash r : n$. By the induction hypothesis, $\llbracket r \rrbracket_\theta = \{(p_i, b_i, \rho_i^n)\}_i$, with $\sum_i p_i = 1$ and $\rho_i^n \in \mathcal{D}_n$. Let $\pi^m = \{\pi_j\}_j$, and $q_{ij} = \text{tr}(\overline{\pi_j^\dagger \pi_j} \rho_i^n)$. So, $\sum_j q_{ij} = 1$. Let $\rho_{ij}^n = \frac{\overline{\pi_j \rho_i^n \pi_j^\dagger}}{q_{ij}} \in \mathcal{D}_n = \llbracket (m, n) \rrbracket$. Then, we have $\llbracket \pi^m r \rrbracket_\theta = \{(p_i q_{ij}, j, \rho_{ij}^n)\}_{ij}$. Notice that $\sum_{ij} p_i q_{ij} = \sum_i p_i \sum_j q_{ij} = 1$.
- Let $t = r \otimes s$. Then $A = n + m$ and $\Gamma = \Gamma_1, \Gamma_2$, with $\Gamma_1 \vdash r : n$ and $\Gamma_2 \vdash s : m$. Since $\theta \vDash \Gamma$, we have $\theta \vDash \Gamma_1$ and $\theta \vDash \Gamma_2$. Then, by the induction hypothesis, $\llbracket r \rrbracket_\theta = \{(p_i, b_i, \rho_i^n)\}_i$, with $\sum_i p_i = 1$ and $\rho_i^n \in \mathcal{D}_n$. Similarly, $\llbracket s \rrbracket_\theta = \{(q_j, b'_j, \rho_j^m)\}_j$, with $\sum_j q_j = 1$ and $\rho_j^m \in \mathcal{D}_m$. Hence, $\llbracket r \otimes s \rrbracket_\theta = \{(p_i q_j, \varepsilon, \rho_i^n \otimes \rho_j^m)\}_{ij}$. Notice that $\rho_i^n \otimes \rho_j^m \in \mathcal{D}_{n+m}$, and $\sum_{ij} p_i q_j = \sum_i p_i \sum_j q_j = 1$.
- Let $t = (b^m, \rho^n)$. Then $A = (m, n)$ and $\llbracket (b^m, \rho^n) \rrbracket_\theta = \{(1, b^m, \rho^n)\}$, with $\rho^n \in \mathcal{D}_n = \llbracket A \rrbracket$.
- Let $t = \text{letcase } x = r \text{ in } \{s_0, \dots, s_{2^m-1}\}$. Then, $x : n \vdash s_k : A$, for $k = 0, \dots, 2^m - 1$, and $\Gamma \vdash r : (m, n)$. Hence, by the induction hypothesis, $\llbracket r \rrbracket_\theta = \{(p_i, b_i, \rho_i^n)\}_i$ with $\rho_i^n \in \mathcal{D}_n$ and $\sum_i p_i = 1$. By Lemma 2.3, $b_i \neq \varepsilon$, so $\theta, x = (\varepsilon, \rho_i^n) \vDash x : n$ and hence, by the induction hypothesis, $\llbracket s_{b_i} \rrbracket_{\theta, x=(\varepsilon, \rho_i^n)} = \{(q_{ij}, b'_{ij}, e_{ij})\}_j$, with $\sum_j q_{ij} = 1$ and $e_{ij} \in \llbracket A \rrbracket$. Hence, $\llbracket \text{letcase } x = r \text{ in } \{s_0, \dots, s_{2^m-1}\} \rrbracket_\theta = \{(p_i q_{ij}, b'_{ij}, e_{ij})\}_{ij}$. Notice that $\sum_{ij} p_i q_{ij} = \sum_i p_i \sum_j q_{ij} = 1$. \square

A.3 Proof of Lemma 2.6

We need the next four lemmas and the corollary as auxiliary results.

Lemma A.1. *If $\Gamma \vdash t : A \multimap B$ and $\theta \vDash \Gamma$, then we have $\langle t \rangle_\theta = \sum_i p_i ((b, e) \mapsto \langle r_i \rangle_{\theta, x=(b, e)})$.* \square

Lemma A.2. *If $\langle t \rangle_\theta = \sum_i p_i ((b, e) \mapsto \langle r_i \rangle_{\theta', x=(b, e)})$ and $\llbracket s \rrbracket_\theta = \{(q_j, b_j, e_j)\}_j$, then we have $\langle ts \rangle_\theta = \sum_{ij} p_i q_j \langle r_i \rangle_{\theta', x=(b_j, e_j)}$* \square

Corollary A.3. *If $\langle t \rangle_\theta = \sum_i p_i ((b, e) \mapsto \langle r_i \rangle_{\theta', x=(b, e)})$ and $\langle s \rangle_\theta = \sum_j q_j e_j$, then $\langle ts \rangle_\theta = \sum_{ij} p_i q_j \langle r_i \rangle_{\theta', x=(\varepsilon, e_j)}$* \square

Lemma A.4. *If $\Gamma \vdash t : n$ and $\theta \vDash \Gamma$, then $\langle U^m t \rangle_\theta = \overline{U^m} \langle t \rangle_\theta \overline{U^{m\dagger}}$ and $\langle \pi^m t \rangle_\theta = \sum_i \overline{\pi_i} \langle t \rangle_\theta \overline{\pi_i^\dagger}$.* \square

Lemma A.5. *If $\Gamma \vdash t : n$, $\Delta \vdash r : m$ and $\theta \vDash \Gamma, \Delta$, then $\langle t \otimes r \rangle_\theta = \langle t \rangle_\theta \otimes \langle r \rangle_\theta$.* \square

Proof of Lemma 2.6. We proceed by induction on t , however, we enforce the hypothesis by also showing that if $\llbracket t \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, b'_{ij}, \rho_{ij})\}_j$, then $\llbracket t[r/x] \rrbracket_{\theta} = \{(p_i q_{ij}, b'_{ij}, \rho_{ij})\}_{ij}$.

- Let $t = x$. $\langle x[r/x] \rangle_{\theta} = \langle r \rangle_{\theta} = \sum_i p_i \langle e_i \rangle = \sum_i p_i \langle x \rangle_{\theta, x=(b_i, e_i)}$.
Notice that $\llbracket x \rrbracket_{\theta, x=(b_i, e_i)} = \{(1, b_i, e_i)\}$ and $\llbracket r \rrbracket_{\theta} = \{(p_i, b_i, e_i)\}_i$.
- Let $t = y$. Let $\theta(y) = (b', f)$. Then, $\langle y[r/x] \rangle_{\theta} = \langle y \rangle_{\theta} = f = \langle y \rangle_{\theta, x=(b_i, e_i)} = \sum_i p_i \langle y \rangle_{\theta, x=(b_i, e_i)}$.
Notice that $\llbracket y \rrbracket_{\theta, x=(b_i, e_i)} = \{(1, b', f)\} = \{(p_i, b', f)\}_i = \llbracket y[r/x] \rrbracket_{\theta}$.
- Let $t = \lambda y.s$. Then, using the induction hypothesis, we have $\langle (\lambda y.s)[r/x] \rangle_{\theta} = \langle \lambda y.s[r/x] \rangle_{\theta} = (\mathbf{b}, \mathbf{e}) \mapsto \langle s[r/x] \rangle_{\theta, y=(\mathbf{b}, \mathbf{e})} = (\mathbf{b}, \mathbf{e}) \mapsto \sum_i p_i \langle s \rangle_{\theta, y=(\mathbf{b}, \mathbf{e}), x=(b_i, e_i)} = \sum_i p_i \langle (\mathbf{b}, \mathbf{e}) \mapsto \langle s \rangle_{\theta, y=(\mathbf{b}, \mathbf{e}), x=(b_i, e_i)} \rangle = \sum_i p_i \langle \lambda y.s \rangle_{\theta, x=(b_i, e_i)}$. Notice that $\lambda y.s$ cannot have type n or (m, n) .
- Let $t = s_1 s_2$
 - Let $x \in FV(s_1)$. By Lemma A.1, we have $\langle s_1 \rangle_{\theta, x=(b_i, e_i)} = \sum_j q_{ij} \langle (\mathbf{b}, \mathbf{e}) \mapsto \langle s'_{ij} \rangle_{\theta, x=(b_i, e_i), y=(\mathbf{b}, \mathbf{e})} \rangle$. Then, by the induction hypothesis, $\langle s_1[r/x] \rangle_{\theta} = \sum_i p_i \langle s_1 \rangle_{\theta, x=(b_i, e_i)} = \sum_{ij} p_i q_{ij} \langle (\mathbf{b}, \mathbf{e}) \mapsto \langle s'_{ij} \rangle_{\theta, x=(b_i, e_i), y=(\mathbf{b}, \mathbf{e})} \rangle$. Let $\llbracket s_2 \rrbracket_{\theta} = \{(h_k, b'_k, f_k)\}_k$. Hence, by Lemma A.2, we have that $\langle s_1[r/x] s_2 \rangle_{\theta} = \sum_{ijk} p_i q_{ij} h_k \langle s'_{ij} \rangle_{\theta, x=(b_i, e_i), y=(b'_k, f_k)}$. Since $x \notin FV(s_2)$, we also have that $\llbracket s_2 \rrbracket_{\theta, x=(b_i, e_i)} = \llbracket s_2 \rrbracket_{\theta}$, so, also by Lemma A.2, we have $\langle s_1 s_2 \rangle_{\theta, x=(b_i, e_i)} = \sum_{jk} q_{ij} h_k \langle s'_{ij} \rangle_{\theta, x=(b_i, e_i), y=(b'_k, f_k)}$. Therefore, we have $\langle (s_1 s_2)[r/x] \rangle_{\theta} = \sum_i p_i \langle s_1 s_2 \rangle_{\theta, x=(b_i, e_i)}$. Since s'_{ij} is smaller than s_1 , the induction hypothesis applies, and so, if $\llbracket s'_{ij} \rrbracket_{\theta, x=(b_i, e_i), y=(b'_k, f_k)} = \{(q_{ij}, b'_{ij}, \rho_{ij})\}_j$, then $\llbracket s'_{ij}[r/x] \rrbracket_{\theta, y=(b'_k, f_k)} = \{(p_i q_{ij}, b'_{ij}, \rho_{ij})\}_{ij}$.
 - Let $x \in FV(s_s)$. By Lemma A.1, we have $\langle s_1 \rangle_{\theta, x=(b_i, e_i)} = \sum_j q_j \langle (\mathbf{b}, \mathbf{e}) \mapsto \langle s'_{ij} \rangle_{\theta, x=(b_i, e_i), y=(\mathbf{b}, \mathbf{e})} \rangle$. By Corollary A.3, we have that $\langle s_1 s_2 \rangle_{\theta, x=(b_i, e_i)} = \sum_j q_j \langle s'_{ij} \rangle_{\theta, x=(b_i, e_i), y=(\varepsilon, \langle s_2 \rangle_{\theta, x=(b_i, e_i)})}$. By the induction hypothesis, we have $\langle s_2[r/x] \rangle_{\theta} = \sum_i p_i \langle s_2 \rangle_{\theta, x=(b_i, e_i)}$. Since $x \notin FV(s_2[r/x])$, we have $\langle s_2[r/x] \rangle_{\theta} = \langle s_2[r/x] \rangle_{\theta, x=(b_i, e_i)}$. Therefore, by Corollary A.3, we have $\langle s_1 s_2[r/x] \rangle_{\theta, x=(b_i, e_i)} = \sum_{ij} p_i q_j \langle s'_{ij} \rangle_{\theta, x=(b_i, e_i), y=(\varepsilon, \langle s_2 \rangle_{\theta, x=(b_i, e_i)})} = \sum_i p_i \langle s_1 s_2 \rangle_{\theta, x=(b_i, e_i)}$. Since s'_{ij} is smaller than s_1 , the induction hypothesis applies, and therefore, if $\llbracket s'_{ij} \rrbracket_{\theta, x=(b_i, e_i), y=(\varepsilon, \langle s_2 \rangle_{\theta, x=(b_i, e_i)})} = \{(q_{ij}, b'_{ij}, \rho_{ij})\}_j$, then $\llbracket s'_{ij}[r/x] \rrbracket_{\theta, y=(\varepsilon, \langle s_2 \rangle_{\theta, x=(b_i, e_i)})} = \{(p_i q_{ij}, b'_{ij}, \rho_{ij})\}_{ij}$.
- Let $t = \rho^n$. $\langle \rho^n[r/x] \rangle_{\theta} = \langle \rho^n \rangle_{\theta} = \rho^n = \langle \rho^n \rangle_{\theta, x=(b_i, e_i)} = \sum_i p_i \langle \rho^n \rangle_{\theta, x=(b_i, e_i)}$. In addition, $\llbracket \rho^n \rrbracket_{\theta, x=(b_i, e_i)} = \{(1, \varepsilon, \rho^n)\} = \{(p_i, \varepsilon, \rho^n)\}_i = \llbracket \rho^n[r/x] \rrbracket_{\theta}$.
- Let $t = U^m s$. By the induction hypothesis, $\langle s[r/x] \rangle_{\theta} = \sum_i p_i \langle s \rangle_{\theta, x=(b_i, e_i)}$. By Lemma A.4, $\langle U^m s[r/x] \rangle_{\theta} = \overline{U^m} \langle s[r/x] \rangle_{\theta} \overline{U^m}^{\dagger} = \overline{U^m} \sum_i p_i \langle s \rangle_{\theta, x=(b_i, e_i)} \overline{U^m}^{\dagger} = \sum_i p_i \overline{U^m} \langle s \rangle_{\theta, x=(b_i, e_i)} \overline{U^m}^{\dagger} = \sum_i p_i \langle U^m s \rangle_{\theta, x=(b_i, e_i)}$. Let $\llbracket s \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, b_{ij}, \rho_{ij})\}_j$, then $\llbracket U^m s \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, \varepsilon, \overline{U^m} \rho_{ij} \overline{U^m}^{\dagger})\}_j$. In addition, by the induction hypothesis, we have $\llbracket s[r/x] \rrbracket_{\theta} = \{(p_i q_{ij}, b_{ij}, \rho_{ij})\}_{ij}$, therefore $\llbracket (U^m s)[r/x] \rrbracket_{\theta} = \llbracket U^m s[r/x] \rrbracket_{\theta} = \{(p_i q_{ij}, \varepsilon, \overline{U^m} \rho_{ij} \overline{U^m}^{\dagger})\}_{ij}$.
- Let $t = \pi^m s$. By the induction hypothesis, $\langle s[r/x] \rangle_{\theta} = \sum_i p_i \langle s \rangle_{\theta, x=(b_i, e_i)}$. By Lemma A.4, $\langle \pi^m s[r/x] \rangle_{\theta} = \sum_j \overline{\pi_j} \langle s[r/x] \rangle_{\theta} \overline{\pi_j}^{\dagger} = \sum_j \overline{\pi_j} \sum_i p_i \langle s \rangle_{\theta, x=(b_i, e_i)} \overline{\pi_j}^{\dagger} = \sum_i p_i \sum_j \overline{\pi_j} \langle s \rangle_{\theta, x=(b_i, e_i)} \overline{\pi_j}^{\dagger} = \sum_i p_i \langle \pi^m s \rangle_{\theta, x=(b_i, e_i)}$. Let $\llbracket s \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, b_{ij}, \rho_{ij})\}_j$, then $\llbracket \pi^m s \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, \text{tr}(\overline{\pi_k}^{\dagger} \overline{\pi_k} \rho_{ij}), k, \frac{\overline{\pi_k} \rho_{ij} \overline{\pi_k}}{\text{tr}(\overline{\pi_k}^{\dagger} \overline{\pi_k} \rho_{ij})})\}_{jk}$.

- By the induction hypothesis, $\llbracket s[r/x] \rrbracket_\theta = \{(p_i q_{ij}, b_{ij}, \rho_{ij})\}_{ij}$, therefore, we have $\llbracket (\pi^m s)[r/x] \rrbracket_\theta = \llbracket \pi^m s[r/x] \rrbracket_\theta = \{(p_i q_{ij} \text{tr}(\overline{\pi_k^\dagger} \overline{\pi_k} \rho_{ij}), k, \frac{\overline{\pi_k} \rho_{ij} \overline{\pi_k}}{\text{tr}(\overline{\pi_k^\dagger} \overline{\pi_k} \rho_{ij})})\}_{ijk}$.
- Let $t = s_1 \otimes s_2$, with $x \in FV(s_1)$. By the induction hypothesis, $\langle s_1[r/x] \rangle_\theta = \sum_i p_i \langle s_1 \rangle_{\theta, x=(b_i, e_i)}$, and notice that, since $x \notin FV(s_2)$, we have $\langle s_2 \rangle_\theta = \langle s_2 \rangle_{\theta, x=(b_i, e_i)}$. Therefore, by Lemma A.5, $\langle s_1[r/x] \otimes s_2 \rangle_\theta = \langle s_1[r/x] \rangle_\theta \otimes \langle s_2 \rangle_\theta = (\sum_i p_i \langle s_1 \rangle_{\theta, x=(b_i, e_i)}) \otimes \langle s_2 \rangle_{\theta, x=(b_i, e_i)} = \sum_i p_i \langle s_1 \rangle_{\theta, x=(b_i, e_i)} \otimes \langle s_2 \rangle_{\theta, x=(b_i, e_i)} = \sum_i p_i \langle s_1 \otimes s_2 \rangle_{\theta, x=(b_i, e_i)}$, where the last step is due to Lemma A.5 as well. Note that if $\llbracket s_1 \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, b_{ij}, \rho_{ij})\}_j$, and $\llbracket s_2 \rrbracket_{\theta, x=(b_i, e_i)} = \{(h_k, b'_k, \rho'_k)\}_k$, we have $\llbracket s_1 \otimes s_2 \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij} h_k, \varepsilon, \rho_{ij} \otimes \rho'_k)\}_{jk}$. By the induction hypothesis $\llbracket s_1[r/x] \rrbracket_\theta = \{(p_i q_{ij}, b_{ij}, \rho_{ij})\}_{ij}$, and so $\llbracket (s_1 \otimes s_2)[r/x] \rrbracket_\theta = \llbracket s_1[r/x] \otimes s_2 \rrbracket_\theta = \{(p_i q_{ij} h_k, \varepsilon, \rho_{ij} \otimes \rho'_k)\}_{ijk}$.
 - Let $t = (b^m, \rho^n)$. $\langle (b^m, \rho^n)[r/x] \rangle_\theta = \langle (b^m, \rho^n) \rangle_\theta = \rho^n = \langle (b^m, \rho^n) \rangle_{\theta, x=(b_i, e_i)} = \sum_i p_i \langle (b^m, \rho^n) \rangle_{\theta, x=(b_i, e_i)}$. Moreover, $\llbracket (b^m, \rho^n) \rrbracket_{\theta, x=(b_i, e_i)} = \{(1, b^m, \rho^n)\} = \{(p_i, b^m, \rho^n)\}_i = \llbracket (b^m, \rho^n)[r/x] \rrbracket_\theta = \llbracket (b^m, \rho^n) \rrbracket_\theta$.
 - Let $t = \text{letcase } y = s \text{ in } \{t_0, \dots, t_{2^m-1}\}$. Let $\llbracket s \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, b'_{ij}, \rho_{ij})\}_j$. Then, by the induction hypothesis, $\llbracket s[r/x] \rrbracket_\theta = \{(p_i q_{ij}, b'_{ij}, \rho_{ij})\}_{ij}$. Let, for all i and j , $\llbracket t_{b'_{ij}} \rrbracket_{\theta, x=(b_i, e_i), y=(\varepsilon, \rho_{ij})} = \{(h_{ijk}, b''_{ijk}, f_{ijk})\}_k$. Hence, we have that $\llbracket \text{letcase } y = s \text{ in } \{t_0, \dots, t_{2^m-1}\} \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij} h_{ijk}, b''_{ijk}, f_{ijk})\}_{jk}$ and also $\llbracket \text{letcase } y = s[r/x] \text{ in } \{t_0, \dots, t_{2^m-1}\} \rrbracket_\theta = \{(p_i q_{ij} h_{ijk}, b''_{ijk}, f_{ijk})\}_{ijk}$. Therefore, we have $\langle \text{letcase } y = s[r/x] \text{ in } \{t_0, \dots, t_{2^m-1}\} \rangle_\theta = \sum_i p_i \langle \text{letcase } y = s \text{ in } \{t_0, \dots, t_{2^m-1}\} \rangle_{\theta, x=(b_i, e_i)}$ \square

A.4 Proof of Theorem 2.7

By induction on the relation \longrightarrow_p .

- $(\lambda x.t)r \longrightarrow_1 t[r/x]$. We have $\llbracket \lambda x.t \rrbracket_\theta = \{1, \varepsilon, (\mathbf{b}, \mathbf{e}) \mapsto \llbracket t \rrbracket_{\theta, x=(\mathbf{b}, \mathbf{e})}\}$. By Lemma 2.4, we have $\llbracket r \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$ with $\sum_i p_i = 1$, and $\llbracket t \rrbracket_{\theta, x=(b_i, e_i)} = \{(q_{ij}, b'_{ij}, g_{ij})\}_j$. Therefore, we have that $\llbracket (\lambda x.t)r \rrbracket_\theta = \{(p_i q_{ij}, b'_{ij}, g_{ij})\}_{ij}$, and $\langle (\lambda x.t)r \rangle_\theta = \sum_{ij} p_i q_{ij} g_{ij}$ which, by Lemma 2.6, is equal to $\langle t[r/x] \rangle_\theta$.
- $\text{letcase } x = (b^m, \rho^n) \text{ in } \{t_0, \dots, t_{2^m-1}\} \longrightarrow_1 t_{b^m}[\rho^n/x]$. Then, we have that $\llbracket \text{letcase } x = (b^m, \rho^n) \text{ in } \{t_0, \dots, t_{2^m-1}\} \rrbracket_\theta = \llbracket t_{b^m} \rrbracket_{\theta, x=(\varepsilon, \rho^n)}$. Therefore, we have that $\langle \text{letcase } x = (b^m, \rho^n) \text{ in } \{t_0, \dots, t_{2^m-1}\} \rangle_\theta = \langle t_{b^m} \rangle_{\theta, x=(\varepsilon, \rho^n)}$. Since $\llbracket \rho^n \rrbracket_\theta = \{(1, \varepsilon, \rho^n)\}$, we have, by Lemma 2.6, $\langle t_{b^m} \rangle_{\theta, x=(\varepsilon, \rho^n)} = \langle t_{b^m}[\rho^n/x] \rangle_\theta$.
- $U^m \rho^n \longrightarrow_1 \rho^n$, with $\rho^n = \overline{U^m} \rho^n \overline{U^m}^\dagger$. Then $\llbracket U^m \rho^n \rrbracket_\theta = \{(1, \varepsilon, \overline{U^m} \rho^n \overline{U^m}^\dagger)\}$ $= \llbracket \rho^n \rrbracket_\theta$, so $\langle U^m \rho^n \rangle_\theta = \rho^n = \langle \rho^n \rangle_\theta$.
- $\pi^n \rho^n \longrightarrow_{p_i} (i^m, \rho_i^n)$, with $p_i = \text{tr}(\overline{\pi_i^\dagger} \overline{\pi_i} \rho^n)$ and $\rho_i^n = \frac{\overline{\pi_i} \rho^n \overline{\pi_i^\dagger}}{p_i}$. We have $\llbracket \pi^m \rho^n \rrbracket_\theta = \{(p_i, i, \rho_i^n)\}_i$. Hence, $\langle \pi^m \rho^n \rangle_\theta = \sum_i p_i \rho_i^n = \sum_i p_i \langle \rho_i^n \rangle_\theta$.
- $\rho_1 \otimes \rho_2 \longrightarrow_1 \rho$, with $\rho = \rho_1 \otimes \rho_2$. We have $\llbracket \rho_1 \otimes \rho_2 \rrbracket_\theta = \{(1, \varepsilon, \rho)\}$, so $\langle \rho_1 \otimes \rho_2 \rangle_\theta = \rho = \langle \rho \rangle_\theta$.
- Contextual cases: Let $s \longrightarrow_{p_i} s_i$. Then
 - $\lambda x.s \longrightarrow_{p_i} \lambda x.s_i$. By the induction hypothesis, $\langle s \rangle_{\theta'} = \sum_i p_i \langle s_i \rangle_{\theta'}$, for all $\theta' \models \Gamma, x : A$. Then, $\langle \lambda x.s \rangle_\theta = (\mathbf{b}, \mathbf{e}) \mapsto \langle s \rangle_{\theta, x=(\mathbf{b}, \mathbf{e})} = (\mathbf{b}, \mathbf{e}) \mapsto \sum_i p_i \langle s_i \rangle_{\theta, x=(\mathbf{b}, \mathbf{e})} = \sum_i p_i \langle (\mathbf{b}, \mathbf{e}) \mapsto \langle s_i \rangle_{\theta, x=(\mathbf{b}, \mathbf{e})} \rangle_\theta = \sum_i p_i \langle \lambda x.s_i \rangle_\theta$.

- $ts \rightarrow_{p_i} t s_i$. By the induction hypothesis, $(s)_\theta = \sum_i p_i (s_i)_\theta$. Then, we have $\llbracket ts \rrbracket_\theta = \{(p_i q_j h_{ijk}, b''_{ijk}, g_{ijk})\}_{ijk}$, with $\llbracket s \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$, $\llbracket t \rrbracket_\theta = \{(q_j, b'_j, f_j)\}_j$, and $f_j(b_i, e_i) = \{(h_{ijk}, b''_{ijk}, g_{ijk})\}_k$. Hence, $(ts)_\theta = \sum_{ijk} p_i q_j h_{ijk} g_{ijk} = \sum_i p_i (\sum_{jk} q_j h_{ijk} g_{ijk}) = \sum_i p_i (t s_i)_\theta$.
- $st \rightarrow_{p_i} s i t$. By the induction hypothesis, $(s)_\theta = \sum_i p_i (s_i)_\theta$. Then, we have $\llbracket st \rrbracket_\theta = \{(q_j p_i h_{jik}, b''_{jik}, g_{jik})\}_{jik}$, with $\llbracket t \rrbracket_\theta = \{(q_j, b'_j, f_j)\}_j$, $\llbracket s \rrbracket_\theta = \{(p_i, b_i, e_i)\}_i$, and $e_i(b_j, f_j) = \{(h_{jik}, b''_{jik}, g_{jik})\}_k$. Hence, $(st)_\theta = \sum_{jik} q_j p_i h_{jik} g_{jik} = \sum_i p_i (\sum_{jk} q_j h_{ijk} g_{ijk}) = \sum_i p_i (s_i t)_\theta$.
- $U^m s \rightarrow_{p_i} U^m s_i$. By the induction hypothesis, $(s)_\theta = \sum_i p_i (s_i)_\theta$. By Lemma A.4, we have $(U^m s)_\theta = \overline{U^m} \sum_i p_i (s_i)_\theta \overline{U^m}^\dagger = \sum_i p_i \overline{U^m} (s_i)_\theta \overline{U^m}^\dagger = \sum_i p_i (U^m s_i)_\theta$.
- $\pi^m s \rightarrow_{p_i} r = \pi^m s_i$. By the induction hypothesis, $(s)_\theta = \sum_i p_i (s_i)_\theta$. By Lemma A.4, we have $(\pi^m s)_\theta = \overline{\pi^m} \sum_i p_i (s_i)_\theta \overline{\pi^m}^\dagger = \sum_i p_i \overline{\pi^m} (s_i)_\theta \overline{\pi^m}^\dagger = \sum_i p_i (\pi^m s_i)_\theta$.
- $t \otimes s \rightarrow_{p_i} r = t \otimes s_i$. By the induction hypothesis, $(s)_\theta = \sum_i p_i (s_i)_\theta$. By Lemma A.5, $(t \otimes s)_\theta = (t)_\theta \otimes (s)_\theta = (t)_\theta \otimes (\sum_i p_i (s_i)_\theta) = \sum_i p_i (t)_\theta \otimes (s_i)_\theta = \sum_i p_i (t \otimes s_i)_\theta$.
- $s \otimes t \rightarrow_{p_i} r = s_i \otimes t$. Analogous to previous case.
- $\text{letcase } x = s \text{ in } \{t_0, \dots, t_{2^m-1}\} \rightarrow_{p_i} \text{letcase } x = s_i \text{ in } \{t_0, \dots, t_{2^m-1}\}$. By the induction hypothesis, we have that $(s)_\theta = \sum_i p_i (s_i)_\theta$. Let $\llbracket s \rrbracket_\theta = \{(p_i, b_i, \rho_i)\}_i$ and $\llbracket t_b \rrbracket_{\theta, x=(\varepsilon, \rho_i)} = \{(q_{ij}, b'_{ij}, e_{ij})\}_j$, then, $(\text{letcase } x = s \text{ in } \{t_0, \dots, t_{2^m-1}\})_\theta = \sum_{ij} p_i q_{ij} e_{ij} = \sum_i p_i (\sum_j q_{ij} e_{ij})$. Notice that $\sum_j q_{ij} e_{ij} = (\text{letcase } x = s_i \text{ in } \{t_0, \dots, t_{2^m-1}\})_\theta$. \square

B Detailed Proofs of Section 3.2

B.1 Proof of Theorem 3.4

By induction on the relation \rightsquigarrow . Rules $(\lambda x.t)r \rightsquigarrow t[r/x]$, $U^m \rho^n \rightsquigarrow \rho'$ and $\rho \otimes \rho' \rightsquigarrow \rho''$ are also valid rules for relation \rightarrow_1 , and hence the proof of these cases are the same than in Theorem 2.7.

Remaining cases:

- $\text{letcase}^\circ x = \pi^m \rho^n \text{ in } \{t_0, \dots, t_{2^m-1}\} \rightsquigarrow \sum_i p_i t_i[\rho'/x]$, with $p_i = \text{tr}(\overline{\pi_i}^\dagger \overline{\pi_i} \rho^n)$ and $\rho' = \frac{\overline{\pi_i} \rho^n \overline{\pi_i}^\dagger}{p_i}$. Since the interpretation of letcase° coincides with the interpretation of letcase , and $\text{letcase } x = \pi^m \rho^n \text{ in } \{t_0, \dots, t_{2^m-1}\} \rightarrow_{p_i} t_i[\rho'/x]$, we can conclude by Theorem 2.7, and Lemma 3.2 that $(\text{letcase}^\circ x = \pi^m \rho^n \text{ in } \{t_0, \dots, t_{2^m-1}\})_\theta = \sum_i p_i (t_i[\rho'/x])_\theta = (\sum_i p_i t_i[\rho'/x])_\theta$.
- $\sum_i p_i \rho_i \rightsquigarrow \rho'$, with $\rho' = \sum_i p_i \rho_i$. $(\sum_i p_i \rho_i)_\theta = \sum_i p_i \rho_i = (\rho')_\theta$.
- $\sum_i p_i t \rightsquigarrow t$. Let $\llbracket t \rrbracket_\theta = \{(q_j, b_j, e_j)\}_j$. Then, $\llbracket \sum_i p_i t \rrbracket_\theta = \{(p_i q_j, b_j, e_j)\}_{ij}$ and so, $(\sum_i p_i t)_\theta = \sum_{ij} p_i q_j e_j = (\sum_i p_i) \sum_j q_j e_j = \sum_j q_j e_j = (t)_\theta$.
- $(\sum_i p_i t_i)r \rightsquigarrow \sum_i p_i (t_i r)$. Let $\llbracket t_i \rrbracket_\theta = \{(q_{ij}, b_{ij}, f_{ij})\}_j$, $\llbracket r \rrbracket_\theta = \{(h_k, b'_k, e_k)\}_k$, and $f_{ij}(b'_k, e_k) = \{(\ell_{ijkh}, b''_{ijkh}, g_{ijkh})\}_{kh}$. Then, we have that $\llbracket t_i r \rrbracket_\theta$ is equal to $\{(q_{ij} h_k \ell_{ijkh}, b''_{ijkh}, g_{ijkh})\}_{ijkh}$, and $(\sum_i p_i (t_i r))_\theta = \sum_{ijkh} p_i q_{ij} h_k \ell_{ijkh} g_{ijkh}$. On the other hand, $\llbracket \sum_i p_i t_i \rrbracket_\theta = \{(p_i q_{ij}, b_{ij}, f_{ij})\}_{ij}$, and so $\llbracket (\sum_i p_i t_i)r \rrbracket_\theta = \{(p_i q_{ij} h_k \ell_{ijkh}, b''_{ijkh}, g_{ijkh})\}_{ijkh}$. Hence, $(\sum_i p_i t_i)r)_\theta = \sum_{ijkh} p_i q_{ij} h_k \ell_{ijkh} g_{ijkh} = (\sum_i p_i (t_i r))_\theta$.

- Contextual cases: Only two cases need to be checked. All the other cases are analogous to those of the proof of Theorem 2.7.
 - Let $\sum_i p_i t_i \rightsquigarrow \sum_i p_i r_i$, where $t_j \rightsquigarrow r_j$ and $\forall i \neq j, t_i = r_i$. By the induction hypothesis, $(t_j)_\theta = (r_j)_\theta$. Hence, using Lemma 3.2, $(\sum_i p_i t_i)_\theta = \sum_i p_i (t_i)_\theta = \sum_i p_i (r_i)_\theta = (\sum_i p_i r_i)_\theta$.
 - Let $\text{letcase}^\circ x = t$ in $\{s_0, \dots, s_n\} \rightsquigarrow \text{letcase}^\circ x = r$ in $\{s_0, \dots, s_n\}$, where $t \rightsquigarrow r$. Let $\llbracket t \rrbracket_\theta = \{(p_i, b_i, \rho_i)\}_i$ and $\llbracket s_{b_i} \rrbracket_{\theta, x=(\varepsilon, \rho_i)} = \{(q_{ij}, b'_{ij}, e_{ij})\}_j$, then $(\text{letcase}^\circ x = t \text{ in } \{s_0, \dots, s_{2^m-1}\})_\theta = \sum_{ij} p_i q_{ij} e_{ij}$.
On the other hand, let $\llbracket r \rrbracket_\theta = \{(h_k, b'_k, \rho'_k)\}_k$. By the induction hypothesis, $\sum_k h_k \rho'_k = \sum_i p_i \rho_i$. We conclude by inversion that $h_i = p_i$ and $\rho'_i = \rho_i$, which prove the case. \square

C Detailed Proofs of Section 4

C.1 Proof of Lemma 4.3

By induction on t . The only difference between λ_ρ and λ_ρ° are in terms (b^m, ρ^n) , which is not present in λ_ρ° , and $\sum_i p_i t_i$, which is not present in λ_ρ . Hence, we can prove both calculi at the same time. We use \vdash generically to refer also to \Vdash where it is also valid.

- Let $t = x$. Then $B = A$. By Lemma 4.1, $\Gamma, \Delta \vdash r : A$. Notice that $t[r/x] = r$.
- Let $t = y$. Then, by Lemmas 4.1 and 4.2, $\Gamma, \Delta \vdash y : B$. Notice that $t[r/x] = y$.
- Let $t = \lambda y.s$. Then $B = C \multimap D$ and, by inversion, $\Gamma, x : A, y : C \vdash s : D$. Then, by the induction hypothesis, $\Gamma, y : C, \Delta \vdash s[r/x] : D$, so, by rule \multimap_o , $\Gamma, \Delta \vdash \lambda y.(s[r/x]) : C \multimap D$. Notice that $\lambda y.(s[r/x]) = (\lambda y.s)[r/x]$.
- Let $t = t_1 t_2$. Then $\Gamma, x : A = \Gamma_1, \Gamma_2$, with $\Gamma_1 \vdash t_1 : C \multimap B$ and $\Gamma_2 \vdash t_2 : C$.
 - If $x : A \in \Gamma_1$, then, by the induction hypothesis $\Gamma_1 \setminus \{x : A\}, \Delta \vdash t_1[r/x] : C \multimap B$, so by rule \multimap_e , $\Gamma_1 \setminus \{x : A\}, \Gamma_2, \Delta \vdash t_1[r/x] t_2 : B$. Notice that $\Gamma_1 \setminus \{x : A\}, \Gamma_2 = \Gamma$ and $t_1[r/x] t_2 = (t_1 t_2)[r/x]$.
 - If $x : A \in \Gamma_2$, then, by the induction hypothesis $\Gamma_2 \setminus \{x : A\}, \Delta \vdash t_2[r/x] : C$, so by rule \multimap_e , $\Gamma_1, \Gamma_2 \setminus \{x : A\}, \Delta \vdash t_1(t_2[r/x]) : B$. Notice that $\Gamma_1, \Gamma_2 \setminus \{x : A\} = \Gamma$ and $t_1(t_2[r/x]) = (t_1 t_2)[r/x]$.
- Let $t = \rho^n$. Then $B = n$. By Lemmas 4.1 and 4.2, $\Gamma, \Delta \vdash \rho^n : n$. Notice that $t[r/x] = \rho^n$.
- Let $t = U^m s$. Then $B = n$ and $\Gamma, x : A \vdash s : n$. Then, by the induction hypothesis, $\Gamma, \Delta \vdash s[r/x] : n$. So, by rule u , $\Gamma, \Delta \vdash U^m(s[r/x]) : n$. Notice that $U^m(s[r/x]) = (U^m s)[r/x]$.
- Let $t = \pi^m s$. Then $B = (m, n)$ and $\Gamma, x : A \vdash s : n$. Then, by the induction hypothesis, $\Gamma, \Delta \vdash s[r/x] : n$. So, by rule m , $\Gamma, \Delta \vdash \pi^m(s[r/x]) : (m, n)$. Notice that $\pi^m(s[r/x]) = (\pi^m s)[r/x]$.
- Let $t = t_1 \otimes t_2$. Then $B = n_1 + n_2$, $\Gamma, x : A = \Gamma_1, \Gamma_2$ with $\Gamma_i \vdash t_i : n_i$ for $i = 1, 2$. Let $x : A \in \Gamma_i$ for some $i = 1, 2$. Then, by the induction hypothesis, $\Gamma_i \setminus \{x : A\}, \Delta \vdash t_i[r/x]$, so by rule \otimes , either $\Gamma, \Delta \vdash t_1[r/x] \otimes t_2 : n_1 + n_2$, or $\Gamma, \Delta \vdash t_1 \otimes t_2[r/x] : n_1 + n_2$. In the first case, notice that $t_1[r/x] \otimes t_2 = (t_1 \otimes t_2)[r/x]$, and in the second, $t_1 \otimes t_2[r/x] = (t_1 \otimes t_2)[r/x]$.

- Let $t = (b^m, \rho^n)$. Then $B = (m, n)$. By Lemmas 4.1 and 4.2, $\Gamma, \Delta \vdash (b^m, \rho^n) : (m, n)$. Notice that $t[r/x] = (b^m, \rho^n)$.
- Let $t = \sum_i p_i t_i$. Then $\Gamma, x : A \vdash t_i : B$ and so, by the induction hypothesis, $\Gamma, \Delta \vdash t_i[r/x] : B$. Therefore, by rule $+$, $\Gamma, \Delta \vdash \sum_i p_i t_i[r/x] : B$.
- Let $t = \text{letcase } y = s \text{ in } \{t_0, \dots, t_{2^m-1}\}$. $y : n \vdash t_i : B$, for $i = 0, \dots, 2^m - 1$, and, $\Gamma \vdash s : (m, n)$. By the induction hypothesis, $\Gamma, \Delta \vdash s[r/x] : (m, n)$. So, by rule lc , $\Gamma, \Delta \vdash \text{letcase } y = s[r/x] \text{ in } \{t_0, \dots, t_{2^m-1}\} : B$. Notice that $\text{letcase } y = s[r/x] \text{ in } \{t_0, \dots, t_{2^m-1}\} = (\text{letcase } y = s \text{ in } \{t_0, \dots, t_{2^m-1}\})[r/x]$. \square

C.2 Proof of Theorem 4.4

By induction on the relations \longrightarrow_p and \rightsquigarrow .

1. – Let $t = (\lambda x.t')s$, $r = t'[r/s]$ and $p = 1$. Then $\Gamma \vdash (\lambda x.t')s : A$, so, $\Gamma_1 \vdash \lambda x.t' : B \multimap A$ and $\Gamma_2 \vdash s : B$, with $\Gamma = \Gamma_1, \Gamma_2$. Hence, $\Gamma_1, x : B \vdash t' : A$, and so, by Lemma 4.3, $\Gamma \vdash t'[s/x] : A$.
- Let $t = \text{letcase } x = (b^m, \rho^n) \text{ in } \{t_0, \dots, t_{2^m-1}\}$, $r = t_{b^m}[\rho^n/x]$ and $p = 1$. Then, by inversion, $x : n' \vdash t_i : A$, for $i = 0, \dots, 2^m - 1$, and $\Gamma \vdash (b^m, \rho^n) : (m', n')$. So, by inversion again, $m' = m$ and $n' = n$. By rule ax_ρ , $\Gamma \vdash \rho^n : n$. Hence, by Lemma 4.3, $\Gamma \vdash t_{b^m}[\rho^n/x] : A$.
- Let $t = U^m \rho^n$, $r = \rho'^n$ and $p = 1$, with $\rho'^n = \overline{U^m} \rho^n \overline{U^m}^\dagger$. Then $A = n$. By rule ax_ρ , $\Gamma \vdash \rho'^n : n$.
- Let $t = \pi^m \rho^n$, $r = (i^m, \rho_i^n)$, with $\rho_i^n = \frac{\overline{\pi_i} \rho^n \overline{\pi_i}^\dagger}{p}$ and $p = \text{tr}(\overline{\pi_1}^\dagger \overline{\pi_i} \rho^n)$. Then $B = (m, n)$. By rule m , $\Gamma \vdash (i^m, \rho_i^n) : (m, n)$.
- Let $t = \rho_1^n \otimes \rho_2^m$ and $r = \rho$, with $\rho = \rho_1^n \otimes \rho_2^m$. Then, $A = n + m$, with $\vdash \rho_1^n : n$ and $\vdash \rho_2^m : m$. Since ρ is a density matrix of $(n + m)$ -qubits, $\vdash \rho : n + m$.
- Contextual cases: Let $s \longrightarrow_p s'$, then
 - Consider $t = \lambda x.s$ and $r = \lambda x.s'$. Then $A = B \multimap C$ and $\Gamma, x : B \vdash s : C$. So, by the induction hypothesis, $\Gamma, x : B \vdash s' : C$ and by rule \multimap_i , $\Gamma \vdash \lambda x.s' : B \multimap C$.
 - Consider $t = t's$ and $r = t's'$. Then $\Gamma = \Gamma_1, \Gamma_2$, with $\Gamma_1 \vdash t' : B \multimap A$ and $\Gamma_2 \vdash s : B$. By the induction hypothesis, $\Gamma_2 \vdash s' : B$, so by rule \multimap_e , $\Gamma \vdash t's' : A$.
 - Consider $t = st'$ and $r = s't'$. Then $\Gamma = \Gamma_1, \Gamma_2$, with $\Gamma_1 \vdash s : B \multimap A$ and $\Gamma_2 \vdash t' : B$. By the induction hypothesis, $\Gamma_1 \vdash s' : B \multimap A$, so by rule \multimap_e , $\Gamma \vdash s't' : A$.
 - Consider $t = U^m s$ and $r = U^m s'$. Then $A = n$ and $\Gamma \vdash s : n$. By the induction hypothesis $\Gamma \vdash s' : n$, so by rule u , $\Gamma \vdash U^m s' : n$.
 - Consider $t = \pi^m s$ and $r = \pi^m s'$. Then $A = n$ and $\Gamma \vdash s : n$. By the induction hypothesis $\Gamma \vdash s' : n$, so by rule m , $\Gamma \vdash \pi^m s' : n$.
 - Consider $t = t' \otimes s$ and $r = t' \otimes s'$. Then $A = n + m$ and $\Gamma = \Gamma_1, \Gamma_2$, with $\Gamma_1 \vdash t' : n$ and $\Gamma_2 \vdash s : m$. By the induction hypothesis $\Gamma_2 \vdash s' : m$, so by rule \otimes , $\Gamma \vdash t' \otimes s' : n + m$.

- Consider $t = s \otimes t'$ and $r = s' \otimes t'$. Then $A = n + m$ and $\Gamma = \Gamma_1, \Gamma_2$, with $\Gamma_1 \vdash s : n$ and $\Gamma_2 \vdash t' : m$. By the induction hypothesis $\Gamma_2 \vdash s' : m$, so by rule \otimes , $\Gamma \vdash t' \otimes s' : n + m$.
 - Consider $t = \text{letcase } x = s \text{ in } \{t_0, \dots, t_{2^m-1}\}$ and $r = \text{letcase } x = s' \text{ in } \{t_0, \dots, t_{2^m-1}\}$. Then $x : n \vdash t_i : A$ for $i = 0, \dots, 2^m - 1$, and $\Gamma \vdash s : (m, n)$. So, by the induction hypothesis, $\Gamma \vdash s' : (m, n)$ and by rule lc , $\Gamma \vdash \text{letcase } x = s' \text{ in } \{t_0, \dots, t_{2^m-1}\} : A$. \square
2. – Let $t = (\lambda x.t')s$ and $r = t'[s/x]$. Analogous to the same rule in λ_ρ .
- Let $t = \text{letcase}^\circ x = \pi^m \rho^n$ in $\{t_0, \dots, t_{2^m-1}\}$ and $r = \sum_i p_i t_i [\rho_i^n/x]$, with $\rho_i^n = \frac{\overline{\pi_i} \rho^n \overline{\pi_i}^\dagger}{p_i}$ and $p_i = \text{tr}(\overline{\pi_i}^\dagger \overline{\pi_i} \rho^n)$. Then $\Gamma \Vdash \pi^m \rho^n : (m, n)$ and $x : n \Vdash t_i : A$. By Lemma 4.3, $\Gamma \Vdash t_i [\rho_i^n/x] : A$, then, by rule $+$, $\Gamma \Vdash \sum_i p_i t_i [\rho_i^n/x] : A$.
- Let $t = U^m \rho^n$ and $r = \rho'^m$, with $\overline{U^m} \rho^n \overline{U^m}^\dagger = \rho'^m$. Analogous to the same rule in λ_ρ .
- Let $t = \rho_1^n \otimes \rho_2^m$ and $r = \rho$, with $\rho = \rho_1^n \otimes \rho_2^m$. Analogous to the same rule in λ_ρ .
- Let $t = \sum_i p_i \rho_i$ and $r = \rho'$, with $\rho' = \sum_i p_i \rho_i$. Then, $\Gamma \Vdash \sum_i p_i \rho_i : n$, and by rule ax_ρ , $\Gamma \Vdash \rho' : n$.
- Let $t = \sum_i p_i r$. Then, $\Gamma \Vdash r : A$.
- Let $t = (\sum_i p_i t_i)r$ and $\sum_i p_i (t_i r)$. Then, $\Gamma = \Gamma_1, \Gamma_2$, $\Gamma_1 \Vdash t_i : B \multimap A$ and $\Gamma_2 \Vdash r : B$. Therefore, by rule \multimap_e , $\Gamma_1, \Gamma_2 \Vdash t_i r : A$, and by rule $+$, $\Gamma_1, \Gamma_2 \Vdash \sum_i p_i (t_i r) : A$.
- Contextual cases. All the contextual cases are analogous to the same rules in λ_ρ , except for the contextual rule of \sum : Consider $t = \sum_i p_i t_i$ and $r = \sum_i p_i r_i$, with $t_j \rightsquigarrow r_j$, and $\forall i \neq j, t_i = r_i$. By inversion, $\Gamma \Vdash t_i : A$. By the induction hypothesis, $\forall i, \Gamma \Vdash r_i : A$. Then, by rule $+$, $\Gamma \Vdash \sum_i p_i r_i$. \square

C.3 Proof of Lemma 4.6

1. We proceed by induction on v .
 - Let $v = x$. Then we are done, since variables do not rewrite.
 - Let $v = \lambda x.v'$. By the induction hypothesis, v' does not rewrite, and so v neither does.
 - Let $v = w_1 \otimes w_2$. By the induction hypothesis, nor w_1 nor w_2 rewrite, and the only rule rewriting a \otimes in head position needs both w_1 and w_2 to be density matrices, which are not according to the grammar.
 - Let $v = \rho^n$. Then we are done, since density matrices are constants and do not rewrite.
 - Let $v = (b^m, \rho^n)$. Then we are done, since pairs are constants and do not rewrite.
2. We proceed by induction on v . The only difference with the previous case is that the last term is not present, and a new term is introduced. Hence, let $v = \sum_i p_i w_i$. The only possible rewrite would be if there were some $w_i = w_j$, which is explicitly excluded from the grammar. So, this term does not rewrite \square

C.4 Proof of Theorem 4.7

We relax the hypotheses and prove the theorem for open terms as well. That is:

1. If $\Gamma \vdash t : A$, then either t is a value, there exist n, p_1, \dots, p_n , and r_1, \dots, r_n such that $t \rightarrow_{p_i} r_i$, or t contains a free variable, and t does not rewrite.
2. If $\Gamma \Vdash t : A$, then either t is a value^o, there exists r such that $t \rightsquigarrow r$, or t contains a free variable, and t does not rewrite.

The proofs proceeds as follows.

1. We proceed by induction on the derivation of $\vdash t : A$.
 - Let $\Gamma, x : A \vdash x : A$ as a consequence of rule ax . Then, we are done since x is a free variable and does not rewrite.
 - Let $\Gamma \vdash \lambda x.t : A \multimap B$ as a consequence of $\Gamma, x : A \vdash t : B$ and rule \multimap_i . Then, by the induction hypothesis, either
 - t is not a value and there exist n, p_1, \dots, p_n and r_1, \dots, r_n such that $t \rightarrow_{p_i} r_i$, which case $\lambda x.t \rightarrow_{p_i} \lambda x.r_i$;
 - t is a value, in which case $\lambda x.t$ is a value as well; or
 - t contains a free variable, and t does not rewrite, in which case the same happens to $\lambda x.t$.
 - Let $\Gamma, \Delta \vdash tr : B$ as a consequence of $\Gamma \vdash t : A \multimap B$, $\Delta \vdash r : A$ and rule \multimap_e . Then, by the induction hypothesis, one of the following cases happens:
 - There exist n, p_1, \dots, p_n , and t_1, \dots, t_n such that $t \rightarrow_{p_i} t_i$, in which case $tr \rightarrow_{p_i} t_i r$.
 - There exist n, p_1, \dots, p_n and r_1, \dots, r_n such that $r \rightarrow_{p_i} r_i$, in which case $tr \rightarrow_{p_i} tr_i$.
 - t is a value and r does not rewrite. The only values which can be typed by $A \multimap B$ are:
 - * $t = x$, in which case xr contains a free variable and does not rewrite.
 - * $t = \lambda x.v$, in which case $(\lambda x.v)r \rightarrow_1 v[r/x]$.
 - t is not a value, contains a free variable, and does not rewrite, and r does not rewrite, in which case tr contains a free variable and does not rewrite.
 - Let $\Gamma \vdash \rho^n : n$ as a consequence of rule ax_ρ . Then, we are done since ρ^n is a value.
 - Let $\Gamma \vdash U^m t : n$ as a consequence of $\Gamma \vdash t : n$ and rule u . Then, by the induction hypothesis, one of the following cases happens:
 - t is a value. The only values which can be typed by n are:
 - * $t = x$, in which case $U^m x$ contains a free variable and does not rewrite.
 - * $t = \bigotimes x_i$, in which case $U^m \bigotimes x_i$ contains free variables and does not rewrite.
 - * $t = \rho^n$, in which case $U^m \rho^n \rightarrow_1 \rho'$, with $\rho' = \overline{U^m} \rho^n \overline{U^m}^\dagger$.
 - There exist n, p_1, \dots, p_n and t_1, \dots, t_n such that $t \rightarrow_{p_i} t_i$, in which case $U^m t \rightarrow_{p_i} t_i$;

- t contains a free variable and does not rewrite, in which case the same is true for $U^m t$.
 - Let $\Gamma \vdash \pi^m t : (m, n)$ as a consequence of $\Gamma \vdash t : n$ and rule **m**. Then, by the induction hypothesis, one of the following cases happens:
 - t is a value. The only values which can be typed by n are:
 - * $t = x$, in which case $\pi^m x$ contains a free variable and does not rewrite.
 - * $t = \bigotimes x_i$, in which case $\pi^m \bigotimes x_i$ contains free variables and does not rewrite.
 - * $t = \rho^n$, in which case $\pi^m \rho^n \rightarrow_{p_i} (i, \rho_i^n)$, with $p_i = \text{tr}(\overline{\pi_i}^\dagger \overline{\pi_i} \rho^n)$ and $\rho_i^n = \frac{\overline{\pi_i} \rho^n \overline{\pi_i}^\dagger}{p_i}$.
 - There exist n, p_1, \dots, p_n and t_1, \dots, t_n such that $t \rightarrow_{p_i} t_i$, in which case $\pi^m t \rightarrow_{p_i} t_i$;
 - t contains a free variable and does not rewrite, in which case the same is true for $\pi^m t$.
 - Let $\Gamma, \Delta, \vdash t \otimes r : n + m$ as a consequence of $\Gamma \vdash t : n$, $\Delta \vdash r : m$ and rule \otimes . Then, by the induction hypothesis, one of the following happens:
 - There exist k, p_1, \dots, p_n , and t_1, \dots, t_k such that $t \rightarrow_{p_i} t_i$, in which case $t \otimes r \rightarrow_{p_i} t_i \otimes r$.
 - There exist k, p_1, \dots, p_n , and r_1, \dots, r_k such that $r \rightarrow_{p_i} r_i$, in which case $t \otimes r \rightarrow_{p_i} t \otimes r_i$.
 - t is a value and r does not rewrite. The only values which can be typed by n are:
 - * $t = x$, then $t \otimes r$ contains a free variable and does not rewrite.
 - * $t = \bigotimes x_i$, then $t \otimes r$ contains free variables and does not rewrite.
 - * $t = \rho^n$, then:
 - If $r = \rho^m$, $t \otimes r \rightarrow_1 \rho'$, with $\rho' = \rho^n \otimes \rho^m$.
 - If r contains a free variable and does not rewrite, then the same is true for $t \otimes r$.
 - t contains a free variable and does not rewrite, and r does not rewrite, in which case $t \otimes r$ contains a free variable and does not rewrite.
 - Let $\Gamma \vdash (b^m, \rho^n) : (m, n)$ as a consequence of rule **ax_{am}**. Then, we are done since (b^m, ρ^n) is a value.
 - Let $\Gamma \vdash \text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^m-1}\} : A$ as a consequence of $x : n \vdash t_i : A$ for $i = 0, \dots, 2^m - 1$, $\Gamma \vdash r : (m, n)$, and rule **lc**. By the induction hypothesis, the possible cases for r are:
 - r is a value. The possible values which can be typed by (m, n) are:
 - * $r = y$, in which case $\text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^m-1}\}$ contains a free variable and does not reduce.
 - * $r = (b^m, \rho^n)$, in which case $\text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^m-1}\} \rightarrow_1 t_{b^m}[\rho^n/x]$.
 - There exist k, p_1, \dots, p_k , and r_1, \dots, r_k such that $r \rightarrow_{p_i} r_i$, and $\text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^m-1}\} \rightarrow_{p_i} \text{letcase } x = r_i \text{ in } \{t_0, \dots, t_{2^m-1}\}$.
 - r contains a free variable and does not rewrite, in which case the same is true for $\text{letcase } x = r \text{ in } \{t_0, \dots, t_{2^m-1}\}$.
2. We proceed by induction on the derivation of $\Gamma \Vdash t : A$.

- Let $\Gamma, x : A \Vdash x : A$ as a consequence of rule ax . Then, we are done since x is a free variable and does not rewrite.
- Let $\Gamma \Vdash \lambda x.t : A \multimap B$ as a consequence of $\Gamma, x : A \Vdash t : B$ and rule \multimap_i . Then, by the induction hypothesis, either
 - t is not a value[◦] and there exists r such that $t \rightsquigarrow r$, which case $\lambda x.t \rightsquigarrow \lambda x.r$;
 - t is a value[◦], in which case $\lambda x.t$ is a value[◦] as well; or
 - t contains a free variable, and t does not rewrite, in which case the same happens to $\lambda x.t$.
- Let $\Gamma, \Delta \Vdash tr : B$ as a consequence of $\Gamma \Vdash t : A \multimap B$, $\Delta \Vdash r : A$ and rule \multimap_e . Then, by the induction hypothesis, one of the following cases happens:
 - There exists t' such that $t \rightsquigarrow t'$, in which case $tr \rightsquigarrow t'r$.
 - There exists r' such that $r \rightsquigarrow r'$, in which case $tr \rightsquigarrow tr'$.
 - t is a value[◦] and r does not rewrite. The only values[◦] which can be typed by $A \multimap B$ are:
 - * $t = x$, in which case tr contains a free variable and does not rewrite.
 - * $t = \lambda x.v$, in which case $(\lambda x.v)r \rightsquigarrow v[r/x]$.
 - * $t = \sum_i p_i t_i$, where $\Gamma \Vdash t_i : A \multimap B$. Then, $tr \rightsquigarrow \sum_i p_i (t_i r)$.
 - t is not a value[◦], contains a free variable, and does not rewrite, and r does not rewrite, in which case, if t is not a sum, tr contains a free variable and does not rewrite. If $t = \sum_i p_i t_i$ is a sum, $tr \rightsquigarrow \sum_i p_i (t_i r)$.
- Let $\Gamma \Vdash \rho^n : n$ as a consequence of rule ax_ρ . Then, we are done since ρ^n is a value[◦].
- Let $\Gamma \Vdash U^m t : n$ as a consequence of $\Gamma \Vdash t : n$ and rule u . Then, by the induction hypothesis, one of the following cases happens:
 - t is a value[◦]. Since $\lambda x.v$ cannot be typed by n , the only values[◦] that can be typed by n are either ρ^n , or they contain free variables:
 - * Let $t = \rho^n$, then $U^m \rho^n \rightsquigarrow \rho'$, with $\rho' = \overline{U^m} \rho^n \overline{U^m}^\dagger$.
 - * Let t contain a free variable. Notice that it can only be either a free variable by itself, a tensor of values[◦] containing free variables, or a linear combination of different values[◦] containing free variables. In any case, t contains a free variable and does not rewrite. Hence, $U^m t$ contains a free variable and does not rewrite.
 - There exists r such that $t \rightsquigarrow r$, in which case $U^m t \rightsquigarrow r$;
 - t contains a free variable and does not rewrite, in which case the same is true for $U^m t$.
- Let $\Gamma \Vdash \pi^m t : (m, n)$ as a consequence of $\Gamma \Vdash t : n$ and rule m . Then, by the induction hypothesis, one of the following cases happens:
 - t is a value[◦]. Since $\lambda x.v$ cannot be typed by n , the only values[◦] that can be typed by n are either ρ^n , or they contain free variables:
 - * Let $t = \rho^n$, then $\pi^m \rho^n \rightsquigarrow \rho'$, with $\rho' = \sum_i \overline{\pi_i} \rho^n \overline{\pi_i}^\dagger$.
 - * Let t contain a free variable. Notice that it can only be either a free variable by itself, a tensor of values[◦] containing free variables, or a linear combination of different values[◦] containing free

- variables. In any case, t contains a free variable and does not rewrite. Hence, $\pi^m t$ contains a free variable and does not rewrite.
- There exists r such that $t \rightsquigarrow r$, in which case $\pi^m t \rightsquigarrow r$;
 - t contains a free variable and does not rewrite, in which case the same is true for $\pi^m t$.
- Let $\Gamma, \Delta, \Vdash t \otimes r : n + m$ as a consequence of $\Gamma \Vdash t : n$, $\Delta \Vdash r : m$ and rule \otimes . Then, by the induction hypothesis, one of the following happens:
- There exists t' such that $t \rightsquigarrow t'$, in which case $t \otimes r \rightsquigarrow t' \otimes r$.
 - There exists r' such that $r \rightsquigarrow r'$, in which case $t \otimes r \rightsquigarrow t \otimes r'$.
 - t is a value^o and r does not rewrite. The only values^o that can be typed by n are either ρ^n , or they contain free variables.
 - * Let $t = \rho^n$, then:
 - If $r = \rho^m$, $t \otimes r \rightsquigarrow \rho'$, with $\rho' = \rho^n \otimes \rho^m$.
 - If r contains a free variable and does not rewrite, then the same is true for $t \otimes r$.
 - * Let t contain a free variable. Then $t \otimes r$ contains a free variable and does not rewrite.
 - t contains a free variable and does not rewrite, and r does not rewrite, in which case $t \otimes r$ contains a free variable and does not rewrite.
- Let $\Gamma \Vdash \text{letcase}^\circ x = r$ in $\{t_0, \dots, t_{2^m-1}\} : A$ as a consequence of $x : n \Vdash t_i : A$ for $i = 0, \dots, 2^m - 1$, $\Gamma \Vdash r : (m, n)$, and rule lc . By the induction hypothesis, the possible cases for r are:
- r is a value^o. The only possible values^o that can be typed by (m, n) are variables or linear combination of variables. In any case, we have that $\text{letcase}^\circ x = r$ in $\{t_0, \dots, t_{2^m-1}\}$ contains at least a free variable and does not rewrite.
 - There exists r' such that $r \rightsquigarrow r'$, in which case, we have to distinguish two cases:
 - * $r \neq \pi^m \rho^n$, and therefore $\text{letcase}^\circ x = r$ in $\{t_0, \dots, t_{2^m-1}\} \rightsquigarrow \text{letcase}^\circ x = r'$ in $\{t_0, \dots, t_{2^m-1}\}$.
 - * $r = \pi^m \rho^n$, and therefore $\text{letcase}^\circ x = r$ in $\{t_0, \dots, t_{2^m-1}\} \rightsquigarrow \sum_i p_i t_i [\rho_i^n / x]$, where $p_i = \text{tr}(\overline{\pi_i}^\dagger \overline{\pi_i} \rho^n)$ and $\rho_i^n = \frac{\overline{\pi_i} \rho^n \overline{\pi_i}^\dagger}{p_i}$.
 - r contains a free variable and does not rewrite, in which case the same is true for $\text{letcase}^\circ x = r$ in $\{t_0, \dots, t_{2^m-1}\}$.
- Let $\Gamma \Vdash \sum_i p_i t_i : A$ as a consequence of $\Gamma \Vdash t_i : A$, $\sum_i p_i = 1$, and rule $+$. If $\sum_i p_i t_i$ is a value^o, then we are done. If it is not a value, then one of the following cases is true:
- $t_j = t_k$ for some $j \neq k$, in which case $\sum_i p_i t_i \rightsquigarrow (\sum_{i \neq j, k} p_i t_i) + (p_j + p_k) t_j$.
 - At least one t_i is not a value. By the induction hypothesis, if t_i is not a value, either it rewrites, or it contains a free variable and does not rewrite. If at least one t_i rewrites, then $\sum_i p_i t_i$ rewrites. If none of these rewrites and at least one contains a free variable, then $\sum_i p_i t_i$ does not rewrite and contain a free variable. \square