

```
movl    $111,%ebx    #START MARKER
.byte   100,103,144  #START MARKER
.L22:
vmovapd 0(%r13,%rax),%ymm0
vfmadd213pd (%r14,%rax),%ymm1,%ymm0
vmovapd %ymm0, (%r12,%rax)
addq    $32,%rax
cmpq    %rax,%r15
jne     .L22

movl    $222,%ebx    #END MARKER
.byte   100,103,144  #END MARKER
```

```
mov x1, #111 //START
.byte 213,3,32,31 //START
.L18:
ldr q2, [x20, x0]
ldr q1, [x21, x0]
fmla v1.2d, v2.2d, v0.2d
str q1, [x19, x0]
add x0, x0, #16
cmp x22, x0
bne .L18

mov x1, #222 //END
.byte 213,3,32,31 //END
```



generic load	load_latency: {gpr: 4, xmm: 4, ymm: 4, zmm: 4}
mnemonic	load_throughput: {port_pressure: [0,0,0,0.5 ... ,0]}
specific operand description	<div><div>- name: vfmadd213pd</div><div>operands:</div><div><div>- class: "register"</div><div>name: "ymm"</div><div>source: true</div><div>destination: false</div><div>- class: "register"</div><div>name: "ymm"</div><div>source: true</div><div>destination: false</div><div>- class: "register"</div><div>name: "ymm"</div><div>source: true</div><div>destination: true</div></div></div>
performance information	throughput: 0.5 latency: 4 # 0 DV 1 2 D 3 D 4 5 6 7 port_pressure: [0.5,0,0.5,0.5,0.5,0.5,0.5,0,0,0,0]



Throughput Analysis

* - Instruction not bound to a port

Port Pressure in cycles								
0	1	2 - 2D	3 - 3D	4	5	6		
0.50	0.50	0.5 0.5 0.5 0.5	0.5 0.5 0.5 0.5					.L22: vmovapd 0(%r13,%rax),%ymm0 vfmadd213pd (%r14,%rax), %ymm1, %ymm0 vmovapd %ymm0, (%r12,%rax)
0.25 0.25	0.25 0.25	0.5	0.5	1.0	0.25 0.25	0.25 0.25		addq \$32,%rax cmpq %rax,%r15 jne .L22
1.00	1.00	1.5 1.0	1.5 1.0	1.00	0.50	0.50	*	

Critical Path Analysis

180	4.0	vmovapd 0(%r13,%rax), %ymm0
181	4.0	vfmadd213pd (%r14,%rax), %ymm1, %ymm0
182	5.0	vmovapd %ymm0, (%r12,%rax)
13.0		

Loop-carried Dependencies Analysis

183	1.0	addq \$32, %rax	[183]
-----	-----	-----------------	-------