

ON A RANDOM NUMBER OF DISORDERS

BY

KRZYSZTOF SZAJOWSKI* (WROCLAW)

Abstract. We register a random sequence which has the following properties: it has three segments being the homogeneous Markov processes. Each segment has his own one step transition probability law and the length of the segment is unknown and random. It means that at two random moments θ_1, θ_2 , where $0 \leq \theta_1 \leq \theta_2$, the source of observations is changed and the first observation in new segment is chosen according to new transition probability starting from the last state of the previous segment. In effect the number of homogeneous segments is random. The transition probabilities of each process are known and *a priori* distribution of the disorder moments is given. The former research on such problem has been devoted to various questions concerning the distribution changes. The random number of distributional segments creates new problems in solutions with relation to analysis of the model with deterministic number of segments. Two cases are presented in details. In the first one the objectives is to stop on or between the disorder moments while in the second one our objective is to find the strategy which immediately detects the distribution changes. Both problems are reformulated to optimal stopping of the observed sequences. The detailed analysis of the problem is presented to show the form of optimal decision function.

2000 AMS Mathematics Subject Classification: Primary: 60G40 60K99; Secondary: 90D60.

Key words and phrases: disorder problem, sequential detection, optimal stopping, Markov process, change point, double optimal stopping

* Affiliation: Institute of Mathematics, Polish Academy of Science, Śniadeckich 8, 00-956 Warszawa, Poland

1. INTRODUCTION

Suppose that the process $X = \{X_n, n \in \mathbb{N}\}$, $\mathbb{N} = \{0, 1, 2, \dots\}$, is observed sequentially. The process is obtained from three Markov processes by switching between them at two random moments of time, θ_1 and θ_2 . Our objective is to detect these moments based on observation of X .

Such model of data appears in many practical problems of the quality control (see Brodsky and Darkhovsky [5], Shewhart [17] and in the collection of the papers [2]), traffic anomalies in networks (in papers by Dube and Mazumdar [6], Tartakovsky et al. [22]), epidemiology models (see Baron [1]). In management of manufacture it happens that the plants which produce some details changes their parameters. It makes that the details change their quality. Production can be divided into three sorts. Assuming that at the beginning of production process the quality is highest, from some moment θ_1 the products should be classified to lower sort and beginning with the moment θ_2 the details should be categorized as having the lowest quality. The aim is to recognize the moments of these changes.

Shiryayev [18, 19] solved the disorder problem of the independent random variables with one disorder where the mean distance between disorder time and the moment of its detection was minimized. The probability maximizing approach to the problem was used by Bojdecki [3] and the stopping time which is in a given neighborhood of the moment of disorder with maximal probability was found. The disorders in more complicated dependence structures of switched sequences are subject of investigation by Pelkowitz [14, 15], Yakir [24], Mustakides [11], Lai [9, 10], Fuh [7], Tartakovsky and Veeravalli [23]. The probability maximizing approach to such problems with two disorders was considered by Yoshida [25], Szajowski [20, 21] and Sarnowski and Szajowski [16]. Yoshida [25] investigated the problem of optimal stopping the observation of the process X so as to maximize the probability that the distance between the moments of disorder θ_i and their estimates, the stopping times τ_i , $i = 1, 2$, will not exceed given numbers (for each disorder independently). This question has been reformulated by Szajowski [21] to the simultaneous

detection of both disorders under requirement that the performance of procedure is globally measured for both detections and it has been extended to the case with unknown distribution between disorders by Sarnowski and Szajowski [16] (see also papers by Bojdecki and Hosza [4] for related approach with switching sequences of independent random variables). The method of solution is based on a transformation of the model to the double optimal stopping problem for markovian function of some statistics (see Haggstrom [8], Nikolaev [12]). The strategy which stops the process between the first and the second disorder with maximal probability has been constructed by Szajowski [20]. The considerations are inspired by the problem regarding how we can protect ourselves against a second fault in a technological system after the occurrence of an initial fault or by the problem of detection the beginning and the end of an epidemic.

The paper is devoted to a generalization of the double disorder problem considered both in [20] and [21] in which immediate switch from the first preliminary distribution to the third one is possible (i.e. it is possible that the random variables θ_1 and θ_2 are equal with a positive probability). It is also possible that we observe the homogeneous data without disorder when both disorder moments are equal to 0. The extension leads to serious difficulties in the construction of an equivalent double optimal stopping model. The formulation of the problem can be found in Section 2. The main results are subject of Sections 4 (see Theorem 4.1) and 5.

2. FORMULATION OF DETECTION PROBLEMS

Let $(X_n)_{n \in \mathbb{N}}$ be an observable sequence of random variables defined on the space $(\Omega, \mathcal{F}, \mathbf{P})$ with values in $(\mathbb{E}, \mathcal{B})$, where \mathbb{E} is a Borel subset of \mathbf{R} . On $(\mathbb{E}, \mathcal{B})$ there is σ -additive measure μ . On the same probability space there are defined random variables θ_1, θ_2 with values in \mathbb{N} and the following distributions:

$$(2.1) \quad \mathbf{P}(\theta_1 = j) = \mathbb{I}_{\{j=0\}}(j)\pi + \mathbb{I}_{\{j>0\}}(j)\bar{\pi}p_1^{j-1}q_1,$$

$$(2.2) \quad \mathbf{P}(\theta_2 = k \mid \theta_1 = j) = \mathbb{I}_{\{k=j\}}(k)\rho + \mathbb{I}_{\{k>j\}}(k)\bar{\rho}p_2^{k-j-1}q_2$$

where $j = 0, 1, 2, \dots$, $k = j, j + 1, j + 2, \dots$, $\bar{\pi} = 1 - \pi$, $\bar{\rho} = 1 - \rho$. Additionally we consider Markov processes $(X_n^i, \mathcal{G}_n^i, \mathbf{P}_x^i)$ on $(\Omega, \mathcal{F}, \mathbf{P})$, $i = 0, 1, 2$, where σ -fields \mathcal{G}_n^i are the smallest σ -fields for which $(X_n^i)_{n=0}^\infty$, $i = 0, 1, 2$, are adapted, respectively. Let us define process $(X_n)_{n \in \mathbb{N}}$ in the following way:

$$(2.3) X_n = X_n^0 \mathbb{I}_{\{\theta_1 > n\}} + X_n^1 \mathbb{I}_{\{X_{\theta_1-1}^1 = X_{\theta_1-1}^0, \theta_1 \leq n < \theta_2\}} + X_n^2 \mathbb{I}_{\{X_{\theta_2-1}^2 = X_{\theta_2-1}^1, \theta_2 \leq n\}}.$$

We make inference on θ_1 and θ_2 from the observable sequence $(X_n, n \in \mathbb{N})$ only. It should be emphasized that the sequence $(X_n, n \in \mathbb{N})$ is not markovian under admitted assumption as it has been mentioned in [20], [24] and [6]. However, the sequence satisfies the Markov property given θ_1 and θ_2 (see Szajowski [21] and Moustakides [11]). Thus for further consideration we define filtration $\{\mathcal{F}_n\}_{n \in \mathbb{N}}$, where $\mathcal{F}_n = \sigma(X_0, X_1, \dots, X_n)$, related to real observation. Variables θ_1, θ_2 are not stopping times with respect to \mathcal{F}_n and σ -fields \mathcal{G}_n^\bullet . Moreover, we have knowledge about the distribution of (θ_1, θ_2) independent of any observation of the sequence $(X_n)_{n \in \mathbb{N}}$. This distribution, called the *a priori distribution* of (θ_1, θ_2) is given by (2.1) and (2.2).

It is assumed that the measures $\mathbf{P}_x^i(\cdot)$ on \mathcal{F} , $i = 0, 1, 2$, have following representation. For any $B \in \mathcal{B}$ we have

$$\mathbf{P}_x^i(\omega : X_1^i \in B) = \mathbf{P}(X_1^i \in B | X_0^i = x) = \int_B f_x^i(y) \mu(dy) = \int_B \mu_x^i(dy) = \mu_x^i(B),$$

where the functions $f_x^i(\cdot)$ are different and $f_x^i(y)/f_x^{(i+1) \bmod 3}(y) < \infty$ for $i = 0, 1, 2$ and all $x, y \in \mathbb{E}$. We assume that the measures μ_x^i , $x \in \mathbb{E}$ are known in advance.

For any $D_n = \{\omega : X_i \in B_i, i = 1, \dots, n\}$, where $B_i \in \mathcal{B}$, and any $x \in \mathbb{E}$ define

$$\mathbf{P}_x(D_n) = \mathbf{P}(D_n | X_0 = x) = \int_{\times_{i=1}^n B_i} S_n(x, \vec{y}_n) \mu(d\vec{y}_n) = \int_{\times_{i=1}^n B_i} \mu_x(d\vec{y}_n) = \mu_x(\times_{i=1}^n B_i),$$

where the sequence of functions $S_n : \times_{i=1}^n \mathbb{E} \rightarrow \mathfrak{R}$ is given by (7.5) in Appendix.

The presented model has the following heuristic justification: two disorders take place in the observed sequence (X_n) . They affect distributions by changing their parameters.

The disorders occur at two random times θ_1 and θ_2 , $\theta_1 \leq \theta_2$. They split the sequence of observations into segments, at most three ones. The first segment is described by (X_n^0) , the second one - for $\theta_1 \leq n < \theta_2$ - by (X_n^1) . The third is given by (X_n^2) and is observed when $n \geq \theta_2$. When the first disorder takes the place there is a "switch" from the initial distribution to the distribution with the conditional density f_x^i with respect of the measure μ , where $i = 1$ or $i = 2$, when $\theta_1 < \theta_2$ or $\theta_1 = \theta_2$, respectively. Next, if $\theta_1 < \theta_2$, at the random time θ_2 the distribution of observations becomes μ_x^2 . We assume that the variables θ_1, θ_2 are unobservable directly.

Let \mathcal{S} denote the set of all stopping times with respect to the filtration (\mathcal{F}_n) , $n = 0, 1, \dots$ and $\mathcal{T} = \{(\tau, \sigma) : \tau \leq \sigma, \tau, \sigma \in \mathcal{S}\}$. Two problems with three distributional segments are recalled to investigate them under weaker assumption that there are at most three homogeneous segments.

2.1. Detection of change. Our aim is to stop the observed sequence between the two disorders. This can be interpreted as a strategy for protecting against a second failure when the first has already happened. The mathematical model of this is to control the probability $\mathbf{P}_x(\tau < \infty, \theta_1 \leq \tau < \theta_2)$ by choosing the stopping time $\tau^* \in \mathcal{S}$ for which

$$(2.4) \quad \mathbf{P}_x(\theta_1 \leq \tau^* < \theta_2) = \sup_{\tau \in \mathcal{T}} \mathbf{P}_x(\tau < \infty, \theta_1 \leq \tau < \theta_2).$$

2.2. Disorders detection. Our aim is to indicate the moments of switching with given precision d_1, d_2 (Problem $D_{d_1 d_2}$). We want to determine a pair of stopping times $(\tau^*, \sigma^*) \in \mathcal{T}$ such that for every $x \in \mathbb{E}$

$$(2.5) \quad \mathbf{P}_x(|\tau^* - \theta_1| \leq d_1, |\sigma^* - \theta_2| \leq d_2) = \sup_{\substack{(\tau, \sigma) \in \mathcal{T} \\ 0 \leq \tau \leq \sigma < \infty}} \mathbf{P}_x(|\tau - \theta_1| \leq d_1, |\sigma - \theta_2| \leq d_2).$$

The problem has been considered in [21] under natural simplification that there are three segments of data (*i.e.* there is $0 < \theta_1 < \theta_2$). In the section 5 the problem D_{00} is analyzed.

3. ON SOME *A POSTERIORI* PROCESSES

The formulated problems are translated to the optimal stopping problems for some Markov processes. The important part of the reformulation process is choice of the *statistics* describing knowledge of the decision maker. The *a posteriori* probabilities of some events play the crucial role. Let us define the following *a posteriori* processes (cf. [25], [20]).

$$(3.1) \quad \Pi_n^i = \mathbf{P}_x(\theta_i \leq n | \mathcal{F}_n),$$

$$(3.2) \quad \Pi_n^{12} = \mathbf{P}_x(\theta_1 = \theta_2 > n | \mathcal{F}_n) = P_x(\theta_1 = \theta_2 > n | \mathcal{F}_{mn}),$$

$$(3.3) \quad \Pi_{mn} = \mathbf{P}_x(\theta_1 = m, \theta_2 > n | \mathcal{F}_{mn}),$$

where $\mathcal{F}_{mn} = \mathcal{F}_n$ for $m, n = 1, 2, \dots, m < n, i = 1, 2$. For recursive representation of (3.1)–(3.3) we need the following functions:

$$\begin{aligned} \Pi^1(x, y, \alpha, \beta, \gamma) &= 1 - \frac{p_1(1 - \alpha)f_x^0(y)}{\mathbf{H}(x, y, \alpha, \beta, \gamma)} \\ \Pi^2(x, y, \alpha, \beta, \gamma) &= \frac{(q_2\alpha + p_2\beta + q_1\gamma)f_x^2(y)}{\mathbf{H}(x, y, \alpha, \beta, \gamma)} \\ \Pi^{12}(x, y, \alpha, \beta, \gamma) &= \frac{p_1\gamma f_x^0(y)}{\mathbf{H}(x, y, \alpha, \beta, \gamma)} \\ \Pi(x, y, \alpha, \beta, \gamma, \delta) &= \frac{p_2\delta f_x^1(y)}{\mathbf{H}(x, y, \alpha, \beta, \gamma)} \end{aligned}$$

where $\mathbf{H}(x, y, \alpha, \beta, \gamma) = (1 - \alpha)p_1f_x^0(y) + [p_2(\alpha - \beta) + q_1(1 - \alpha - \gamma)]f_x^1(y) + [q_2\alpha + p_2\beta + q_1\gamma]f_x^2(y)$. In the sequel we adopt the following denotations

$$(3.4) \quad \vec{\alpha} = (\alpha, \beta, \gamma)$$

$$(3.5) \quad \vec{\Pi}_n = (\Pi_n^1, \Pi_n^2, \Pi_n^{12}).$$

The basic formulae used in the transformation of the disorder problems to the stopping problems are given in the following

LEMMA 3.1. For each $x \in \mathbb{E}$ the following formulae, for $m, n = 1, 2, \dots, m < n$, hold:

$$(3.6) \quad \Pi_{n+1}^1 = \Pi^1(X_n, X_{n+1}, \Pi_n^1, \Pi_n^2, \Pi_n^{12})$$

$$(3.7) \quad \Pi_{n+1}^2 = \Pi^2(X_n, X_{n+1}, \Pi_n^1, \Pi_n^2, \Pi_n^{12})$$

$$(3.8) \quad \Pi_{n+1}^{12} = \Pi^{12}(X_n, X_{n+1}, \Pi_n^1, \Pi_n^2, \Pi_n^{12})$$

$$(3.9) \quad \Pi_{mn+1} = \Pi(X_n, X_{n+1}, \Pi_n^1, \Pi_n^2, \Pi_n^{12}, \Pi_{mn})$$

with boundary condition $\Pi_0^1 = \pi$, $\Pi_0^2(x) = \pi\rho$, $\Pi_0^{12}(x) = \bar{\pi}\rho$, and $\Pi_{mm} = (1 - \rho) \frac{q_1 f_{X_{m-1}}^1(X_m)}{p_1 f_{X_{m-1}}^0(X_m)} (1 - \Pi_m^1)$.

PROOF. The cases (3.6), (3.7) and (3.9), when $0 < \theta_1 < \theta_2$, have been proved in [25] and [20]. Let us assume $0 \leq \theta_1 \leq \theta_2$ and suppose that $B_i \in \mathcal{B}$, $1 \leq i \leq n+1$. Let us assume that $X_0 = x$ and denote $D_n = \{\omega : X_i(\omega) \in B_i, 1 \leq i \leq n\}$.

Ad. (3.6) For $A_i = \{\omega : X_i \in B_i\} \in \mathcal{F}_i$, $1 \leq i \leq n+1$ and $D_{n+1} \in \mathcal{F}_{n+1}$ we have by properties of $S_n(\vec{x}_n)$ where $\vec{x}_n = (x_0, \dots, x_n)$ (see Lemma 7.1)

$$\begin{aligned} \int_{D_{n+1}} \mathbf{P}_x(\theta_1 > n+1 | \mathcal{F}_{n+1}) d\mathbf{P}_x &= \int_{D_{n+1}} \mathbb{I}_{\{\theta_1 > n+1\}} d\mathbf{P}_x \\ &= \int_{\times_{i=1}^{n+1} B_i} \frac{(f_x^{n < \theta_1 < \theta_2}(\vec{x}_{1,n}) + f_x^{n < \theta_1 = \theta_2}(\vec{x}_{1,n}))}{S_n(\vec{x}_n)} \frac{p_1 f_{x_n}^0(x_{n+1})}{\mathbf{H}(x_n, x_{n+1}, \vec{\Pi}_n(\vec{x}_n))} \mu_x(d\vec{x}_{1,n+1}) \\ &= \int_{D_{n+1}} (1 - \Pi_n^1) \frac{p_1 f_{X_n}^0(X_{n+1})}{\mathbf{H}(X_n, X_{n+1}, \vec{\Pi}_n)} d\mathbf{P}_x. \end{aligned}$$

Thus, taking into account (3.1) we have $\Pi_{n+1}^1 = 1 - P_x(\theta_1 > n+1 | \mathcal{F}_{n+1}) = 1 - (1 - \Pi_n^1) p_1 f_{X_n}^0(X_{n+1}) \mathbf{H}^{-1}(X_n, X_{n+1}, \vec{\Pi}_n)$. This proves the form of the formula (3.6).

Ad. (3.7) Under the same denotations like in the proof of (3.6) we have using denotation

from Section 7.1 and the results of Lemma 7.3

$$\begin{aligned}
\int_{D_{n+1}} \mathbf{P}_x(\theta_2 \leq n+1 \mid \mathcal{F}_{n+1}) d\mathbf{P}_x &= \int_{D_{n+1}} \mathbb{I}_{\{\theta_2 \leq n+1\}} d\mathbf{P}_x \\
&\stackrel{(7.1)}{=} \int_{\times_{i=1}^{n+1} B_i} \frac{f_x^{\theta_1 \leq \theta_2 \leq n+1}(\vec{x}_{1,n+1})}{S_n(\vec{x}_n) \mathbf{H}(x_n, x_{n+1}, \vec{\Pi}_n(\vec{x}_n))} \mu_x(d\vec{x}_{1,n+1}) \\
&= \int_{\times_{i=1}^{n+1} B_i} \frac{[q_2 \Pi_n^1(\vec{x}_{0,n}) + p_2 \Pi_n^2(\vec{x}_{0,n}) + q_1 \Pi_n^{12}(\vec{x}_{0,n})] f_{x_n}^2(x_{n+1})}{\mathbf{H}(x_n, x_{n+1}, \vec{\Pi}_n(\vec{x}_n))} \mu_x(d\vec{x}_{1,n+1}) \\
&= \int_{D_{n+1}} \frac{[q_2 \Pi_n^1 + p_2 \Pi_n^2 + q_1 \Pi_n^{12}] f_{X_n}^2(X_{n+1})}{\mathbf{H}(X_n, X_{n+1}, \vec{\Pi}_n)} d\mathbf{P}_x.
\end{aligned}$$

Thus we get:

$$\begin{aligned}
\Pi_{n+1}^2 &= \mathbf{P}_x(\theta_2 \leq n+1 \mid \mathcal{F}_{n+1}) \\
&= [(\Pi_n^1 - \Pi_n^2)q_2 + \Pi_n^2 + q_1 \Pi_n^{12}] f_{X_n}^2(X_{n+1}) \mathbf{H}^{-1}(X_n, X_{n+1}, \vec{\Pi}_n)
\end{aligned}$$

which leads to the formula (3.7).

Ad. (3.8) By (3.2) and the results of Lemma 7.3

$$\begin{aligned}
\int_{D_{n+1}} \mathbf{P}_x(\theta_2 = \theta_1 > n+1 \mid \mathcal{F}_{n+1}) d\mathbf{P}_x &= \int_{D_{n+1}} \mathbb{I}_{\{\theta_2 = \theta_1 \geq n+1\}} d\mathbf{P}_x \\
&= \int_{\times_{i=1}^{n+1} B_i} \frac{f_x^{\theta_1 = \theta_2 > n}(\vec{x}_{1,n+1})}{S_n(\vec{x}_n) \mathbf{H}(x_n, x_{n+1}, \vec{\Pi}_n(\vec{x}_n))} \mu_x(d\vec{x}_{1,n+1}) \\
&= \int_{\times_{i=1}^{n+1} B_i} \frac{\Pi_n^{12}(\vec{x}_n) p_1 f_{x_n}^0(x_{n+1})}{\mathbf{H}(x_n, x_{n+1}, \vec{\Pi}_n(\vec{x}_n))} \mu_x(d\vec{x}_{1,n+1}) \\
&= \int_{D_{n+1}} \frac{\Pi_n^{12} p_1 f_{X_n}^0(X_{n+1})}{\mathbf{H}(X_n, X_{n+1}, \vec{\Pi}_n)} d\mathbf{P}_x,
\end{aligned}$$

which leads to:

$$\Pi_{n+1}^{12} = p_1 \Pi_n^{12} f_{X_n}^0(X_{n+1}) \mathbf{H}^{-1}(X_n, X_{n+1}, \vec{\Pi}_n)$$

and it proves the formula (3.8).

Ad. (3.9) Similarly, by the definition (3.3) and the results of Lemma 7.3 we get

$$\begin{aligned}
 \int_{D_{n+1}} \mathbf{P}_x(\theta_1 = m, \theta_2 > n+1 \mid \mathcal{F}_{n+1}) d\mathbf{P}_x &= \int_{D_{n+1}} \mathbb{I}_{\{\theta_1=m, \theta_2>n+1\}} d\mathbf{P}_x \\
 &= \int_{\times_{i=1}^{n+1} B_i} \frac{\bar{\pi} \bar{\rho} p_1^{m-1} q_1 p_2^{n+1} \prod_{s=1}^{m-1} f_{x_{s-1}}^0(x_s) \prod_{k=m}^n f_{x_{k-1}}^1(x_k) f_{x_n}^1(x_{n+1})}{S_n(x_{0,n}) \mathbf{H}(x_n, x_{n+1}, \vec{\Pi}_n(\vec{x}_n))} \mu_x(d\vec{x}_{1,n+1}) \\
 &= \int_{\times_{i=1}^{n+1} B_i} \frac{\Pi_{m,n}(\vec{x}_n) p_2 f_{\vec{x}_n}^1(x_{n+1})}{\mathbf{H}(x_n, x_{n+1}, \vec{\Pi}_n(\vec{x}_n))} \mu_x(d\vec{x}_{1,n+1}) = \int_{D_{n+1}} \frac{\Pi_{m,n} p_2 f_{X_n}^1(X_{n+1})}{\mathbf{H}(X_n, X_{n+1}, \vec{\Pi}_n)} d\mathbf{P}_x.
 \end{aligned}$$

It leads to relation

$$\Pi_{m,n+1} = p_2 \Pi_{m,n} f_{X_n}^1(X_{n+1}) \mathbf{H}^{-1}(X_n, X_{n+1}, \vec{\Pi}_n)$$

and it proves the formula (3.9).

Further details concerning recursive formula for conditional probabilities can be found in Remark 7.1 in Appendix. \boxtimes

REMARK 3.1. *Let us assume that the considered Markov processes have the finite state space and $\vec{x}_n = (x_0, x_1, \dots, x_n)$, $x_0 = x$ are given. In this case the formula (3.9) follows from the Bayes formula:*

$$\mathbf{P}_x(\theta_1 = j, \theta_2 = k \mid \vec{X}_n = \vec{x}_n) = \begin{cases} p_{jk}^\theta \prod_{s=1}^n f_{x_{s-1}}^0(x_s) (S_n(\vec{x}_n))^{-1} & \text{if } j > n, \\ p_{jk}^\theta \prod_{s=1}^{j-1} f_{x_{s-1}}^0(x_s) \\ \quad \times \prod_{t=j}^n f_{x_{t-1}}^1(x_t) (S_n(\vec{x}_n))^{-1} & \text{if } j \leq n < k, \\ p_{jk}^\theta \prod_{s=1}^n f_{x_{s-1}}^0(x_s) \prod_{t=j}^{k-1} f_{x_{t-1}}^1(x_t) \\ \quad \times \prod_{u=k}^n f_{x_{u-1}}^2(x_u) (S_n(\vec{x}_n))^{-1} & \text{if } k \leq n, \end{cases}$$

where $p_{jk}^\theta = \mathbf{P}(\theta_1 = j, \theta_2 = k)$ and $S_n(\cdot)$ is given by (7.5).

LEMMA 3.2. *For each $x \in \mathbb{E}$ and each Borel function $u : \mathbb{E} \rightarrow \mathfrak{R}$ the following equations are fulfilled:*

$$(3.10) \quad \mathbf{E}_x(u(X_{n+1})(1 - \Pi_{n+1}^1) | \mathcal{F}_n) = (1 - \Pi_n^1)p_1 \int_{\mathbb{E}} u(y)f_{X_n}^0(y)\mu(dy),$$

$$(3.11) \quad \begin{aligned} \mathbf{E}_x(u(X_{n+1})(\Pi_{n+1}^1 - \Pi_{n+1}^2) | \mathcal{F}_n) \\ = [q_1(1 - \Pi_n^1 - \Pi_n^{12}) + p_2(\Pi_n^1 - \Pi_n^2)] \int_{\mathbb{E}} u(y)f_{X_n}^1(y)\mu(dy), \end{aligned}$$

$$(3.12) \quad \mathbf{E}_x(u(X_{n+1})\Pi_{n+1}^2 | \mathcal{F}_n) = [q_2\Pi_n^1 + p_2\Pi_n^2 + q_1\Pi_n^{12}] \int_{\mathbb{E}} u(y)f_{X_n}^2(y)\mu(dy),$$

$$(3.13) \quad \mathbf{E}_x(u(X_{n+1})\Pi_{n+1}^{12} | \mathcal{F}_n) = p_1\Pi_n^{12} \int_{\mathbb{E}} u(y)f_{X_n}^0(y)\mu(dy)$$

$$(3.14) \quad \mathbf{E}_x(u(X_{n+1}) | \mathcal{F}_n) = \int_{\mathbb{E}} u(y)\mathbf{H}(X_n, y, \vec{\Pi}_n)\mu(dy).$$

PROOF. The relations (3.10)-(3.13) are consequence of suitable division of Ω defined by (θ_1, θ_2) and properties established in Lemma 7.3. Let us prove the equation (3.12). To this end let us define σ -field $\tilde{\mathcal{F}}_n = \sigma(\theta_1, \theta_2, X_0, \dots, X_n)$. Notice that $\mathcal{F}_n \subset \tilde{\mathcal{F}}_n$. We have:

$$\begin{aligned} \mathbf{E}_x(u(X_{n+1})\Pi_{n+1}^2 | \mathcal{F}_n) &= \mathbf{E}_x(u(X_{n+1})\mathbf{E}_x(\mathbb{I}_{\{\theta_2 \leq n+1\}} | \mathcal{F}_{n+1}) | \mathcal{F}_n) \\ &= \mathbf{E}_x(u(X_{n+1})\mathbb{I}_{\{\theta_2 \leq n+1\}} | \mathcal{F}_n) = \mathbf{E}_x(\mathbf{E}_x(u(X_{n+1})\mathbb{I}_{\{\theta_2 \leq n+1\}} | \tilde{\mathcal{F}}_n) | \mathcal{F}_n) \\ &= \mathbf{E}_x(\mathbb{I}_{\{\theta_2 \leq n+1\}}\mathbf{E}_x(u(X_{n+1}) | \tilde{\mathcal{F}}_n) | \mathcal{F}_n) = \int_{\mathbb{E}} u(y)f_{X_n}^2(y)\mu(dy)\mathbf{P}_x(\theta_2 \leq n+1 | \mathcal{F}_n) \\ &\stackrel{L.7.3}{=} (q_2\Pi_n^1 + p_2\Pi_n^2 + q_1\Pi_n^{12}) \int_{\mathbb{E}} u(y)f_{X_n}^2(y)\mu(dy) \end{aligned}$$

We used the properties of conditional expectation and point 5 of Lemma 7.3. Similar transformations give us equations (3.10), (3.13) and (3.11) when the points 1 and 2, the point 4 and the point 1 of Lemma 7.3, respectively. From (3.10)-(3.12) we get (3.14). The proof of the lemma is complete. \blacklozenge

4. DETECTION OF NEW HOMOGENEOUS SEGMENT

4.1. Equivalent optimal stopping problem. For $X_0 = x$ let us define: $Z_n = \mathbf{P}_x(\theta_1 \leq n < \theta_2 \mid \mathcal{F}_n)$ for $n = 0, 1, 2, \dots$. We have

$$(4.1) \quad Z_n = \mathbf{P}_x(\theta_1 \leq n < \theta_2 \mid \mathcal{F}_n) = \Pi_n^1 - \Pi_n^2$$

$Y_n = \text{esssup}_{\{\tau \in \mathcal{T}, \tau \geq n\}} \mathbf{P}_x(\theta_1 \leq \tau < \theta_2 \mid \mathcal{F}_n)$ for $n = 0, 1, 2, \dots$ and

$$(4.2) \quad \tau_0 = \inf\{n \geq 0 : Z_n = Y_n\}$$

Notice that, if $Z_\infty = 0$, then $Z_\tau = \mathbf{P}_x(\theta_1 \leq \tau < \theta_2 \mid \mathcal{F}_\tau)$ for $\tau \in \mathcal{T}$. Since $\mathcal{F}_n \subseteq \mathcal{F}_\tau$ (when $n \leq \tau$) we have

$$Y_n = \text{ess sup}_{\tau \geq n} E_x(Z_\tau \mid \mathcal{F}_n).$$

LEMMA 4.1. *The stopping time τ_0 defined by the formula (4.2) is the solution of the problem (2.4).*

PROOF. From the theorems presented in [3] it is enough to show that $\lim_{n \rightarrow \infty} Z_n = 0$. For all natural numbers n, k , where $n \geq k$ for each $x \in \mathbf{E}$ we have:

$$Z_n = E_x(\mathbb{I}_{\{\theta_1 \leq n < \theta_2\}} \mid \mathcal{F}_n) \leq E_x(\sup_{j \geq n} \mathbb{I}_{\{\theta_1 \leq j < \theta_2\}} \mid \mathcal{F}_n)$$

From Levy's theorem $\limsup_{n \rightarrow \infty} Z_n \leq E_x(\sup_{j \geq k} \mathbb{I}_{\{\theta_1 \leq j < \theta_2\}} \mid \mathcal{F}_\infty)$ where $\mathcal{F}_\infty = \sigma(\bigcup_{n=1}^{\infty} \mathcal{F}_n)$. It is true that: $\lim_{k \rightarrow \infty} \sup_{j \geq k} \mathbb{I}_{\{\theta_1 \leq j < \theta_2\}} = 0$ a.s. and by the dominated convergence theorem we get

$$\lim_{k \rightarrow \infty} E_x(\sup_{j \geq k} \mathbb{I}_{\{\theta_1 \leq j < \theta_2\}} \mid \mathcal{F}_\infty) = 0 \text{ a.s.}$$

what ends the proof of the lemma. ✠

The reduction of the disorder problem to optimal stopping of Markov sequence is the consequence of the following lemma.

LEMMA 4.2. System $X^x = \{X_n^x\}$, where $X_n^x = (X_{n-1}, X_n, \Pi_n^1, \Pi_n^2, \Pi_n^{12})$ forms a family of random Markov functions.

PROOF. Define a function:

$$(4.3) \quad \varphi(x_1, x_2, \vec{\alpha}; z) = (x_2, z, \Pi^1(x_2, z, \vec{\alpha}), \Pi^2(x_2, z, \vec{\alpha}), \Pi^{12}(x_2, z, \vec{\alpha}))$$

Observe that

$$X_n^x = \varphi(X_{n-2}, X_{n-1}, \vec{\Pi}_{n-1}; X_n) = \varphi(X_{n-1}^x; X_n)$$

Hence X_n^x can be interpreted as the function of the previous state X_{n-1}^x and the random variable X_n . Moreover, applying (3.14), we get that the conditional distribution of X_n given σ -field \mathcal{F}_{n-1} depends only on X_{n-1}^x . According to [19] (pp. 102-103) system X^x is a family of random Markov functions. ✠

This fact implies that we can reduce the initial problem (2.4) to the optimal stopping of the five-dimensional process $(X_{n-1}, X_n, \Pi_n^1, \Pi_n^2, \Pi_n^{12})$ with the reward

$$(4.4) \quad h(x_1, x_2, \vec{\alpha}) = \alpha - \beta$$

The reward function results from the equation (4.1). Thanks to Lemma 4.2 we construct the solution using standard tools of optimal stopping theory (cf [19]), as we do below.

Let us define two operators for any Borel function $v : \mathbf{E}^2 \times [0, 1]^3 \rightarrow [0, 1]$ and the set $D = \{\omega : X_{n-1} = y, X_n = z, \Pi_n^1 = \alpha, \Pi_n^2 = \beta, \Pi_n^{12} = \gamma\}$:

$$\begin{aligned} T_x v(y, z, \vec{\alpha}) &= E_x(v(X_n, X_{n+1}, \vec{\Pi}_{n+1}) \mid D) \\ \mathbf{Q}_x v(y, z, \vec{\alpha}) &= \max\{v(y, z, \vec{\alpha}), \mathbf{T}_x v(y, z, \vec{\alpha})\} \end{aligned}$$

From the well known theorems of optimal stopping theory (see [19]), we infer that the solution of the problem (2.4) is the Markov time τ_0 :

$$(4.5) \quad \tau_0^* = \inf\{n \geq 0 : h(X_n, X_{n+1}, \vec{\Pi}_{n+1}) \geq h^*(X_n, X_{n+1}, \vec{\Pi}_{n+1})\},$$

where:

$$h^*(y, z, \vec{\alpha}) = \lim_{k \rightarrow \infty} \mathbf{Q}_x^k h(y, z, \vec{\alpha}).$$

Of course

$$\mathbf{Q}_x^k v(y, z, \vec{\alpha}) = \max\{\mathbf{Q}_x^{k-1} v, \mathbf{T}_x \mathbf{Q}_x^{k-1} v\} = \max\{v, \mathbf{T}_x \mathbf{Q}_x^{k-1} v\}.$$

To obtain a clearer formula for τ_0^* and the solution of the problem (2.4), we formulate (cf (3.5) and (3.4)):

THEOREM 4.1. (a) *The solution (4.5) of the optimal stopping problem for the stochastic system X^x defined in Lemma 4.2 with payoff function (4.4) is given by:*

$$(4.6) \quad \tau_0^* = \inf\{n \geq 0 : (X_n, X_{n+1}, \vec{\Pi}_{n+1}) \in B^*\}.$$

Set B^* is of the form:

$$\begin{aligned} B^* = & \left\{ (y, z, \vec{\alpha}) : (\alpha - \beta) \geq (1 - \alpha - \gamma) \left[p_1 \int_{\mathbb{E}} R^*(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^0(u) \mu(du) \right. \right. \\ & + q_1 \int_{\mathbb{E}} S^*(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du) \\ & \left. \left. + (\alpha - \beta) p_2 \int_{\mathbb{E}} S^*(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du) \right] \right\}, \end{aligned}$$

where $R^*(y, z, \vec{\alpha}) = \lim_{k \rightarrow \infty} R^k(y, z, \vec{\alpha})$, $S^*(y, z, \vec{\alpha}) = \lim_{k \rightarrow \infty} S^k(y, z, \vec{\alpha})$. The functions R^k and S^k are defined recursively: $R^1(y, z, \vec{\alpha}) = 0$, $S^1(y, z, \vec{\alpha}) = 1$ and

$$(4.7) \quad R^{k+1}(y, z, \vec{\alpha}) = (1 - \mathbb{I}_{\mathcal{R}_k}(y, z, \vec{\alpha})) \left(p_1 \int_{\mathbb{E}} R^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^0(u) \mu(du) \right. \\ \left. + q_1 \int_{\mathbb{E}} S^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du) \right),$$

$$(4.8) \quad S^{k+1}(y, z, \vec{\alpha}) = \mathbb{I}_{\mathcal{R}_k}(y, z, \vec{\alpha}) + (1 - \mathbb{I}_{\mathcal{R}_k}(y, z, \vec{\alpha})) \\ \times p_2 \int_{\mathbb{E}} S^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du),$$

where the set \mathcal{R}_k is:

$$\begin{aligned}
(4.9) \quad \mathcal{R}_k &= \left\{ (y, z, \vec{\alpha}) : h(y, z, \vec{\alpha}) \geq \mathbf{T}_x \mathbf{Q}_x^{k-1} h(y, z, \vec{\alpha}) \right\} \\
&= \left\{ (y, z, \vec{\alpha}) : (\alpha - \beta) \geq (1 - \alpha - \gamma) \right. \\
&\quad \times \left[p_1 \int_{\mathbb{E}} R^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^0(u) \mu(du) \right. \\
&\quad \left. \left. + q_1 \int_{\mathbb{E}} S^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du) \right] \right. \\
&\quad \left. + (\alpha - \beta) p_2 \int_{\mathbb{E}} S^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du) \right\}.
\end{aligned}$$

(b) The optimal value for (2.4) is given by the formula

$$V(x) = \max\{p_2 \bar{\pi} \rho, V_0(x)\}$$

where

$$\begin{aligned}
V_0(x) &= \bar{\pi} \bar{\rho} \left[p_1 \int_{\mathbb{E}} R^*(x, u, \vec{\Pi}_1(x, u, \pi, \rho\pi, \rho\bar{\pi})) f_x^0(u) \mu(du) \right. \\
&\quad \left. + q_1 \int_{\mathbb{E}} S^*(x, u, \vec{\Pi}_1(x, u, \pi, \rho\pi, \rho(1 - \pi))) f_x^1(u) \mu(du) \right] \\
&\quad + \bar{\pi} \rho p_2 \int_{\mathbb{E}} S^*(x, u, \vec{\Pi}_1(x, u, \pi, \rho\pi, \rho(1 - \pi))) f_x^1(u) \mu(du)
\end{aligned}$$

$$\text{and } \tau^* = 0 \mathbb{I}_{\{p_2 \bar{\pi} \rho \geq V_0(x)\}} + \tau_0^* \mathbb{I}_{\{p_2 \bar{\pi} \rho < V_0(x)\}}.$$

PROOF. Part (a) results from Lemma 3.2 - the problem reduces to the optimal stopping of the Markov process $(X_{n-1}, X_n, \Pi_n^1, \Pi_n^2, \Pi_n^{12})$ with the payoff function $h(y, z, \vec{\alpha}) = \alpha - \beta$. Given (3.11) with the function u equal to unity we get on $D = \{\omega : X_{n-1} = y, X_n = z, \Pi_n^1 = \alpha, \Pi_n^2 = \beta, \Pi_n^{12} = \gamma\}$:

$$\begin{aligned}
\mathbf{T}_x h(y, z, \vec{\alpha}) &= \mathbf{E}_x (\Pi_{n+1}^1 - \Pi_{n+1}^2 \mid \mathcal{F}_n) \mid_D \\
&= \left[((1 - \Pi_n^1 - \Pi_n^{12}) q_1 + (\Pi_n^1 - \Pi_n^2) p_2) \int_{\mathbb{E}} f_{X_n}^1(u) \mu(du) \right] \mid_D \\
&= (1 - \alpha - \gamma) q_1 + (\alpha - \beta) p_2.
\end{aligned}$$

From the definition of R^1 and S^1 it is clear that

$$h(y, z, \vec{\alpha}) = \alpha - \beta = (1 - \alpha - \gamma)R^1(y, z, \vec{\alpha}) + (\alpha - \beta)S^1(y, z, \vec{\alpha})$$

Also $\mathcal{R}_1 = \{(y, z, \vec{\alpha}) : h(y, z, \vec{\alpha}) \geq \mathbf{T}_x h(y, z, \vec{\alpha})\}$. From the definition of \mathbf{Q}_x and the facts above we obtain

$$\mathbf{Q}_x h(y, z, \vec{\alpha}) = (1 - \alpha - \gamma)R^2(y, z, \vec{\alpha}) + (\alpha - \beta)S^2(y, z, \vec{\alpha}),$$

where $R^2(y, z, \vec{\alpha}) = q_1(1 - \mathbb{I}_{\mathcal{R}_1}(y, z, \vec{\alpha}))$ and $S^2(y, z, \vec{\alpha}) = p_2 + (1 - p_2)\mathbb{I}_{\mathcal{R}_1}(y, z, \vec{\alpha})$.

Suppose the following induction hypothesis holds

$$\mathbf{Q}_x^{k-1} h(y, z, \vec{\alpha}) = (1 - \alpha - \gamma)R^k(y, z, \vec{\alpha}) + (\alpha - \beta)S^k(y, z, \vec{\alpha}),$$

where R^k and S^k are given by equations (4.7), (4.8), respectively. We will show

$$\mathbf{Q}_x^k h(y, z, \vec{\alpha}) = (1 - \alpha - \gamma)R^{k+1}(y, z, \vec{\alpha}) + (\alpha - \beta)S^{k+1}(y, z, \vec{\alpha}).$$

From the induction assumption and the equations (3.10), (3.13) and (3.11) we obtain:

$$\begin{aligned} (4.10) \quad \mathbf{T}_x \mathbf{Q}_x^{k-1} h(y, z, \vec{\alpha}) &= \mathbf{T}_x (1 - \alpha - \gamma)R^k(y, z, \vec{\alpha}) \\ &\quad + \mathbf{T}_x (\alpha - \beta)S^k(y, z, \vec{\alpha}) \\ &= (1 - \alpha - \gamma)p_1 \int_{\mathbb{E}} R^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^0(u) \mu(du) \\ &\quad + [(1 - \alpha - \gamma)q_1 + (\alpha - \beta)p_2] \int_{\mathbb{E}} S^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du) \\ &= (1 - \alpha - \gamma) \left[p_1 \int_{\mathbb{E}} R^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^0(u) \mu(du) \right. \\ &\quad \left. + q_1 \int_{\mathbb{E}} S^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du) \right] \\ &\quad + (\alpha - \beta)p_2 \int_{\mathbb{E}} S^k(y, u, \vec{\Pi}_1(y, u, \vec{\alpha})) f_y^1(u) \mu(du). \end{aligned}$$

Notice that

$$(1 - \alpha - \gamma)R^{k+1}(y, z, \vec{\alpha}) + (\alpha - \beta)S^{k+1}(y, z, \vec{\alpha})$$

is equal $\alpha - \beta = h(y, z, \vec{\alpha}) = \mathbf{Q}_x^k h(y, z, \vec{\alpha})$ for $(y, z, \vec{\alpha}) \in \mathcal{R}_k$ and, taking into account (4.10), it is equal $\mathbf{T}_x \mathbf{Q}_x^{k-1} h(y, z, \vec{\alpha}) = \mathbf{Q}_x^k h(y, z, \vec{\alpha})$ for $(y, z, \vec{\alpha}) \notin \mathcal{R}_k$, where \mathcal{R}_k is given by (4.9). Finally we get

$$\mathbf{Q}_x^k h(y, z, \vec{\alpha}) = (1 - \alpha - \gamma)R^{k+1}(y, z, \vec{\alpha}) + (\alpha - \beta)S^{k+1}(y, z, \vec{\alpha}).$$

This proves (4.7) and (4.8). Using the monotone convergence theorem and the theorems of optimal stopping theory (see [19]) we conclude that the optimal stopping time τ_0^* is given by (4.6). ✠

PROOF. Part (b). First, notice that Π_1^1 , Π_1^2 and Π_1^{12} are given by (3.6)-(3.8) and the boundary condition formulated in Lemma 3.1. Under the assumption $\tau^* < \infty$ a.s. we get:

$$\begin{aligned} \mathbf{P}_x(\tau^* < \infty, \theta_1 \leq \tau^* < \theta_2) &= \sup_{\tau} \mathbf{E} Z_{\tau} \\ &= \mathbf{E} \max\{h(x, X_1, \vec{\Pi}_1), \mathbf{T}_x h^*(x, X_1, \vec{\Pi}_1)\} = \mathbf{E} \lim_{k \rightarrow \infty} \mathbf{Q}_x^k h(x, X_1, \vec{\Pi}_1) \\ &= \mathbf{E} \left[(1 - \Pi_1^1 - \Pi_1^{12})R^*(x, X_1, \vec{\Pi}_1) + (\Pi_1^1 - \Pi_1^2)S^*(x, X_1, \vec{\Pi}_1) \right] \\ &= \bar{\pi} \bar{\rho} p_1 \int_{\mathbb{E}} R^*(x, u, \vec{\Pi}_1(x, u, \pi, \rho\pi, \rho\bar{\pi})) f_x^0(u) \mu(du) \\ &\quad + (\bar{\pi} \bar{\rho} q_1 + \pi \bar{\rho} p_2) \int_{\mathbb{E}} S^*(x, u, \vec{\Pi}_1(x, u, \pi, \rho\pi, \rho\bar{\pi})) f_x^1(u) \mu(du). \end{aligned}$$

We used Lemma 3.2 here and simple calculations for Π_1^1 , Π_1^2 and Π_1^{12} . This ends the proof. ✠

4.2. Remarks. It is notable that the solution of formulated problem depends only on two-dimensional vector of posterior processes because $\Pi_n^{12} = \rho(1 - \Pi_n^1)$. The obtained formulae are very general and for this reason – quite complicated. We simplify the model by assuming that $P(\theta_1 > 0) = 1$ and $P(\theta_2 > \theta_1) = 1$. However, it seems that some further simplifications can be made in special cases. Further research should be carried out in this direction. From a practical point of view, computer algorithms are necessary to construct B^* – the set in which it is optimally to stop our observable sequence.

5. IMMEDIATE DETECTION OF THE FIRST AND THE SECOND DISORDER

5.1. Equivalent double optimal stopping problem. Let us consider the problem D_{00} formulated in (2.5). A *compound stopping variable* is a pair (τ, σ) of stopping times such that $0 \leq \tau \leq \sigma$ a.e.. The aim is to find a compound stopping variable (τ^*, σ^*) such that

$$(5.1) \quad \mathbf{P}_x((\theta_1, \theta_2) = (\tau^*, \sigma^*)) = \sup_{\substack{(\tau, \sigma) \in \mathcal{T} \\ 0 \leq \tau \leq \sigma < \infty}} \mathbf{P}_x((\theta_1, \theta_2) = (\tau, \sigma)).$$

Denote $\mathcal{T}_m = \{(\tau, \sigma) \in \mathcal{T} : \tau \geq m\}$, $\mathcal{T}_{mn} = \{(\tau, \sigma) \in \mathcal{T} : \tau = m, \sigma \geq n\}$ and $\mathcal{S}_m = \{\tau \in \mathcal{S} : \tau \geq m\}$. Let us denote $\mathcal{F}_{mn} = \mathcal{F}_n$, $m, n \in \mathbb{N}$, $m \leq n$. We define two-parameter stochastic sequence $\xi(x) = \{\xi_{mn}, m, n \in \mathbb{N}, m < n, x \in \mathbb{E}\}$, where

$$\xi_{mn} = \mathbf{P}_x(\theta_1 = m, \theta_2 = n | \mathcal{F}_{mn}).$$

We can consider for every $x \in \mathbb{E}$, $m, n \in \mathbb{N}$, $m < n$, the optimal stopping problem of $\xi(x)$ on $\mathcal{T}_{mn}^+ = \{(\tau, \sigma) \in \mathcal{T}_{mn} : \tau < \sigma\}$. A compound stopping variable (τ^*, σ^*) is said to be optimal in \mathcal{T}_m^+ (or \mathcal{T}_{mn}^+) if

$$(5.2) \quad \mathbf{E}_x \xi_{\tau^* \sigma^*} = \sup_{(\tau, \sigma) \in \mathcal{T}_m} \mathbf{E}_x \xi_{\tau \sigma}$$

(or $\mathbf{E}_x \xi_{\tau^* \sigma^*} = \sup_{(\tau, \sigma) \in \mathcal{T}_{mn}^+} \mathbf{E}_x \xi_{\tau \sigma}$). Let us define

$$(5.3) \quad \eta_{mn} = \operatorname{ess\,sup}_{(\tau, \sigma) \in \mathcal{T}_{mn}^+} \mathbf{E}_x(\xi_{\tau \sigma} | \mathcal{F}_{mn}).$$

If we put $\xi_{m\infty} = 0$, then

$$\eta_{mn} = \operatorname{ess\,sup}_{(\tau, \sigma) \in \mathcal{T}_{mn}^+} \mathbf{P}_x(\theta_1 = \tau, \theta_2 = \sigma | \mathcal{F}_{mn}).$$

From the theory of optimal stopping for double indexed processes (cf. [8],[13]) the sequence η_{mn} satisfies

$$\eta_{mn} = \max\{\xi_{mn}, \mathbf{E}(\eta_{mn+1} | \mathcal{F}_{mn})\}.$$

Moreover, if $\sigma_m^* = \inf\{n > m : \eta_{mn} = \xi_{mn}\}$, then (m, σ_m^*) is optimal in \mathcal{T}_m^+ and $\eta_{mn} = \mathbf{E}_x(\xi_{m\sigma_m^*} | \mathcal{F}_{mn})$ a.e.. The case when there are no segment with the distribution

$f_x^1(y)$ appears with probability ρ . It will be taken into account. Define

$$\hat{\eta}_{mn} = \max\{\xi_{mn}, \mathbf{E}(\eta_{m, n+1} | \mathcal{F}_{mn})\}, \text{ for } n \geq m.$$

if $\hat{\sigma}_m^* = \inf\{n \geq m : \hat{\eta}_{mn} = \xi_{mn}\}$, then $(m, \hat{\sigma}_m^*)$ is optimal in \mathcal{T}_{mn} and $\hat{\eta}_{mm} = \mathbf{E}_x(\xi_{m\sigma_m^*} | \mathcal{F}_{mm})$ a.e.. For further consideration denote

$$(5.4) \quad \eta_m = \mathbf{E}_x(\eta_{mm+1} | \mathcal{F}_m).$$

LEMMA 5.1. *The stopping time σ_m^* is optimal for every stopping problem (5.3).*

PROOF. It suffices to prove $\lim_{n \rightarrow \infty} \xi_{mn} = 0$ (cf. [3]). We have for $m, n, k \in \mathbb{N}$, $n \geq k > m$ and every $x \in \mathbb{E}$

$$\mathbf{E}_x(\mathbb{I}_{\{\theta_1=m, \theta_2=n\}} | \mathcal{F}_{mn}) = \xi_{mn}(x) \leq \mathbf{E}_x(\sup_{j \geq k} \mathbb{I}_{\{\theta_1=m, \theta_2=j\}} | \mathcal{F}_m),$$

where \mathbb{I}_A is the characteristic function of the set A . By Levy's theorem

$$\limsup_{n \rightarrow \infty} \xi_{mn}(x) \leq \mathbf{E}_x(\sup_{j \geq k} \mathbb{I}_{\{\theta_1=m, \theta_2=j\}} | \mathcal{F}_{n\infty}),$$

where $\mathcal{F}_\infty = \mathcal{F}_{n\infty} = \sigma(\bigcup_{n=1}^\infty \mathcal{F}_n)$. We have $\lim_{k \rightarrow \infty} \sup_{j \geq k} \mathbb{I}_{\{\theta_1=m, \theta_2=j\}} = 0$ a.e. and by dominated convergence theorem

$$\lim_{k \rightarrow \infty} \mathbf{E}_x(\sup_{j \geq k} \mathbb{I}_{\{\theta_1=m, \theta_2=j\}} | \mathcal{F}_\infty) = 0.$$

✂

What is left is to consider the optimal stopping problem for $(\eta_{mn})_{m=0, n=m}^{\infty, \infty}$ on $(\mathcal{T}_{mn})_{m=0, n=m}^{\infty, \infty}$. Let us define

$$(5.5) \quad V_m = \text{ess sup}_{\tau \in \mathcal{S}_m} \mathbf{E}_x(\eta_\tau | \mathcal{F}_m).$$

Then $V_m = \max\{\eta_m, \mathbf{E}_x(V_{m+1} | \mathcal{F}_m)\}$ a.e. and we define $\tau_n^* = \inf\{k \geq n : V_k = \eta_k\}$.

LEMMA 5.2. *The strategy τ_0^* is the optimal first stop.*

PROOF. To show that τ_0^* is the optimal first stop strategy we prove that $\mathbf{P}_x(\tau_0^* < \infty) = 1$. To this end, we argue in the usual manner i.e. we show $\lim_{m \rightarrow \infty} \eta_m = 0$.

We have

$$\begin{aligned} \eta_m &= \mathbf{E}_x(\xi_{m\sigma_m^*} | \mathcal{F}_m) = \mathbf{E}_x(\mathbf{E}_x(\mathbb{I}_{\{\theta_1=m, \theta_2=\sigma_m^*\}} | \mathcal{F}_{m\sigma_m^*}) | \mathcal{F}_m) \\ &= \mathbf{E}_x(\mathbb{I}_{\{\theta_1=m, \theta_2=\sigma_m^*\}} | \mathcal{F}_m) \leq \mathbf{E}_x(\sup_{j \geq k} \mathbb{I}_{\{\theta_1=j, \theta_2=\sigma_j^*\}} | \mathcal{F}_m). \end{aligned}$$

Similarly as in proof of Lemma 5.1 we have got

$$\limsup_{m \rightarrow \infty} \eta_m(x) \leq \mathbf{E}_x(\sup_{j \geq k} \mathbb{I}_{\{\theta_1=j, \theta_2=\sigma_j^*\}} | \mathcal{F}_\infty).$$

Since $\lim_{k \rightarrow \infty} \sup_{j \geq k} \mathbb{I}_{\{\theta_1=k, \theta_2=\sigma_j^*\}} \leq \lim_{k \rightarrow \infty} \sup_{k \rightarrow \infty} \mathbb{I}_{\{\theta_1=k\}} = 0$, it follows that

$$\lim_{m \rightarrow \infty} \eta_m(x) \leq \lim_{k \rightarrow \infty} \mathbf{E}_x(\sup_{j \geq k} \mathbb{I}_{\{\theta_1=j, \theta_2=\sigma_j^*\}} | \mathcal{F}_\infty) = 0.$$

✠

Lemmas 5.1 and 5.2 describe the method of solving the “disorder problem” formulated in Section 2 (see (5.1)).

5.2. Solution of the equivalent double stopping problem. For the sake of simplicity we shall confine ourselves to the case $d_1 = d_2 = 0$. It will be easily seen how to generalize the solution of the problem to solve $D_{d_1 d_2}$ for $d_1 > 0$ or $d_2 > 0$. First of all we construct multidimensional Markov chains such that ξ_{mn} and η_m will be the functions of their states. By consideration of Section 3 concerning *a posteriori* processes we get $\xi_{00} = \pi\rho$ and for $m < n$

$$\begin{aligned} \xi_{mn}^x &= \mathbf{P}_x(\theta_1 = m, \theta_2 = n | \mathcal{F}_{mn}) \\ &= \frac{\bar{\pi}\bar{\rho} p_1^{m-1} q_1 p_2^{n-m-1} q_2 \prod_{s=1}^{j-1} f_{X_{s-1}}^0(X_s) \prod_{t=j}^{n-1} f_{X_{t-1}}^1(X_t) f_{X_{n-1}}^2(X_n)}{S_n(x_0, X_1, \dots, X_n)} \\ &= \frac{q_2}{p_2} \Pi_{mn}(x) \frac{f_{X_{n-1}}^2(X_n)}{f_{X_{n-1}}^1(X_n)} \end{aligned}$$

and for $n = m$, by Lemma 7.3,

$$(5.6) \quad \xi_{m m}^x = \mathbf{P}_x(\theta_1 = m, \theta_2 = m | \mathcal{F}_{m m}) = \rho \frac{q_1 f_{X_{m-1}}^2(X_m)}{p_1 f_{X_{m-1}}^0(X_m)} (1 - \Pi_m^1).$$

We can observe that $(X_n, X_{n+1}, \vec{\Pi}_{n+1}, \Pi_{m n+1})$ for $n = m + 1, m + 2, \dots$ is a function of $(X_{n-1}, X_n, \vec{\Pi}_n, \Pi_{m n})$ and X_{n+1} . Besides, the conditional distribution of X_{n+1} given \mathcal{F}_n (cf. (3.14)) depends on X_n , $\Pi_n^1(x)$ and $\Pi_n^2(x)$ only. These facts imply that $\{(X_n, X_{n+1}, \vec{\Pi}_{n+1}, \Pi_{m n+1})\}_{n=m+1}^\infty$ form a homogeneous Markov process (see Chapter 2.15 of [19]). This allows us to reduce the problem (5.3) for each m to the optimal stopping problem of the Markov process $Z_m(x) = \{(X_{n-1}, X_n, \vec{\Pi}_n, \Pi_{m n}), m, n \in \mathbb{N}, m < n, x \in \mathbb{E}\}$ with the reward function $h(t, u, \vec{\alpha}, \delta) = \frac{q_2}{p_2} \delta \frac{f_t^2(u)}{f_t^1(u)}$.

LEMMA 5.3. *A solution of the optimal stopping problem (5.3) for $m = 1, 2, \dots$ has a form*

$$(5.7) \quad \sigma_m^* = \inf\{n > m : \frac{f_{X_{n-1}}^2(X_n)}{f_{X_{n-1}}^1(X_n)} \geq R^*(X_n)\}$$

where $R^*(t) = p_2 \int_{\mathbb{E}} r^*(t, s) f_t^1(s) \mu(ds)$. The function $r^* = \lim_{n \rightarrow \infty} r_n$, where $r_0(t, u) = \frac{f_t^2(u)}{f_t^1(u)}$,

$$(5.8) \quad r_{n+1}(t, u) = \max\left\{\frac{f_t^2(u)}{f_t^1(u)}, p_2 \int_{\mathbb{E}} r_n(u, s) f_u^1(s) \mu(ds)\right\}.$$

So $r^*(t, u)$ satisfies the equation

$$(5.9) \quad r^*(t, u) = \max\left\{\frac{f_t^2(u)}{f_t^1(u)}, p_2 \int_{\mathbb{E}} r^*(u, s) f_u^1(s) \mu(ds)\right\}.$$

The value of the problem

$$(5.10) \quad \eta_m = \mathbf{E}_x(\eta_{m m+1} | \mathcal{F}_m) = \frac{q_1 f_{X_{m-1}}^1(X_m)}{p_1 f_{X_{m-1}}^0(X_m)} (1 - \Pi_m^1) R_\rho^*(X_{m-1}, X_m),$$

where

$$(5.11) \quad R_\rho^*(t, u) = \max\left\{\rho \frac{f_t^2(u)}{f_t^1(u)}, \frac{q_2}{p_2} (1 - \rho) R^*(u)\right\}.$$

PROOF. For any Borel function $u : \mathbb{E} \times \mathbb{E} \times [0, 1]^4 \rightarrow [0, 1]$ and $D = \{\omega : X_{n-1} = t, X_n = u, \Pi_n^1(x) = \alpha, \Pi_n^2(x) = \beta, \Pi_n^{12} = \gamma, \Pi_{m n}(x) = \delta\}$ let us define two operators

$$\mathbf{T}_x u(t, u, \vec{\alpha}, \delta) = \mathbf{E}_x(u(X_n, X_{n+1}, \vec{\Pi}_{n+1}(x), \Pi_{m n+1}(x)) | D)$$

and

$$\mathbf{Q}_x u(t, u, \vec{\alpha}, \delta) = \max\{u(t, u, \vec{\alpha}, \delta), \mathbf{T}_x u(t, u, \vec{\alpha}, \delta)\}.$$

On the bases of the well-known theorem from the theory of optimal stopping (see [19], [13]) we conclude that the solution of (5.3) is a Markov time

$$\sigma_m^* = \inf\{n > m : h(X_{n-1}, X_n, \vec{\Pi}_n, \Pi_{m n}) = h^*(X_{n-1}, X_n, \vec{\Pi}_n(x), \Pi_{m n})\},$$

where $h^* = \lim_{k \rightarrow \infty} \mathbf{Q}_x^k h(t, u, \vec{\alpha}, \delta)$. By (3.9) and (3.14) on $D = \{\omega : X_{n-1} = t, X_n = u, \Pi_n^1 = \alpha, \Pi_n^2 = \beta, \Pi_n^{12} = \gamma, \Pi_{m n} = \delta\}$ we have

$$\begin{aligned} \mathbf{T}_x h(t, u, \vec{\alpha}, \delta) &= \mathbf{E}_x\left(\frac{q_2}{p_2} \Pi_{m n+1} \frac{f_{X_n}^2(X_{n+1})}{f_{X_n}^1(X_{n+1})} | D\right) \\ &= \frac{q_2}{p_2} \delta p_2 \mathbf{E}\left(\frac{f_u^1(X_{n+1})}{H(u, X_{n+1}, \vec{\alpha})} \frac{f_u^2(X_{n+1})}{f_u^1(X_{n+1})} | \mathcal{F}_n\right) | D \\ &\stackrel{(3.14)}{=} q_2 \delta \int_{\mathbb{E}} \frac{f_u^2(s)}{H(u, s, \vec{\alpha})} H(u, s, \vec{\alpha}) \mu(ds) = q_2 \delta \end{aligned}$$

and

$$(5.12) \quad \mathbf{Q}_x h(t, u, \vec{\alpha}, \delta) = \frac{q_2}{p_2} \delta \max\left\{\frac{f_t^2(u)}{f_t^1(u)}, p_2\right\}.$$

Let us define $r_0(t, u) = 1$ and

$$r_{n+1}(t, u) = \max\left\{\frac{f_t^2(u)}{f_t^1(u)}, p_2 \int_{\mathbb{E}} r_n(u, s) f_u^1(s) \mu(ds)\right\}.$$

We show that

$$(5.13) \quad \mathbf{Q}_x^\ell h(t, u, \vec{\alpha}, \delta) = \frac{q_2}{p_2} \delta r_\ell(t, u)$$

for $\ell = 1, 2, \dots$. We have by (5.12) that $\mathbf{Q}_x h = \frac{q_2}{p_2} \gamma r_1$. Let us assume (5.13) for $\ell \leq k$. By (3.14) on $D = \{\omega : X_{n-1} = t, X_n = u, \Pi_n^1 = \alpha, \Pi_n^2 = \beta, \Pi_n^{12} = \gamma, \Pi_{mn} = \delta\}$ we have got

$$\begin{aligned} \mathbf{T}_x \mathbf{Q}_x^k h(t, u, \vec{\alpha}, \delta) &= \mathbf{E}_x \left(\frac{q_2}{p_2} \Pi_{m, k+1} r_k(X_n, X_{n+1}) | D \right) \\ &= \frac{q_2}{p_2} \delta p_2 \int_{\mathbb{E}} r_k(u, s) f_u^1(s) \mu(ds). \end{aligned}$$

It is easy to show (see [19]) that

$$\mathbf{Q}_x^{k+1} h = \max\{h, \mathbf{T}_x \mathbf{Q}_x^k h\}, \text{ for } k = 1, 2, \dots$$

Hence we have got $\mathbf{Q}_x^{k+1} h = \frac{q_2}{p_2} \delta r_{k+1}$ and (5.13) is proved for $\ell = 1, 2, \dots$. This gives

$$(5.14) \quad h^*(t, u, \vec{\alpha}, \delta) = \frac{q_2}{p_2} \delta \lim_{k \rightarrow \infty} r_k(t, u) = \frac{q_2}{p_2} \delta r^*(t, u)$$

and

$$\eta_{mn} = \operatorname{ess\,sup}_{(\tau, \sigma) \in \mathcal{T}_{mn}} \mathbf{E}_x(\xi_{\tau, \sigma} | \mathcal{F}_{mn}) = h^*(X_{n-1}, X_n, \vec{\Pi}_n, \Pi_{mn}).$$

We have by (5.14) and (3.9)

$$\mathbf{T}_x h^*(t, u, \vec{\alpha}, \delta) = \frac{q_2}{p_2} \delta p_2 \int_{\mathbb{E}} r^*(u, s) f_u^1(s) \mu(ds) = \frac{q_2}{p_2} \delta R^*(u)$$

and σ_m^* has form (5.7). By (5.4), (5.6) and (3.14) we obtain

$$(5.15) \quad \begin{aligned} \eta_m &= \max\{\xi_{mm}^x, \mathbf{E}(\eta_{m, m+1} | \mathcal{F}_m)\} = f(X_{m-1}, X_m, \vec{\Pi}_m, \Pi_{mm}) \\ &= \max\left\{\rho \frac{q_1}{p_1} \frac{f_{X_{m-1}}^2(X_m)}{f_{X_{m-1}}^0(X_m)} (1 - \Pi_m^1), \frac{q_2}{p_2} (1 - \Pi_{mm}) R^*(X_m)\right\} \\ &\stackrel{L.3.1}{=} \frac{q_1}{p_1} \frac{f_{X_{m-1}}^1(X_m)}{f_{X_{m-1}}^0(X_m)} (1 - \Pi_m^1) R_\rho^*(X_{m-1}, X_m). \end{aligned}$$

✠

REMARK 5.1. *Based on the results of Lemma 5.3 and properties of the a posteriori process Π_{nm} we have that the expected value of success for the second stop when the observer stops immediately at $n = 0$ is $\pi \rho$ and when at least one observation has been made*

$$\mathbf{E}(\eta_1|\mathcal{F}_0) = \frac{q_1}{p_1}\mathbf{E}((1 - \Pi_1^1)\frac{f_x^1(X_1)}{f_x^0(X_1)}R_\rho^*(x, X_1)|\mathcal{F}_0) = \frac{q_1}{p_1}(1 - \pi)p_1 \int_{\mathbb{E}} f_x^1(u)R_\rho^*(x, u)\mu(du).$$

As a consequence we have optimal second moment

$$\hat{\sigma}_0^* = \begin{cases} 0 & \text{if } \pi\rho \geq q_1(1 - \pi) \int_{\mathbb{E}} f_x^1(u)R_\rho^*(x, u)\mu(du), \\ \sigma_0^* & \text{otherwise.} \end{cases}$$

By Lemmas 5.3 and 3.1 (the formula (3.9)) the optimal stopping problem (5.5) has been transformed to the optimal stopping problem for the homogeneous Markov process

$$W = \{(X_{m-1}, X_m, \vec{\Pi}_m), m \in \mathbb{N}, x \in \mathbb{E}\}$$

with the reward function

$$(5.16) \quad f(t, u, \vec{\alpha}) = \frac{q_1}{p_1} \frac{f_t^1(u)}{f_t^0(u)} (1 - \alpha) R_\rho^*(t, u).$$

THEOREM 5.1. *A solution of the optimal stopping problem (5.5) for $n = 1, 2, \dots$ has a form*

$$(5.17) \quad \tau_n^* = \inf\{k \geq n : (X_{k-1}, X_k, \vec{\Pi}_k) \in B^*\}$$

where $B^* = \{(t, u, \vec{\alpha}) : \frac{f_t^2(u)}{f_t^1(u)} R_\rho^*(t, u) \geq p_1 \int_{\mathbb{E}} v^*(u, s) f_u^0(s) \mu(ds)\}$. The function $v^*(t, u) = \lim_{n \rightarrow \infty} v_n(t, u)$, where $v_0(t, u) = R_\rho^*(t, u)$,

$$(5.18) \quad v_{n+1}(t, u) = \max\left\{\frac{f_t^2(u)}{f_t^1(u)} R_\rho^*(t, u), p_1 \int_{\mathbb{E}} v_n(u, s) f_u^1(s) \mu(ds)\right\}.$$

So $v^*(t, u)$ satisfies the equation

$$(5.19) \quad v^*(t, u) = \max\left\{\frac{f_t^2(u)}{f_t^1(u)} R_\rho^*(t, u), p_1 \int_{\mathbb{E}} v^*(u, s) f_u^1(s) \mu(ds)\right\}.$$

The value of the problem $V_n = v^*(X_{n-1}, X_n)$.

PROOF. For any Borel function $u : \mathbb{E} \times \mathbb{E} \times [0, 1]^3 \rightarrow [0, 1]$ and $D = \{\omega : X_{n-1} = t, X_n = u, \Pi_n^1(x) = \alpha, \Pi_n^2(x) = \beta, \Pi_n^{12} = \gamma\}$ let us define two operators

$$\mathbf{T}_x u(t, u, \vec{\alpha}) = \mathbf{E}_x(u(X_n, X_{n+1}, \vec{\Pi}_{n+1})|D)$$

and $\mathbf{Q}_x u(t, u, \vec{\alpha}) = \max\{u(t, u, \vec{\alpha}), \mathbf{T}_x u(t, u, \vec{\alpha})\}$. Similarly as in the proof of Lemma 5.3 we conclude that the solution of (5.5) is a Markov time

$$\tau_m^* = \inf\{n > m : f(X_{n-1}, X_n, \vec{\Pi}_n) = f^*(X_{n-1}, X_n, \vec{\Pi}_n)\},$$

where $f^* = \lim_{k \rightarrow \infty} \mathbf{Q}_x^k f(t, u, \vec{\alpha})$. By (3.14) and (5.16) on $D = \{\omega : X_{n-1} = t, X_n = u, \Pi_n^1 = \alpha, \Pi_n^2 = \beta, \Pi_n^{12} = \gamma\}$ we have

$$\begin{aligned} \mathbf{T}_x f(t, u, \vec{\alpha}) &= \mathbf{E}_x \left(\frac{q_1}{p_1} (1 - \Pi_{n+1}^1) \frac{f_{X_n}^1(X_{n+1})}{f_{X_n}^0(X_{n+1})} R_\rho^*(X_n, X_{n+1}) | D \right) \\ &= \frac{q_1}{p_1} (1 - \alpha) p_1 \mathbf{E} \left(\frac{f_u^0(X_{n+1})}{H(u, X_{n+1}, \alpha, \beta)} \frac{f_u^1(X_{n+1})}{f_u^0(X_{n+1})} R_\rho^*(X_n, X_{n+1}) | \mathcal{F}_n \right) | D \\ &\stackrel{(3.14)}{=} \frac{q_1}{p_1} (1 - \alpha) p_1 \int_{\mathbb{E}} \frac{f_u^1(s)}{H(u, s, \alpha, \beta)} H(u, s, \alpha, \beta) R_\rho^*(u, s) \mu(ds) \\ &= \frac{q_1}{p_1} (1 - \alpha) p_1 \int_{\mathbb{E}} R_\rho^*(u, s) f_u^1(s) \mu(ds) \end{aligned}$$

and

$$\begin{aligned} (5.20) \mathbf{Q}_x f(t, u, \vec{\alpha}) &= \frac{q_1}{p_1} (1 - \alpha) \max \left\{ \frac{f_t^1(u)}{f_t^0(u)} R_\rho^*(t, u), p_1 \int_{\mathbb{E}} R_\rho^*(u, s) f_u^1(s) \mu(ds) \right\} \\ &= \frac{q_1}{p_1} \alpha v_1(t, u). \end{aligned}$$

Let us define $v_1(t, u) = \max \left\{ \frac{f_t^1(u)}{f_t^0(u)} R_\rho^*(t, u), p_1 \int_{\mathbb{E}} R_\rho^*(u, s) f_u^1(s) \mu(ds) \right\}$ and

$$v_{n+1}(t, u) = \max \left\{ \frac{f_t^1(u)}{f_t^0(u)} R_\rho^*(t, u), p_1 \int_{\mathbb{E}} v_n(u, s) f_u^0(s) \mu(ds) \right\}.$$

We show that

$$(5.21) \quad \mathbf{Q}_x^\ell f(t, u, \vec{\alpha}) = \frac{q_1}{p_1} (1 - \alpha) v_\ell(t, u)$$

for $\ell = 1, 2, \dots$. We have by (5.20) that $\mathbf{Q}_x f(t, u, \vec{\alpha}) = \frac{q_1}{p_1} (1 - \alpha) v_1(t, u)$ and let us assume (5.21) for $\ell \leq k$. By (3.14) on $D = \{\omega : X_{n-1} = t, X_n = u, \Pi_n^1 = \alpha, \Pi_n^2 = \beta, \Pi_n^{12} = \gamma\}$ we have got

$$\begin{aligned} \mathbf{T}_x \mathbf{Q}_x^k f(t, u, \vec{\alpha}) &= \mathbf{E}_x \left(\frac{q_1}{p_1} (1 - \Pi_{k+1}^1) v_k(X_n, X_{n+1}) | D \right) \\ &= \frac{q_1}{p_1} (1 - \alpha) p_1 \int_{\mathbb{E}} v_k(u, s) f_u^0(s) \mu(ds). \end{aligned}$$

Hence we have got $\mathbf{Q}_x^{k+1}f = \frac{q_1}{p_1}(1 - \alpha)v_{k+1}$ and (5.21) is proved for $\ell = 1, 2, \dots$. This gives

$$f^*(t, u, \vec{\alpha}) = \frac{q_1}{p_1}(1 - \alpha) \lim_{k \rightarrow \infty} v_k(t, u) = \frac{q_1}{p_1}\alpha v^*(t, u)$$

and

$$V_m = \frac{q_1}{p_1}(1 - \Pi_m^1)v^*(X_{m-1}, X_m).$$

We have

$$\mathbf{T}_x f^*(t, u, \vec{\alpha}) = \frac{q_1}{p_1}(1 - \alpha)p_1 \int_{\mathbb{E}} v^*(u, s) f_u^0(s) \mu(ds).$$

Define $B^* = \{(t, u, \vec{\alpha}) : \frac{f_t^1(u)}{f_t^0(u)} R_\rho^*(t, u) \geq p_1 \int_{\mathbb{E}} v^*(u, s) f_u^0(s) \mu(ds)\}$ then τ_n^* for $n \geq 1$ has a form (5.17). The value of the problem (5.2), (5.5) and (2.5) is equal

$$v_0(x) = \max\{\pi, \mathbf{E}_x(V_1 | \mathcal{F}_0)\} = \max\{\pi, \frac{q_1}{p_1}(1 - \pi)p_1 \int_{\mathbb{E}} v^*(u, s) f_u^0(s) \mu(ds)\}$$

and

$$\hat{\tau}_0^* = \begin{cases} 0 & \text{if } \pi \geq q_1(1 - \pi) \int_{\mathbb{E}} v^*(u, s) f_u^0(s) \mu(ds), \\ \tau_0^* & \text{otherwise.} \end{cases}$$

✠

Based on Lemmas 5.3 and 5.1 the solution of the problem D_{00} can be formulated as follows.

THEOREM 5.2. *A compound stopping time $(\tau^*, \sigma_{\tau^*}^*)$, where σ_m^* is given by (5.7) and $\tau^* = \hat{\tau}_0^*$ is given by (5.17), is the solution of the problem D_{00} . The value of the problem*

$$\mathbf{P}_x(\tau^* < \sigma^* < \infty, \theta_1 = \tau^*, \theta_2 = \sigma_{\tau^*}^*) = \max\{\pi, q_1(1 - \pi) \int_{\mathbb{E}} v^*(u, s) f_u^0(s) \mu(ds)\}.$$

REMARK 5.2. *The problem can be extended to optimal detection of more than two successive disorders. The distribution of θ_1, θ_2 may be more general. The general a priori distributions of disorder moments leads to more complicated formulae, since the corresponding Markov chains are not homogeneous.*

6. FINAL REMARKS

It is notable that the final optimal solutions turns out to have an unexpectedly simple form. It seems that some further simplifications can be made in special cases. From a practical point of view, computer algorithms are necessary to construct B^* – the set in which we stop our observable sequence. Since we always refer to the transitions densities it is still open problem of switching between the independent Markov sequences.

7. APPENDICES

APPENDIX 1 — USEFUL RELATIONS

7.1. Distributions of disordered samples. Let us introduce the n -dimensional distribution for various configuration of disorders.

$$(7.1) \quad f_x^{\theta_1 \leq \theta_2 \leq n}(\vec{x}_{1,n}) = \bar{\pi} \rho \sum_{j=1}^n \{p_1^{j-1} q_1 \prod_{s=1}^{j-1} f_{x_{s-1}}^0(x_s) \prod_{t=j}^n f_{x_{t-1}}^2(x_t)\} \\ + \bar{\pi} \bar{\rho} \sum_{j=1}^{n-1} \sum_{k=j+1}^n \{p_1^{j-1} q_1 p_2^{k-j-1} q_2 \prod_{s=1}^{j-1} f_{x_{s-1}}^0(x_s) \prod_{t=j}^{k-1} f_{x_{t-1}}^1(x_t) \prod_{u=k}^n f_{x_{u-1}}^2(x_u)\} \\ + \pi \rho \prod_{s=1}^n f_{x_{s-1}}^2(x_s)$$

$$(7.2) \quad f_x^{\theta_1 \leq n < \theta_2}(\vec{x}_{1,n}) = \bar{\pi} \bar{\rho} \sum_{j=1}^n \{p_1^{j-1} q_1 p_2^{n-j} \prod_{s=1}^{j-1} f_{x_{s-1}}^0(x_s) \prod_{t=j}^n f_{x_{t-1}}^1(x_t)\} \\ + \pi \bar{\rho} \sum_{j=1}^n \{p_2^{j-1} q_2 \prod_{s=1}^{j-1} f_{x_{s-1}}^1(x_s) \prod_{t=j}^n f_{x_{t-1}}^2(x_t)\}$$

$$(7.3) \quad f_x^{\theta_1 = \theta_2 > n}(\vec{x}_{1,n}) = \rho \bar{\pi} p_1^n \prod_{s=1}^n f_{x_{s-1}}^0(x_s)$$

$$(7.4) \quad f_x^{n < \theta_1 < \theta_2}(\vec{x}_{1,n}) = \bar{\rho} \bar{\pi} p_1^n \prod_{s=1}^n f_{x_{s-1}}^0(x_s).$$

Let us define the sequence of functions $S_n : \times_{i=1}^n \mathbb{E} \rightarrow \mathfrak{R}$ as follows: $S_0(x_0) = 1$ and for $n \geq 1$

$$(7.5) \quad S_n(\vec{x}_n) = f_x^{\theta_1 \leq \theta_2 \leq n}(\vec{x}_{1,n}) + f_x^{\theta_1 \leq n < \theta_2}(\vec{x}_{1,n}) \\ + f_x^{\theta_1 = \theta_2 > n}(\vec{x}_{1,n}) + f_x^{n < \theta_1 < \theta_2}(\vec{x}_{1,n}).$$

LEMMA 7.1. For $n > 0$ the function $S_n(\vec{x}_{1,n})$ follows recursion

$$(7.6) \quad S_{n+1}(\vec{x}_{1,n+1}) = \mathbf{H}(x_n, x_{n+1}, \vec{\Pi}_n) S_n(\vec{x}_{1,n})$$

where

$$(7.7) \quad \mathbf{H}(x, y, \alpha, \beta, \gamma) = (1 - \alpha)p_1 f_x^0(y) + [p_2(\alpha - \beta) + q_1(1 - \alpha - \gamma)]f_x^1(y) \\ + [q_2\alpha + p_2\beta + q_1\gamma]f_x^2(y).$$

PROOF. Let us assume $0 \leq \theta_1 \leq \theta_2$ and suppose that $B_i \in \mathcal{B}$, $1 \leq i \leq n+1$ and let us assume that $X_0 = x$ and denote $D_n = \{\omega : X_i(\omega) \in B_i, 1 \leq i \leq n\}$. For $A_i = \{\omega : X_i \in B_i\} \in \mathcal{F}_i$, $1 \leq i \leq n+1$ we have by properties of the density function $S_n(\vec{x})$ with respect to the measure $\mu(\cdot)$

$$\begin{aligned} \int_{D_{n+1}} d\mathbf{P}_x &= \int_{\times_{i=1}^{n+1} B_i} S_{n+1}(\vec{x}_{n+1}) \mu(d\vec{x}_{1,n+1}) \\ &= \int_{\times_{i=1}^n B_i} \int_{B_{n+1}} f(x_{n+1} | \vec{x}_n) \mu(dx_{n+1}) S_n(\vec{x}_{0,n}) \mu(d\vec{x}_{1,n}) \\ &= \int_{\times_{i=1}^n B_i} \mathbf{P}(A_{n+1} | \vec{X}_n = x_n) \mu_x(d\vec{x}_{1,n}) \\ &= \int_{D_n} \mathbf{P}_x(A_{n+1} | \vec{X}_{1,n}) d\mathbf{P}_x = \int_{D_n} \mathbf{P}_x(A_{n+1} | \mathcal{F}_n) d\mathbf{P}_x = \int_{D_n} \mathbb{I}_{A_{n+1}} d\mathbf{P}_x \end{aligned}$$

Now we split the conditional probability of A_{n+1} into the following parts

$$(7.8) \quad \mathbf{P}_x(X_{n+1} \in A_{n+1} | \mathcal{F}_n) = \mathbf{P}_x(n < \theta_1 < \theta_2, X_{n+1} \in A_{n+1} | \mathcal{F}_n)$$

$$(7.9) \quad + \mathbf{P}_x(\theta_1 \leq n < \theta_2, X_{n+1} \in A_{n+1} | \mathcal{F}_n)$$

$$(7.10) \quad + \mathbf{P}_x(n < \theta_1 = \theta_2, X_{n+1} \in A_{n+1} | \mathcal{F}_n)$$

$$(7.11) \quad + \mathbf{P}_x(\theta_1 \leq \theta_2 \leq n, X_{n+1} \in A_{n+1} | \mathcal{F}_n)$$

In (7.8) we have:

$$\begin{aligned} \int_{D_n} \mathbf{P}_x(\theta_2 > \theta_1 > n, X_{n+1} \in A_{n+1} | \mathcal{F}_n) d\mathbf{P}_x &= \int_{D_n} (\mathbb{I}_{\{\theta_1 = n+1\}} + \mathbb{I}_{\{\theta_1 > n+1\}}) \mathbb{I}_{A_{n+1}} d\mathbf{P}_x \\ &= \int_{\times_{i=1}^{n+1} B_i} (f_x^{n < \theta_1 < \theta_2}(\vec{x}_{1,n}) (p_1 f_{x_n}^0(x_{n+1}) + q_1 f_{x_n}^1(x_{n+1}))) \mu(d\vec{x}_{1,n+1}) \\ &= \int_{\times_{i=1}^n B_i} (f_x^{n < \theta_1 < \theta_2}(\vec{x}_{1,n}) \int_{B_{n+1}} (p_1 f_{x_n}^0(x_{n+1}) + q_1 f_{x_n}^1(x_{n+1}))) \mu(dx_{n+1}) \mu(d\vec{x}_{1,n}) \\ &= \int_{D_n} \mathbf{P}_x(\theta_2 > \theta_1 > n | \mathcal{F}_n) [\mathbf{P}_{X_n}^0(A_{n+1}) p_1 + q_1 \mathbf{P}_{X_n}^1(A_{n+1})] d\mathbf{P}_x. \end{aligned}$$

In (7.9) we get by similar arguments as for (7.8)

$$\begin{aligned}
& \mathbf{P}_x(\theta_1 \leq n < \theta_2 \quad , \quad X_{n+1} \in A_{n+1} \mid \mathcal{F}_n) \\
&= \mathbf{P}_x(\theta_1 \leq n < \theta_2, \theta_2 = n+1, X_{n+1} \in A_{n+1} \mid \mathcal{F}_n) \\
&\quad + \mathbf{P}_x(\theta_1 \leq n < \theta_2, \theta_2 \neq n+1, X_{n+1} \in A_{n+1} \mid \mathcal{F}_n) \\
&= (\mathbf{P}_x(\theta_1 \leq n \mid \mathcal{F}_n) - \mathbf{P}_x(\theta_2 \leq n \mid \mathcal{F}_n)) \\
&\quad \times [q_2 \mathbf{P}_{X_n}^2(A_{n+1}) + p_2 \mathbf{P}_{X_n}^1(A_{n+1})]
\end{aligned}$$

In (7.11) this part has the form:

$$\mathbf{P}_x(\theta_2 \leq n, X_{n+1} \in A_{n+1} \mid \mathcal{F}_n) = \mathbf{P}_x(\theta_2 \leq n \mid \mathcal{F}_n) \mathbf{P}_{X_n}^2(A_{n+1})$$

In (7.10) the conditional probability is equal to

$$\begin{aligned}
& \mathbf{P}_x(\theta_1 = \theta_2 > n \quad , \quad X_{n+1} \in A_{n+1} \mid \mathcal{F}_n) \\
&= \mathbf{P}_x(\theta_1 = \theta_2 > n, \theta_2 = n+1, X_{n+1} \in A_{n+1} \mid \mathcal{F}_n) \\
&\quad + \mathbf{P}_x(\theta_1 = \theta_2 > n, \theta_2 \neq n+1, X_{n+1} \in A_{n+1} \mid \mathcal{F}_n) \\
&= \mathbf{P}_x(\theta_1 = \theta_2 > n \mid \mathcal{F}_n) [q_1 \mathbf{P}_{X_n}^2(A_{n+1}) + p_1 \mathbf{P}_{X_n}^0(A_{n+1})]
\end{aligned}$$

These formula lead to

$$f(X_{n+1} \mid \vec{X}_{1,n}) = \mathbf{H}(X_n, X_{n+1}, \Pi_n^1, \Pi_n^2, \Pi_n^{12}).$$

which proves the lemma. ✠

7.2. Conditional probability of various events defined by disorder moments. According to definition of $\Pi_n^1, \Pi_n^2, \Pi_n^{12}$ we get

LEMMA 7.2. *For the model described in Section 2 the following formulae are valid:*

1. $\mathbf{P}_x(\theta_2 > \theta_1 > n \mid \mathcal{F}_n) = 1 - \Pi_n^1 - \Pi_n^{12} = \frac{f_x^{n < \theta_1 < \theta_2}(\vec{x}_{1,n})}{S_n(\vec{x}_n)}$;
2. $\mathbf{P}_x(\theta_2 = \theta_1 > n \mid \mathcal{F}_n) = \Pi_n^{12} = \frac{f_x^{\theta_1 = \theta_2 > n}(\vec{x}_{1,n})}{S_n(\vec{x}_n)}$;
3. $\mathbf{P}_x(\theta_1 \leq n < \theta_2 \mid \mathcal{F}_n) = \Pi_n^1 - \Pi_n^2$;
4. $\mathbf{P}_x(\theta_2 \geq \theta_1 > n \mid \mathcal{F}_n) = 1 - \Pi_n^1 = \frac{\bar{\pi} p_1^n \prod_{s=1}^n f_{x_{s-1}}^0(x_s)}{S_n(\vec{x}_n)}$.

PROOF.

1. We have

$$(7.12) \quad \begin{aligned} \Omega &= \{\omega : n < \theta_1 < \theta_2\} \cup \{\omega : \theta_1 \leq n < \theta_2\} \\ &\cup \{\omega : \theta_1 \leq \theta_2 \leq n\} \cup \{\omega : \theta_1 = \theta_2 > n\}. \end{aligned}$$

Hence $1 = \mathbf{P}_x(\omega : n < \theta_1 < \theta_2 | \mathcal{F}_n) + (\Pi_n^1 - \Pi_n^2) + \Pi_n^2 + \Pi_n^{12}$ and

$$\mathbf{P}_x(\omega : n < \theta_1 < \theta_2 | \mathcal{F}_n) = 1 - \Pi_n^1 - \Pi_n^{12}.$$

Let $B_i \in \mathcal{B}$, $1 \leq i \leq n$, $X_0 = x$ and denote $D_n = \{\omega : X_i(\omega) \in B_i, 1 \leq i \leq n\}$. For $A_i = \{\omega : X_i \in B_i\} \in \mathcal{F}_i$, $1 \leq i \leq n$ and $D_n \in \mathcal{F}_n$ we have

$$\begin{aligned} \int_{D_n} \mathbb{I}_{\{\theta_2 > \theta_1 > n\}} d\mathbf{P}_x &= \int_{D_n} \mathbf{P}_x(\theta_2 > \theta_1 > n | \mathcal{F}_n) d\mathbf{P}_x = \int_{D_n} \mathbf{P}_x(\theta_2 > \theta_1 > n | \vec{X}_n) d\mathbf{P}_x \\ &= \mathbf{P}_x(\theta_2 > \theta_1 > n, D_n) = \int_{\times_{i=1}^n B_i} f_x^{n < \theta_1 < \theta_2}(\vec{x}_{1,n}) \mu(d\vec{x}_{1,n}) \\ &= \int_{\times_{i=1}^n B_i} f_x^{n < \theta_1 < \theta_2}(\vec{x}_{1,n}) (S_n(\vec{x}_n))^{-1} \mu_x(d\vec{x}_{1,n}) \\ &= \int_{D_n} f_x^{n < \theta_1 < \theta_2}(\vec{X}_{1,n}) (S_n(\vec{X}_n))^{-1} d\mathbf{P}_x. \end{aligned}$$

Thus $\mathbf{P}_x(\theta_2 > \theta_1 > n | \mathcal{F}_n) = \bar{\rho} \bar{\pi} p_1^n \prod_{i=1}^n f_{X_{i-1}}^0(X_i) (S_n(\vec{X}_n))^{-1}$.

2. The second formula can be obtained by similar argument.

3. Let $\theta_1 \leq \theta_2$. Since $\{\omega : \theta_2 \leq n\} \subset \{\omega : \theta_1 \leq n < \theta_n\} | \mathcal{F}_n = \mathbf{P}_x(\{\omega : \theta_1 \leq n\} \setminus \{\omega : \theta_2 \leq n\} | \mathcal{F}_n) = \Pi_n^1 - \Pi_n^2$.

These end the proof of the lemma. \boxtimes

REMARK 7.1. Let $B_i \in \mathcal{B}$, $1 \leq i \leq n+1$, $X_0 = x$ and denote $D_n = \{\omega : X_i(\omega) \in B_i, 1 \leq i \leq n\}$. For $A_i = \{\omega : X_i \in B_i\} \in \mathcal{F}_i$, $1 \leq i \leq n$ and $D_n \in \mathcal{F}_n$ we have

$$\begin{aligned} \int_{D_n} \mathbb{I}_{\{\theta_1 > n\}} d\mathbf{P}_x &= \int_{D_n} \mathbf{P}_x(\theta_1 > n | \mathcal{F}_n) d\mathbf{P}_x = \int_{D_n} \mathbf{P}_x(\theta_1 > n | \vec{X}_n) d\mathbf{P}_x \\ &= \mathbf{P}_x(\theta_1 > n, D_n) = \int_{\times_{i=1}^n B_i} p_1^n \prod_{i=1}^n f_{x_{i-1}}^0(x_i) \mu(d\vec{x}_{1,n}) \\ &= \int_{\times_{i=1}^n B_i} p_1^n \prod_{i=1}^n f_{x_{i-1}}^0(x_i) (S_n(\vec{x}_n))^{-1} \mu_x(d\vec{x}_{1,n}). \end{aligned}$$

Thus $\mathbf{P}_x(\theta_1 > n | \mathcal{F}_n) = p_1^n \prod_{i=1}^n f_{X_{i-1}}^0(X_i)(S_n(\vec{X}_n))^{-1}$. Moreover

$$1 - \Pi_{n+1}^1 = p_1 f_{X_n}^0(X_{n+1})(1 - \Pi_n^1) S_n(\vec{X}_n)(S_{n+1}(\vec{X}_{n+1}))^{-1}$$

and $S_{n+1}(\vec{X}_{n+1}) = \mathbf{H}(X_n, X_{n+1}, \vec{\Pi}_n^1) S_n(\vec{X}_n)$. Hence

$$\Pi_{n+1}^1 = 1 - \frac{p_1 f_{X_n}^0(X_{n+1})(1 - \Pi_n^1)}{\mathbf{H}(X_n, X_{n+1}, \vec{\Pi}_n^1)}.$$

7.3. Some recursive formulae. In derivation of the formulae in Theorem 3.1 the form of the distribution of some random vectors is taken into account.

LEMMA 7.3. *For the model described in Section 2 the following formulae are valid:*

1. $\mathbf{P}_x(\theta_2 = \theta_1 > n + 1 | \mathcal{F}_n) = p_1 \Pi_n^{12} = p_1 \rho(1 - \Pi_n^1)$;
2. $\mathbf{P}_x(\theta_2 > \theta_1 > n + 1 | \mathcal{F}_n) = p_1(1 - \Pi_n^1 - \Pi_n^{12})$;
3. $\mathbf{P}_x(\theta_1 \leq n + 1 | \mathcal{F}_n) = \mathbf{P}_x(\theta_1 \leq n + 1 < \theta_2 | \mathcal{F}_n) + \mathbf{P}_x(\theta_2 \leq n + 1 | \mathcal{F}_n)$;
4. $\mathbf{P}_x(\theta_1 \leq n + 1 < \theta_2 | \mathcal{F}_n) = q_1(1 - \Pi_n^1 - \Pi_n^{12}) + p_2(\Pi_n^1 - \Pi_n^2)$;
5. $\mathbf{P}_x(\theta_2 \leq n + 1 | \mathcal{F}_n) = q_2 \Pi_n^1 + p_2 \Pi_n^2 + q_1 \Pi_n^{12}$.
6. $\mathbf{P}_x(\theta_1 = m, \theta_2 > n + 1 | \mathcal{F}_n) = p_2 \Pi_m n$.

PROOF.

1. On the set $D = \{\omega : X_0 = x, X_1 \in A_1, X_2 \in A_2, \dots, X_n \in A_n\} \in \mathcal{F}_n$ we have

$$\begin{aligned} \int_D \mathbb{I}_{\{\theta_2 = \theta_1 > n + 1\}} d\mathbf{P}_x &= \mathbf{P}_x(D) \mathbf{P}_x(\theta_2 = \theta_1 > n + 1 | D) \\ &= \rho \bar{\pi} \sum_{j=n+2}^{\infty} p_1^{j-1} q_1 \int_{\times_{i=1}^n A_i} \prod_{i=1}^n f_{x_{i-1}}^0(x_i) \mu(d\vec{x}_{1,n}) \\ &= p_1 \rho \bar{\pi} p_1^n \int_{\times_{i=1}^n A_i} \prod_{i=1}^n f_{x_{i-1}}^0(x_i) \mu(d\vec{x}_{1,n}) \\ &= p_1 \mathbf{P}_x(D) \mathbf{P}_x(\theta_2 = \theta_1 > n | D) = p_1 \int_D \mathbb{I}_{\{\theta_2 = \theta_1 > n\}} d\mathbf{P}_x. \end{aligned}$$

By (3.2) and the definition of the conditional probability this implies $\mathbf{P}_x(\theta_2 = \theta_1 > n + 1 | \mathcal{F}_n) =$

$p_1 \Pi_n^{12}$. Next,

$$\begin{aligned}
\int_D \mathbb{I}_{\{\theta_1 > n\}} d\mathbf{P}_x &= \mathbf{P}_x(D) \mathbf{P}_x(\theta_1 > n | D) \\
&= \bar{\pi} \sum_{j=n+1}^{\infty} p_1^{j-1} q_1 \int_{\times_{i=1}^n A_i} \prod_{i=1}^n f_{x_{i-1}}^0(x_i) \mu(d\vec{x}_{1,n}) \\
&= \frac{1}{\rho} \mathbf{P}_x(D) \mathbf{P}_x(\theta_2 = \theta_1 > n | D) = \frac{1}{\rho} \int_D \mathbb{I}_{\{\theta_2 = \theta_1 > n\}} d\mathbf{P}_x.
\end{aligned}$$

These prove the part 1 of the lemma.

2. Similarly as above we get

$$\begin{aligned}
\int_D \mathbb{I}_{\{\theta_2 > \theta_1 > n+1\}} d\mathbf{P}_x &= \mathbf{P}(D) \mathbf{P}_x(\theta_2 > \theta_1 > n+1 | D) \\
&= p_1 \rho \bar{\pi} p_1^n \int_{\times_{i=1}^n A_i} \prod_{i=1}^n f_{x_{i-1}}^0(x_i) \mu(d\vec{x}_{1,n}) \\
&= p_1 \mathbf{P}(D) \mathbf{P}_x(\theta_2 > \theta_1 > n | D) = p_1 \int_D \mathbb{I}_{\{\theta_2 > \theta_1 > n\}} d\mathbf{P}_x
\end{aligned}$$

By point 2 of Lemma 7.2 we get the formula 2 of the lemma.

3. It is obvious by assumption $\theta_1 \leq \theta_2$.

4. On the set D we have

$$\begin{aligned}
\int_D \mathbb{I}_{\{\theta_1 \leq n+1 < \theta_2\}} d\mathbf{P}_x &= \mathbf{P}(D) \mathbf{P}_x(\theta_1 \leq n+1 < \theta_2 | D) \\
&\stackrel{(2.1), (2.2)}{=} \sum_{j=0}^{n+1} \mathbf{P}(\omega : \theta_1 = j) \sum_{k=n+2}^{\infty} \bar{\rho} p_2^{k-j-1} q_2 \int_{\times_{i=1}^n A_i} \prod_{s=1}^{j-1} f_{x_{s-1}}^0(x_s) \prod_{r=j}^n f_{x_{r-1}}^1(x_r) \mu(d\vec{x}_{1,n}) \\
&= \bar{\pi} p_1^n q_1 (1 - \rho) \int_{\times_{i=1}^n A_i} \prod_{s=1}^n f_{x_{s-1}}^0(x_s) \mu(d\vec{x}_{1,n}) \\
&\quad + p_2 \sum_0^n \mathbf{P}(\omega : \theta_1 = j) p_2^{n+1-j} \int_{\times_{i=1}^n A_i} \prod_{s=1}^{j-1} f_{x_{s-1}}^0(x_s) \prod_{r=j}^n f_{x_{r-1}}^1(x_r) \mu(d\vec{x}_{1,n}) \\
&\stackrel{(L.7.2)}{=} q_1 \mathbf{P}(D) \mathbf{P}_x(\theta_2 > \theta_1 > n | D) + p_2 \mathbf{P}(D) \mathbf{P}_x(\theta_1 \leq n < \theta_2 | D) \\
&= q_1 \int_D \mathbb{I}_{\{\theta_2 > \theta_1 > n\}} d\mathbf{P}_x + p_2 \int_D \mathbb{I}_{\{\theta_1 \leq n < \theta_2\}} d\mathbf{P}_x.
\end{aligned}$$

5. If we substitute n by $n + 1$ in (7.12) than we obtain

$$\begin{aligned}
\mathbf{P}_x(\theta_2 \leq n + 1 | \mathcal{F}_n) &= 1 - \mathbf{P}_x(n + 1 < \theta_1 = \theta_2 | \mathcal{F}_n) \\
&\quad - \mathbf{P}_x(n + 1 < \theta_1 < \theta_2 | \mathcal{F}_n) - \mathbf{P}_x(\theta_1 \leq n + 1 < \theta_2 | \mathcal{F}_n) \\
&= 1 - p_1 \Pi_n^{12} - p_1(1 - \Pi_n^1 - \Pi_n^{12}) - q_1(1 - \Pi_n^1 - \Pi_n^{12}) \\
&\quad + p_2(\Pi_n^2 - \Pi_n^1) = q_2 \Pi_n^1 + p_2 \Pi_n^2 + q_1 \Pi_n^{12}.
\end{aligned}$$

6. We have

$$\begin{aligned}
\int_D \mathbb{I}_{\{\theta_1=m, \theta_2>n+1\}} d\mathbf{P}_x &= \mathbf{P}_x(D) \mathbf{P}_x(\theta_1 = m, \theta_2 > n + 1 | D) \\
&= \bar{\pi} \bar{\rho} p_1^{m-1} q_1 \sum_{j=n+2}^{\infty} p_2^{j-m-1} q_2 \int_{\times_{i=1}^n B_i} \prod_{i=1}^m f_{x_{i-1}}^0(x_i) \prod_{j=m+1}^n f_{x_{j-1}}^1(x_j) \mu(d\vec{x}_{1,n}) \\
&= p_2 \bar{\pi} \bar{\rho} p_1^{m-1} q_1 p_2^{n-m} \int_{\times_{i=1}^n B_i} \prod_{i=1}^m f_{x_{i-1}}^0(x_i) \prod_{j=m+1}^n f_{x_{j-1}}^1(x_j) \mu(d\vec{x}_{1,n}) \\
&= p_2 \mathbf{P}_x(D) \mathbf{P}_x(\theta_1 = m, \theta_2 > n | D) = p_2 \int_D \mathbb{I}_{\{\theta_1=m, \theta_2>n\}} d\mathbf{P}_x.
\end{aligned}$$

By (3.3) and the definition of conditional probability this implies $\mathbf{P}_x(\theta_2 = m, \theta_1 > n + 1 | \mathcal{F}_n) = p_2 \Pi_n^m$. These prove the part 6 of the lemma. \spadesuit

Acknowledgements. I have benefited from discussions with Wojciech Sarnowski and Anna Karpowicz, for which I am grateful. I should like to thank Professor Elżbieta Ferenstein for helpful suggestions. They provided numerous corrections to the manuscript.

REFERENCES

- [1] M. Baron. Early detection of epidemics as a sequential change-point problem. In V. Antonov, C. Huber, M. Nikulin, and V. Polischuk, editors, *Longevity, aging and degradation models in reliability, public health, medicine and biology, LAD 2004. Selected papers from the first French-Russian conference, St. Petersburg, Russia, June 7–9, 2004*, volume 2 of *IMS Lecture Notes-Monograph Series*, pages 31–43, St. Petersburg, Russia, 2004. St. Petersburg State Polytechnical University.
- [2] M. Basseville and A. Benveniste, editors. *Detection of abrupt changes in signals and dynamical systems*, volume 77 of *Lecture Notes in Control and Information Sciences*, page 373. Springer-Verlag, Berlin, 1986.

-
- [3] T. Bojdecki. Probability maximizing approach to optimal stopping and its application to a disorder problem. *Stochastics*, 3:61–71, 1979.
- [4] T. Bojdecki and J. Hosza. On a generalized disorder problem. *Stochastic Processes Appl.*, 18:349–359, 1984.
- [5] B.E. Brodsky and B.S. Darkhovsky. *Nonparametric Methods in Change-Point Problems*. Mathematics and its Applications (Dordrecht). 243. Dordrecht: Kluwer Academic Publishers. 224 p., Dordrecht, 1993.
- [6] P. Dube and R. Mazumdar. A framework for quickest detection of traffic anomalies in networks. Technical report, Electrical and Computer Engineering, Purdue University, November 2001. citeseer.ist.psu.edu/506551.html.
- [7] Ch.-D. Fuh. Asymptotic operating characteristics of an optimal change point detection in hidden Markov models. *Ann. Stat.*, 32(5):2305–2339, 2004.
- [8] G.W. Haggstrom. Optimal sequential procedures when more than one stop is required. *Ann. Math. Statist.*, 38:1618–1626, 1967.
- [9] T. L. Lai. Sequential changepoint detection in quality control and dynamical systems (with discussion). *J. R. Stat. Soc., Ser. B*, 57(4):613–658, 1995.
- [10] T. L. Lai. Information bounds and quick detection of parameter changes in stochastic systems. *IEEE Trans. Inf. Theory*, 44(7):2917–2929, 1998.
- [11] G.V. Moustakides. Quickest detection of abrupt changes for a class of random processes. *IEEE Trans. Inf. Theory*, 44(5):1965–1968, 1998.
- [12] M.L. Nikolaev. Obobshchennye posledovatel'nye procedury. *Litovskii Matematicheskii Sbornik*, 19:35–44, 1979.
- [13] M.L. Nikolaev. O kriterii optimal'nosti obobshchennoi posledovatel'noj procedury. *Litov. Mat. Sb.*, 21:75–82, 1981. On the criterion of optimality of the extended sequential procedure (in Russian).
- [14] L. Pelkowitz. The general discrete-time disorder problem. *Stochastics*, 20:89–110, 1987.
- [15] L. Pelkowitz. The general Markov chain disorder problem. *Stochastics*, 21:113–130, 1987.
- [16] W. Sarnowski and K. Szajowski. On-line detection of a part of a sequence with unspecified distribution. *Stat. Probab. Lett.*, 78(15):2511–2516, 2008. doi:10.1016/j.spl.2008.02.040.
- [17] W.A. Shewhart. *Economic control of quality of manufactured products*. D. Van Nostrand, New York, 1931.

- [18] A.N. Shiryaev. The detection of spontaneous effects. *Sov. Math, Dokl.*, 2:740–743, 1961. translation from Dokl. Akad. Nauk SSSR 138, 799-801 (1961).
- [19] A.N. Shiryaev. *Optimal Stopping Rules*. Springer-Verlag, New York, Heidelberg, Berlin, 1978.
- [20] K. Szajowski. Optimal on-line detection of outside observation. *J.Stat. Planning and Inference*, 30:413–426, 1992.
- [21] K. Szajowski. A two-disorder detection problem. *Appl. Math.*, 24(2):231–241, 1996.
- [22] A. G. Tartakovsky, B. L. Rozovskii, R. B. Blažek, and H. Kim. Detection of intrusions in information systems by sequential change-point methods. *Stat. Methodol.*, 3(3):252–293, 2006.
- [23] A. G. Tartakovsky and V. V. Veeravalli. Asymptotically optimal quickest change detection in distributed sensor systems. *Sequential Anal.*, 27(4):441–475, 2008.
- [24] B. Yakir. Optimal detection of a change in distribution when the observations form a Markov chain with a finite state space. In E. Carlstein, H.-G. Müller, and D. Siegmund, editors, *Change-point Problems. Papers from the AMS-IMS-SIAM Summer Research Conference held at Mt. Holyoke College, South Hadley, MA, USA, July 11–16, 1992*, volume 23 of *IMS Lecture Notes-Monograph Series*, pages 346–358, Hayward, California, 1994. Institute of Mathematical Statistics.
- [25] M. Yoshida. Probability maximizing approach for a quickest detection problem with complicated Markov chain. *J. Inform. Optimization Sci.*, 4:127–145, 1983.

Institute of Mathematics and Computer Science
Wrocław University of Technology
Wybrzeże Wyspiańskiego 27
50-370 Wrocław, Poland
E-mail: Krzysztof.Szajowski@pwr.wroc.pl

*Received on 23rd of November 2008;
last revised version on 2nd of January 2010*
