

Operator Splitting Based Dynamic Iteration for Linear Port-Hamiltonian Systems

Andreas Bartel¹, Michael Günther¹, Birgit Jacob¹ and Timo Reis²

¹ IMACM, Bergische Universität Wuppertal,
Gaußstr. 20, 42119 Wuppertal, Germany

² Institut für Mathematik, Technische Universität Ilmenau,
Weimarer Str. 25, 98693 Ilmenau, Germany

August 9, 2022

Abstract. A dynamic iteration scheme for linear differential-algebraic port-Hamiltonian systems based on Lions-Mercier-type operator splitting methods is developed. The dynamic iteration is monotone in the sense that the error is decreasing and no stability conditions are required. The developed iteration scheme is even new for linear port-Hamiltonian systems. The obtained algorithm is applied to multibody systems and electrical networks.

Keywords. Port-Hamiltonian Systems, DAE, Operator Splitting, Dynamic Iteration.

MSC Classification. 37Jxx, 34A09

1 Introduction

Dynamic iteration schemes for differential-algebraic equations (DAE) have been widely used and discussed for multiphysics problems, which allow for an easy exploitation of the different properties of the subsystems [1, 3, 4, 6–8]. In general, we consider an initial value problem for a (semi-explicit index-1) DAE on $t \in [0, T]$ of the form

$$\dot{v} = f(t, v, w), \quad v(0) = v_0, \quad (1a)$$

$$0 = g(t, v, w), \quad (1b)$$

where $\partial g(t, v, w)/\partial w$ is regular in a neighborhood of the solution $(v(t), w(t))^\top$, $t \in [0, T]$. A general dynamic iteration scheme is given by an initial guess $(v^{(0)}(t), w^{(0)}(t))^\top$ ($t \in [0, T]$), i.e., an initial

waveform) and the solution $(v^{(k)}(t), w^{(k)}(t))^\top$ of the DAE for integer $k \geq 1$

$$\begin{aligned} \dot{v}^{(k)} &= F(t, v^{(k)}, v^{(k-1)}, w^{(k)}, w^{(k-1)}), & v^{(k)}(0) &= v_0, \\ 0 &= G(t, v^{(k)}, v^{(k-1)}, w^{(k)}, w^{(k-1)}) \end{aligned}$$

with arbitrary splitting functions F, G fulfilling the compatibility conditions

$$F(t, v, v, w, w) = f(t, v, w) \quad \text{and} \quad G(t, v, v, w, w) = g(t, v, w).$$

Hence a dynamic iteration defines as a mapping from the $(k-1)$ -th iterate to the k -th iterate:

$$(v^{(k-1)}(t), w^{(k-1)}(t)) \mapsto (v^{(k)}(t), w^{(k)}(t)).$$

One drawback of such schemes for DAE is given by the fact that stability conditions for a guaranteed convergence must hold in a twofold manner:

- (a) convergence within one time window has to be present [4, 15], and
- (b) stable error propagation from window to window is needed [1, 4].

If one of these conditions is not met choosing arbitrary small time windows will not help out (in general).

In the case of initial value problems of ordinary differential equations

$$\dot{x} = f(t, x), \quad x(0) = x_0, \quad t \in [0, T],$$

convergence of dynamic iteration schemes (analogously defined) is given for arbitrary long time windows $[0, T]$. However, the convergence might not be monotone, and the error might increase drastically in the beginning, causing an overflow in computer implementations, see chapter 3 for an example.

In this work, we show that an alternative iterative approach for linear DAE systems can avoid both flaws described above if the DAE system (1) is composed of coupled port-Hamiltonian systems. This type of systems is motivated by physics, provides an energy balance and gives a simple framework for coupled systems [9, 12, 13, 16, 20, 21, 23–25]. Now, the alternative iterative approach is based on an iteration scheme from Lions and Mercier [19]. The convergence will be monotone, and no stability conditions appear.

The paper is organized as follows: in the subsequent chapter 2, the framework of linear coupled port-Hamiltonian DAE systems is set. Both, the perspective of an overall coupled system and the perspective of a system composed of coupled port-Hamiltonian DAE subsystems is given. Chapter 3 illustrates the limits of classical dynamic iteration schemes such as the Jacobi iteration, which motivates the derivation and analysis of operator splitting based dynamic iteration schemes in the following. Chapter 4 recapitulates some basic facts on maximal monotone operators, which are used in chapter 5 to derive the monotone convergence results of operator splitting based dynamic iteration schemes. An estimate for the convergence rate can be given in the case of ODE systems and DAE systems with enough dissipation. Numerical results are discussed in chapter 6. The paper finishes with some concluding remarks and an outlook.

2 The setting

We consider linear time-invariant initial value problems of DAEs, which have the following structure:

Definition 1. For a final time $T > 0$, the descriptor variable $x(t) \in \mathbb{R}^n$ and $t \in [0, T]$, we consider

$$\frac{d}{dt}Ex(t) = (J - R)Qx(t) + Bu(t), \quad t \in [0, T], \quad Ex(0) = Ex_0, \quad (2a)$$

$$y(t) = B^\top Qx(t), \quad (2b)$$

where E , J , R and Q are real $n \times n$ -matrices, B is a $n \times m$ -matrix, $Ex_0 \in \mathbb{R}^n$ is a given initial value, u is a given input and y is referred to as output. (The matrix E may have no full rank.) \square

Throughout this article, we are working with weak solutions.

Definition 2 (Solution). Let $x_0 \in \mathbb{R}^n$ and $u \in L^2([0, T], \mathbb{R}^m)$. A function $x \in L^2([0, T], \mathbb{R}^n)$ is called (weak) solution of (2) if $Ex \in H^1([0, T], \mathbb{R}^n)$, $Ex(0) = Ex_0$ and (2) is satisfied for $t \in [0, T]$ almost everywhere. \square

Proposition 3. Assume that a differential-algebraic system (2) is given with $E, J, R \in \mathbb{R}^{n \times n}$, $B \in \mathbb{R}^{n \times m}$ satisfying $E^\top Q = Q^\top E \geq 0$, $R = R^\top \geq 0$ and $J^\top = -J$. Furthermore, let $u \in L^2([0, T], \mathbb{R}^m)$, $x_0 \in \mathbb{R}^n$, and let $x \in L^2([0, T], \mathbb{R}^n)$ be a solution of (2). Then the following statements hold:

(a) The function $t \mapsto x(t)^\top Q^\top Ex(t)$ is weakly differentiable with

$$\frac{d}{dt}(x^\top Q^\top Ex) = 2x^\top Q^\top \left(\frac{d}{dt}Ex \right) \in L^1([0, T], \mathbb{R}).$$

(b) The following dissipation inequality holds for all $t \in [0, T]$:

$$\begin{aligned} & \frac{1}{2}(x(t)^\top Q^\top Ex(t)) - \frac{1}{2}(x_0^\top Q^\top Ex_0) \\ &= - \int_0^t x(\tau)^\top Q^\top RQx(\tau) d\tau + \int_0^t u(\tau)^\top y(\tau) d\tau \leq \int_0^t u(\tau)^\top y(\tau) d\tau. \end{aligned}$$

Proof. (a) We have $E^\top Q = Q^\top E$, and thus, for the Moore-Penrose inverse E^+ of E , we have

$$E^\top Q = E^\top (E^+)^\top E^\top Q = E^\top (E^+)^\top Q^\top E.$$

Consequently, for $X = (E^+)^\top Q^\top \in \mathbb{R}^{n \times n}$, we have $Q^\top E = E^\top XE$. By using that $Ex \in H^1([0, T], \mathbb{R}^n)$, the product rule for weak derivatives [2, Thm. 4.25] implies that

$$x^\top Q^\top Ex = (Ex)^\top X(Ex) \in W^{1,1}([0, T], \mathbb{R})$$

with

$$\begin{aligned} \frac{d}{dt}(x^\top Q^\top Ex) &= \frac{d}{dt} \left((Ex)^\top X(Ex) \right) = 2x^\top E^\top X \frac{d}{dt}(Ex) = 2x^\top \frac{d}{dt} \left(E^\top XEx \right) \\ &= 2x^\top \frac{d}{dt} \left(Q^\top Ex \right) = 2x^\top Q^\top \frac{d}{dt}(Ex). \end{aligned}$$

(b) The previous statement yields

$$\begin{aligned} \frac{d}{dt} \frac{1}{2} (x^\top Q^\top E x) &= x^\top Q^\top \frac{d}{dt} (E x) = x^\top Q^\top ((J - R) Q x + B u) \\ &= -(Q x)^\top R (Q x) + x^\top Q B u \leq (B^\top Q x)^\top u = y^\top u. \end{aligned}$$

Now an integration on $[0, t]$ leads to the dissipation inequality. \square

Thus, we investigate the following class of port-Hamiltonian DAEs:

Definition 4 (PH-DAE). *The system (2) with the assumptions of Prop. 3 is here referred as port-Hamiltonian DAE (PH-DAE).* \square

2.1 Perspective as overall coupled system

We further assume that (2) is composed of several port-Hamiltonian systems which are coupled in an energy-preserving way. The assumptions are collected in the following.

Assumption 5. (Overall coupled PH-DAE) *We consider the setting (2).*

(a) *The matrices in (2) are, for some $s, n_1, \dots, n_s \in \mathbb{N}$, structured as*

$$E = \begin{bmatrix} E_1 & & \\ & \ddots & \\ & & E_s \end{bmatrix}, \quad R = \begin{bmatrix} R_1 & & \\ & \ddots & \\ & & R_s \end{bmatrix}, \quad Q = \begin{bmatrix} Q_1 & & \\ & \ddots & \\ & & Q_s \end{bmatrix}, \quad (3)$$

$$J = \begin{bmatrix} J_1 & J_{12} & \cdots & J_{1s} \\ -J_{12}^\top & \ddots & \ddots & \vdots \\ \vdots & \ddots & \ddots & J_{s-1,s} \\ -J_{1s}^\top & \cdots & -J_{s-1,s}^\top & J_s \end{bmatrix}, \quad B = \begin{bmatrix} B_1 \\ \vdots \\ \vdots \\ B_s \end{bmatrix}, \quad (4)$$

with $n_1 + n_2 + \dots + n_s = n$, where

- (i) for $i = 1, \dots, s$, $E_i, Q_i, J_i, R_i \in \mathbb{R}^{n_i \times n_i}$ with $R_i = R_i^\top \geq 0$, $J_i^\top = -J_i$, $E_i^\top Q_i = Q_i^\top E_i \geq 0$, Q_i invertible and $B_i \in \mathbb{R}^{n_i \times m}$;
- (ii) $J_{ij} \in \mathbb{R}^{n_i \times n_j}$ for $i, j \in \{1, \dots, s\}$ with $i < j$.

(b) $\text{rk} \begin{bmatrix} E & R & J \end{bmatrix} = n$.

(c) $T > 0$, $x_0 \in \mathbb{R}^n$ and $u \in L^2([0, T]; \mathbb{R}^m)$. Furthermore, for matrices $Z \in \mathbb{R}^{n \times r}$, $Z_1 \in \mathbb{R}^{r \times r_1}$, with full column rank and

$$\begin{aligned} \text{im } Z &= \ker E, \\ \text{im } Z_1 &= \ker R Q Z \cap \ker Z^\top Q^\top J Q Z, \end{aligned}$$

the input u and the initial value x_0 fulfill

$$Z_1^\top Z^\top Q^\top B u \in H^1([0, T]; \mathbb{R}^{r_1}) \quad \text{with } Z_1^\top Z^\top Q^\top (J Q x_0 + B u(0)) = 0. \quad \square$$

Remark 6. Notice that with Assumption 5, we have for (2):

(a) $Q^\top E = E^\top Q \geq 0$, $R = R^\top \geq 0$, and Q is invertible. Hence, the overall coupled PH-DAE of Assumption 5 is a PH-DAE (in the sense of Definition 4).

(b) As $Q^\top E \geq 0$, we have that $EQ^{-1} = Q^{-\top}(Q^\top E)Q^{-1}$ is positive semi-definite as well, and therefore possesses a matrix square root $(EQ^{-1})^{1/2}$.

(c) The i th subsystem for the variable x_i reads:

$$E_i x_i = (J_i - R_i)Q_i x_i + B_i u - \sum_{j < i} J_{ji}^\top Q_j x_j + \sum_{i < j} J_{ij} Q_j x_j.$$

The coupling is facilitated by the off-diagonal terms within the matrix J . □

Remark 7 (Coupled linear PH-DAE systems). A PH-DAE system of type (2) with coupling structure (3) and (4) is naturally given in the case of s coupled linear PH-DAE systems as follows: consider s PH-DAE subsystems

$$\frac{d}{dt} E_i x_i(t) = (\tilde{J}_i - R_i)Q_i x_i(t) + B_i u_i(t), \quad y_i(t) = B_i^\top Q_i x_i(t),$$

$i = 1, \dots, s$, with $\tilde{J}_i = -\tilde{J}_i^\top$, $R_i = R_i^\top \geq 0$, and $Q_i^\top E_i = E_i^\top Q_i \geq 0$. The input u_i , the output y_i and B_i are split into

$$u_i(t) = \begin{pmatrix} \hat{u}_i(t) \\ \bar{u}_i(t) \end{pmatrix}, \quad y_i(t) = \begin{pmatrix} \hat{y}_i(t) \\ \bar{y}_i(t) \end{pmatrix}, \quad B_i = (\hat{B}_i \quad \bar{B}_i)$$

according to external and coupling quantities. The subsystems are coupled via external inputs and outputs by

$$\begin{pmatrix} \hat{u}_1 \\ \vdots \\ \hat{u}_k \end{pmatrix} + \hat{C} \begin{pmatrix} \hat{y}_1 \\ \vdots \\ \hat{y}_k \end{pmatrix} = 0, \quad \hat{C} = -\hat{C}^\top.$$

These s systems can be condensed to one large PH-DAE system [8]

$$\frac{d}{dt} E x = (J - R)Q x + \bar{B} \bar{u}, \tag{5a}$$

$$\bar{y} = \bar{B}^\top Q x \tag{5b}$$

with $J = \tilde{J} - \hat{B} \hat{C} \hat{B}^\top$ and the condensed quantities

$$v^\top = (v_1^\top, \dots, v_s^\top) \quad \text{for } v \in \{x, \bar{u}, \bar{y}\},$$

$$F = \text{diag}(F_1, \dots, F_s) \quad \text{for } F \in \{E, Q, \tilde{J}, R, \hat{B}, \bar{B}\}.$$

Equation (5) defines now a PH-DAE system of type (2) with structure given by (3) and (4): the matrices \tilde{J} and R are block-diagonal, and the Schur complement type matrix $-\hat{B} \hat{C} \hat{B}^\top$ has only off-block diagonal entries. Note that the coupling has been shifted from the port matrices B_i to the off-block diagonal part of J . □

Now we collect some properties of systems (2) with properties as in Assumption 5. To this end, we note that a matrix pencil $sE - A \in \mathbb{R}[s]^{n \times n}$ is called *regular*, if $\det(sE - A)$ is not the zero polynomial. Furthermore, for a regular pencil $sE - A$, the *index* $\nu \in \mathbb{N}_0$ of the DAE $\frac{d}{dt}Ex(t) = Ax(t) + f(t)$ is the smallest number for which the mapping $\lambda \mapsto \lambda^{1-\nu}(\nu E - A)^{-1}$ is bounded outside a compact subset of \mathbb{C} . Note that the index equals to the number of differentiations of the DAE needed to obtain an ordinary differential equation [17, Chap. 2].

Proposition 8. *Any system (2) fulfilling Assumption 5 has the following properties.*

- (a) *The pencil $sE - (J - R)Q \in \mathbb{R}[s]^{n \times n}$ is regular.*
- (b) *There exists a unique solution x of (2).*
- (c) *The index of the DAE (2) is at most two.*

Proof.

- (a) For $\lambda \in \mathbb{C}$ with $\operatorname{Re} \lambda > 0$, we show that $C := \lambda E - (J - R)Q$ has a trivial kernel. Let $z \in \mathbb{C}^n$ with $Cz = 0$. Then

$$0 = \operatorname{Re}(z^*Q^\top Cz) = \operatorname{Re}(\lambda z^*Q^\top Ez) - \operatorname{Re}(z^*Q^\top JQz) + \operatorname{Re}(z^*Q^\top RQz).$$

Invoking that $J = -J^\top$, $Q^\top E = E^\top Q \geq 0$ and $R = R^\top \geq 0$, we obtain

$$\begin{aligned} \operatorname{Re}(\lambda z^*Q^\top Ez) &= \operatorname{Re}(\lambda)z^*Q^\top Ez \geq 0, \\ \operatorname{Re}(z^*Q^\top JQz) &= \operatorname{Re}((Qz)^*J(Qz)) = 0, \\ \operatorname{Re}(z^*Q^\top RQz) &= \operatorname{Re}((Qz)^*R(Qz)) = (Qz)^*R(Qz) \geq 0, \end{aligned}$$

which leads to $z^*Q^\top Ez = 0$ and $(Qz)^*R(Qz) = 0$. The positive semi-definiteness of $Q^\top E$ and R implies that $E^\top Qz = Q^\top Ez = 0$ and $RQz = 0$. Using $(\lambda E - (J - R)Q)z = 0$, this yields $JQz = 0$. Hence, by $R = R^\top$ and $J = -J^\top$,

$$Qz \in \ker [E \quad R \quad J]^\top.$$

Assumption 5 (b) now gives $Qz = 0$. Since Q is invertible, we are led to $z = 0$.

- (b) By using that the pencil $sE - (J - R)Q$ is regular, uniqueness of solutions of the initial value problem (2) follows from the considerations in [18, Sec. 1.1].

It remains to prove that a solution of (2) exists. Let $Z \in \mathbb{R}^{n \times r}$, $Z_1 \in \mathbb{R}^{r \times r_1}$ be as in Assumption 5 (c). Furthermore, let $Z' \in \mathbb{R}^{n \times (n-r)}$, $Z'_1 \in \mathbb{R}^{r \times (r-r_1)}$ be matrices with $\operatorname{im} Z' = (\operatorname{im} Z)^\perp$ and $\operatorname{im} Z'_1 = (\operatorname{im} Z_1)^\perp$. Moreover, we introduce matrices $Z_2 \in \mathbb{R}^{(n-r) \times r_1}$, $Z'_2 \in \mathbb{R}^{(n-r) \times (n-r-r_1)}$ with full column rank and

$$\operatorname{im} Z_2 = \ker Z_1^\top Z'^\top Q^\top (J - R)Z', \quad \operatorname{im} Z'_2 = (\operatorname{im} Z_2)^\perp.$$

The construction of $Z, Z', Z_1, Z'_1, Z_2, Z'_2$ yields that the columns of the matrix

$$V := [Z'_2, Z'_1, Z_2, Z_1] \tag{6}$$

are linearly independent, and thus, $V, V^\top Q^\top \in \mathbb{R}^{n \times n}$ are invertible matrices. Then we obtain

$$V^\top Q^\top (sE - (J - R)Q)V = \begin{bmatrix} sE_{11} - A_{11} & sE_{12} - A_{12} & -A_{13} & -A_{14} \\ sE_{12}^\top - A_{21} & sE_{22} - A_{22} & -A_{23} & 0 \\ -A_{31} & -A_{32} & -A_{33} & 0 \\ A_{14}^\top & 0 & 0 & 0 \end{bmatrix}, \quad (7)$$

where

$$\begin{aligned} E_{11} &= (Z'_2)^\top (Z')^\top Q^\top E Z' Z'_2, & E_{12} &= (Z'_2)^\top (Z')^\top Q^\top E Z' Z_2, \\ E_{22} &= Z_2^\top (Z')^\top Q^\top E Z' Z_2, & A_{11} &= (Z'_2)^\top (Z')^\top Q^\top (J - R)Q Z' Z'_2, \\ A_{12} &= (Z'_2)^\top (Z')^\top Q^\top (J - R)Q Z' Z_2, & A_{21} &= Z_2^\top (Z')^\top Q^\top (J - R)Q Z' Z'_2, \\ A_{13} &= (Z'_2)^\top (Z')^\top Q^\top (J - R)Q Z Z'_1, & A_{31} &= (Z_1)^\top Z^\top Q^\top (J - R)Q Z' Z'_2, \\ A_{22} &= Z_2^\top (Z')^\top Q^\top (J - R)Q Z' Z_2, & A_{33} &= (Z_1)^\top Z^\top Q^\top (J - R)Q Z Z'_1, \\ A_{14} &= (Z'_2)^\top (Z')^\top Q^\top J Q Z Z_1, & & \\ B_1 &= (Z'_2)^\top (Z')^\top Q^\top B, & B_2 &= Z_2^\top (Z')^\top Q^\top B, \\ B_3 &= (Z'_1)^\top Z^\top Q^\top B, & B_4 &= Z_1^\top Z^\top Q^\top B. \end{aligned}$$

The construction of the matrices $Z, Z', Z_1, Z'_1, Z_2, Z'_2$ yields that

- $\begin{bmatrix} E_{11} & E_{12} \\ E_{12}^\top & E_{22} \end{bmatrix}$ is positive definite. In particular, E_{22} is invertible,
- A_{33} is invertible, and
- A_{14} has full row rank.

The already proved regularity of $sE - (J - R)Q$, which implies regularity of the pencil $V^\top Q^\top (sE - (J - R)Q)QV$, which yields that A_{14} has moreover full column rank. As a consequence, A_{14} is square (i.e., $2r_1 = n - r$) and invertible.

Set $z_0 = (z_{10}^\top, z_{20}^\top, z_{30}^\top, z_{40}^\top)$, $z_{10} \in \mathbb{R}^{n-r-r_1}$, $z_{20} \in \mathbb{R}^{r_1}$, $z_{30} \in \mathbb{R}^{r-r_1}$, $z_{40} \in \mathbb{R}^{r_1}$. By Assumption 5 (c), we have $B_4 u \in H^1([0, T]; \mathbb{R}^{r_1})$ and

$$\begin{aligned} 0 &= Z_1^\top Z^\top Q^\top (JQx_0 + Bu(0)) = Z_1^\top Z^\top Q^\top JQx_0 + B_4 u(0) \\ &= Z_1^\top Z^\top Q^\top JQ(Z'Z'_2 z_{10} + Z'Z_2 z_{20} + ZZ'_1 z_{30} + ZZ_1 z_{40}) + B_4 u(0) \\ &= Z_1^\top Z^\top Q^\top JQZ'Z'_2 z_{10} + B_4 u(0) = -Z_1^\top Z^\top Q^\top J^\top QZ'Z'_2 z_{10} + B_4 u(0) \\ &= -A_{14}^\top z_{10} + B_4 u(0). \end{aligned}$$

Consequently, $z_1 = (A_{14}^\top)^{-1} B_4 u$ fulfills $z_1 \in H^1([0, T]; \mathbb{R}^r)$, $-A_{14}^\top z_1 + B_4 u(t) = 0$ and $z_1(0) = z_{10}$. Moreover, let $z_2 \in H^1([0, T]; \mathbb{R}^{r_1})$ be the solution of the following ODE with initial value $z_2(0) = z_{20}$

$$\begin{aligned} \frac{d}{dt} z_2(t) &= E_{22}^{-1} (A_{22} - A_{23} A_{33}^{-1} A_{32}) z_2(t) \\ &\quad + E_{22}^{-1} \left(-\frac{d}{dt} E_{12}^\top z_1(t) + A_{21} z_1(t) + B_2 u(t) - A_{23} A_{33}^{-1} z_1(t) - A_{23} A_{33}^{-1} B_3 u(t) \right), \end{aligned}$$

and we successively define $z_3 \in L^2([0, T]; \mathbb{R}^{r-r_1})$, $z_4 \in L^2([0, T]; \mathbb{R}^{r_1})$ by

$$\begin{aligned} z_3(t) &= -A_{33}^{-1}A_{23}z_2(t) - A_{33}^{-1}A_{13}z_1(t), \\ z_4(t) &= -A_{14}^{-1}\left(\frac{d}{dt}E_{11}z_1(t) + \frac{d}{dt}E_{12}z_2(t) - A_{11}z_1(t) - A_{12}z_2(t) - A_{13}z_3(t)\right). \end{aligned}$$

Altogether, we have that $z := (z_1^\top, z_2^\top, z_3^\top, z_4^\top)^\top$ is a solution of the differential-algebraic equation

$$\begin{aligned} \frac{d}{dt} \begin{bmatrix} E_{11} & E_{12} & 0 & 0 \\ E_{12}^\top & E_{22} & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix} \begin{pmatrix} z_1(t) \\ z_2(t) \\ z_3(t) \\ z_4(t) \end{pmatrix} &= \begin{bmatrix} A_{11} & A_{12} & A_{13} & A_{14} \\ A_{21} & A_{22} & A_{23} & 0 \\ A_{31} & A_{32} & A_{33} & 0 \\ -A_{14}^\top & 0 & 0 & 0 \end{bmatrix} \begin{pmatrix} z_1(t) \\ z_2(t) \\ z_3(t) \\ z_4(t) \end{pmatrix} + \begin{bmatrix} B_1 \\ B_2 \\ B_3 \\ B_4 \end{bmatrix} u(t), \\ \begin{bmatrix} E_{11} & E_{12} & 0 & 0 \\ E_{12}^\top & E_{22} & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix} \begin{pmatrix} z_1(0) \\ z_2(0) \\ z_3(0) \\ z_4(0) \end{pmatrix} &= \begin{bmatrix} E_{11} & E_{12} & 0 & 0 \\ E_{12}^\top & E_{22} & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix} \begin{pmatrix} z_{10} \\ z_{20} \\ z_{30} \\ z_{40} \end{pmatrix}. \end{aligned} \quad (8)$$

Now setting

$$x(t) := (Q^\top)^{-1}(V^\top)^{-1}z(t),$$

we obtain from (7) and (8) that x is a solution of (2).

- (c) The result has been shown in [22, Thm. 4.3] and [12, Thm. 6.6]. Notice, this can be also seen from the proof of (b). \square

Remark 9. Assume that the DAE (2) fulfills Assumption 5(a) & (b). By using $V \in \mathbb{R}^{n \times n}$ as defined as in (6), we can transform (2) to an equivalent DAE (8). Consequently, the existence of a solution of (2) implies $z_1 \in H^1([0, T]; \mathbb{R}^{r_1})$ with, and thus $B_4u = (A_{14}^\top)^{-1} \in H^1([0, T]; \mathbb{R}^{r_1})$. Invoking that $B_4 = Z_1^\top Z^\top Q^\top B$, we obtain that $Z_1^\top Z^\top Q^\top Bu \in H^1([0, T]; \mathbb{R}^{r_1})$ with $Z_1^\top Z^\top Q^\top (JQx_0 + Bu(0)) = 0$ has to be fulfilled. Consequently, under Assumption 5(a) & (b), the conditions in Assumption 5(c) are also necessary for the existence of a solution of the DAE (2). \square

2.2 Perspective as coupled PH-subsystems

We take the perspective of the paper [14] for the system (2) and its partitioning given in Rem. 6. To this end, we need to introduce the internal inputs u_{ij} , i.e., data stemming from the j th system being input for the i th system, and outputs y_{ij} (i.e., data from the i system to be transferred to the j th system). This read for the i th subsystems ($i = 1, \dots, s$):

$$\begin{aligned} \frac{d}{dt}E_i x_i(t) &= (J_i - R_i)Q_i x_i(t) + \sum_{\substack{j=1 \\ j \neq i}}^s B_{ij}u_{ij}(t) + B_i u_i(t), & E_i x_i(0) &= E x_{i0}, \\ y_{ij}(t) &= B_{ij}^\top Q_i x_i(t), & j &= 1, \dots, s, j \neq i, \\ y_i(t) &= B_i^\top Q_i x_i(t) \end{aligned}$$

with matrices $E_i, Q_i, J_i, R_i \in \mathbb{R}^{n_i \times n_i}$, and $B_i \in \mathbb{R}^{n_i \times m}$ fulfilling the properties of Assumption 5 (a), and $B_{ij} \in \mathbb{R}^{n_i \times m_{ij}}$ for $i = 1, \dots, s$, $j = 1, \dots, s$, $i \neq j$ with $m_{ij} = m_{ji}$. The dissipation inequality for this subsystem reads

$$\begin{aligned} & \frac{1}{2}(x_i(t)^\top Q_i^\top E_i x_i(t)) - \frac{1}{2}(x_i(0)^\top Q_i^\top E_i x_i(0)) \\ & \leq \int_0^t u_i(\tau)^\top y_i(\tau) d\tau + \sum_{\substack{j=1 \\ j \neq i}}^s \int_0^t u_{ij}(\tau)^\top y_{ij}(\tau) d\tau \quad \forall t \in [0, T] \end{aligned}$$

The overall input is $u = u_1 = \dots = u_s$, whereas the overall output is given by the sum

$$y = \sum_{j=1}^s y_j.$$

Coupling is done such that $x \mapsto x^\top Q^\top E x$ with E and Q as in (3) is a storage function for the overall system [11]. This is for instance achieved by

$$\begin{aligned} \forall i = 1, \dots, s : u_{ij} + y_{ji} &= 0, & j = 1, \dots, i-1, \\ u_{ji} - y_{ij} &= 0, & j = i+1, \dots, s, \end{aligned}$$

since

$$\begin{aligned} & \frac{1}{2}(x(t)^\top Q^\top E x(t)) - \frac{1}{2}(x(0)^\top Q^\top E x(0)) \\ &= \sum_{i=1}^s \frac{1}{2} \left((x_i(t)^\top Q_i^\top E_i x_i(t)) - \frac{1}{2}(x_i(0)^\top Q_i^\top E_i x_i(0)) \right) \\ &\leq \sum_{i=1}^s \int_0^t u_i(\tau)^\top y_i(\tau) d\tau + \sum_{i=1}^s \sum_{\substack{j=1 \\ j \neq i}}^s \int_0^t u_{ij}(\tau)^\top y_{ij}(\tau) d\tau \\ &= \int_0^t u(\tau)^\top \sum_{i=1}^s y_i(\tau) d\tau + \sum_{i=1}^s \sum_{j=1}^{i-1} \int_0^t u_{ij}(\tau)^\top y_{ij}(\tau) d\tau + \sum_{i=1}^s \sum_{j=i+1}^s \int_0^t u_{ij}(\tau)^\top y_{ij}(\tau) d\tau \\ &= \int_0^t u(\tau)^\top y(\tau) d\tau + \sum_{i=1}^s \sum_{j=1}^{i-1} \int_0^t -y_{ji}(\tau)^\top u_{ji}(\tau) d\tau + \sum_{i=1}^s \sum_{j=i+1}^s \int_0^t u_{ij}(\tau)^\top y_{ij}(\tau) d\tau \\ &= \int_0^t u(\tau)^\top y(\tau) d\tau. \end{aligned}$$

The overall system is given by (2) with E, Q and R as in (3), and J structured as in (4) with

$$\forall i = 1, \dots, s-1, j = i+1, \dots, s : J_{ij} = B_{ij} B_{ji}^\top.$$

Remark 10. *This coupling has the drawback that all variables enter the definition of the coupling. And we have as many outputs of a subsystem as the other subsystem has variables times the number of other subsystems. This will be treated differently in practice. A 'sparse' coupling has to be introduced.*

Before we investigate the Lions/Mercier based algorithm, we revisit the Jacobi dynamic iteration and discuss some limitations.

3 Failure of Jacobi dynamic iteration

To motivate the development of monotone operator splitting based dynamic iteration schemes in chapter 5, we remind that classical approaches such as the Jacobi or Gauss-Seidel iteration scheme may not always be feasible for a computer implementation. To this end, we address system (2) in the following ODE setting: assigning $E = Q = I$, the initial value problem (2) reads

$$\dot{x} = (J - R)x + Bu(t), \quad x(0) = x_0, \quad t \in [0, T]. \quad (9)$$

For this system, we recall that the dynamic iteration is based on a splitting $J - R = M - N$ and an iteration count $k \in \mathbb{N}_0$. Now, let be an initial guess $k = 0$ be given $x^{(0)} \in C^0([0, T], \mathbb{R}^n)$ with $x^{(0)}(0) = x_0$ (e.g., $x^{(0)}(t) = x_0$) for all $t \in [0, T]$, the dynamic iteration scheme reads:

$$\dot{x}^{(k+1)} = Mx^{(k+1)} - Nx^{(k)} + Bu(t), \quad x^{(k+1)}(0) = x_0. \quad (10)$$

Remark 11. Note that setting $M = J_d - R$ and $N = -J_o$ in the case of the pHS-ODE system (9) defines a block-Jacobi dynamic iteration scheme. \square

If we restrict to $u \in C^0([0, T], \mathbb{R}^m)$, we obtain from (10) $x^{(k+1)} \in C^0([0, T], \mathbb{R}^n)$. Let $x \in C^0([0, T], \mathbb{R}^n)$ denote the analytic solution of (9). Then, the recursion error is given by $\epsilon^{(k)} := x^{(k)} - x$. Following Burrage [10], we can derive an exact error recursion for the dynamic iteration (10). Doing this, for the system (9) with

$$R = \text{diag}(\tau, \dots, \tau), \quad B = 0, \quad (11)$$

and setting $M = -R, N = -J_o = -J$, we get the error recursion on $t \in [0, T]$:

$$\begin{aligned} \epsilon^{(k)}(t) &= \int_0^t e^{-(t-s_{k-1})R} J \epsilon^{(k-1)}(s_{k-1}) ds_{k-1} = J \int_0^t e^{-\tau(t-s_{k-1})} \epsilon^{(k-1)}(s_{k-1}) ds_{k-1} \\ &= J^k \int_0^t e^{-\tau(t-s_{k-1})} \int_0^{s_{k-1}} e^{-\tau(s_{k-1}-s_{k-2})} \dots \int_0^{s_1} e^{-\tau(s_1-s_0)} \epsilon^{(0)}(s_0) ds_0 \dots ds_{k-2} ds_{k-1} \\ &= e^{-\tau t} J^k \int_0^t \int_0^{s_{k-1}} \dots \int_0^{s_1} e^{\tau s_0} \epsilon^{(0)}(s_0) ds_0 \dots ds_{k-2} ds_{k-1}. \end{aligned}$$

Now, just for demonstration purposes and simplicity, let us assume that initial error has the format:

$$\epsilon^{(0)}(s_0) = D s_0 e^{-\tau s_0} \mathbb{1} \quad \text{with } \mathbb{1} = [1, 1]^\top$$

and $D > 0$. Using the maximum norm $\|f\|_T := \max_{t \in [0, T]} \|f(t)\|_2$ for $f \in C^0([0, T], \mathbb{R}^n)$, the error reads for all $k \geq \tau T - 1$ (maximal error at T):

$$\|\epsilon^{(k)}\|_T = \sqrt{2} D \|J\|_2^k \frac{e^{-\tau T} T^{k+1}}{(k+1)!} \Rightarrow \frac{\|\epsilon^{(k+1)}\|_T}{\|\epsilon^{(k)}\|_T} = \frac{\|J\|_2 \cdot T}{k+2}.$$

Example 12. We analyse a 2×2 version of (9) with the restriction (11), which reads:

$$x' = (J - R)x, \quad x(0) = x_0 = \begin{bmatrix} 2 \\ 2 \end{bmatrix}, \quad \text{with } J = \begin{bmatrix} 0 & \nu \\ -\nu & 0 \end{bmatrix}, \quad R = \begin{bmatrix} \tau & 0 \\ 0 & \tau \end{bmatrix} \quad (12)$$




Figure 1: Jacobi iteration for system (12) with $\nu = 15$, $\tau = 0.01$, $D = 1$. Left: $T = 10$. The maximum error would be obtained at iteration $k = 148$: $\sqrt{2} \cdot 150^{148}/148!$ and error decrease from $k = 149$ on. Overflow in single precision at $k = 40$. Right: $T = 0.5$. Maximum error for $k = 5$ ($\nu T - 2 = 5.5$), then decrease. After $k = 29$, we achieve the solution (in single precision).

and employing $\tau, \nu > 0$. The analytic solution and error evolution are given by:

$$x(t) = e^{-\tau t} \begin{bmatrix} \cos(\nu t) & \sin(\nu t) \\ -\sin(\nu t) & \cos(\nu t) \end{bmatrix} x_0, \quad \frac{\|\epsilon^{(k+1)}\|_T}{\|\epsilon^{(k)}\|_T} = \frac{\nu T}{k+2} \quad \forall k \geq \tau T - 1.$$

The error amplification factor $\nu T/(k+2)$ is bounded by one for all $k > \nu T - 2$. For all $k < \nu T - 2$ the error is increasing. Hence, the convergence is monotone (for all k) only if $\nu T - 2 \leq 0$. We give results for both cases:

- (a) For $\nu T > 2$, we obtain a decrease of the error only if k is large enough. On the other hand, we may trigger overflows if νT is large enough, see Fig. 1, left.
- (b) If $\nu T \leq 2$, we have monotone convergence. Hence windowing is always a solution to obtain (good) convergence.

An example for $T = 0.5$ is shown in Fig. 1, right. Thus using Jacobi with windows, we can obtain convergences. Note that the behavior in the window $[0, 0.5]$ yields a kind of worst case for the convergence. \square

4 Recap on maximal monotone operators

For $\omega \geq 0$, we introduce the weighted L^2 -space

$$L_\omega^2([0, T], \mathbb{R}^n) := \{f : [0, T] \rightarrow \mathbb{R}^n \mid t \mapsto e^{-t\omega} f(t) \in L^2([0, T], \mathbb{R}^n)\}$$

equipped with the norm $\|\cdot\|_{2,\omega}$ defined as

$$\|f\|_{2,\omega}^2 = \int_0^T e^{-2t\omega} \|f(t)\|^2 dt.$$

Clearly, as $T \in (0, \infty)$, we have $L_\omega^2([0, T], \mathbb{R}^n) = L^2([0, T], \mathbb{R}^n)$ with equivalent norms. Furthermore, if $\omega = 0$, then the norms in $L_\omega^2([0, T], \mathbb{R}^n)$ and $L^2([0, T], \mathbb{R}^n)$ coincide, i.e.,

$$\forall f \in L^2([0, T], \mathbb{R}^n) : \quad \|f\|_{2,0} = \|f\|_2 = \left(\int_0^T \|f(t)\|^2 dt \right)^{1/2}.$$

Definition 13 (Contraction). *Let X be a Banach space with norm $\|\cdot\|$. A (possibly nonlinear) operator $A : D(A) \subset X \rightarrow X$ is called contractive, if*

$$\|Ax - Ay\| \leq \|x - y\|, \quad \forall x, y \in X,$$

and strictly contractive, if there exists some $L < 1$, such that

$$\|Ax - Ay\| \leq L \|x - y\|, \quad \forall x, y \in X. \quad \square$$

Definition 14 (Maximally monotone operator). *Let X be a real Hilbert space with inner product $\langle \cdot, \cdot \rangle$. A set $Y \subset X \times X$ is called monotone, if*

$$\langle x - u, y - v \rangle \geq 0, \quad (x, y), (u, v) \in Y.$$

Further, $Y \subset X \times X$ is called maximally monotone, if it is monotone and not a proper subset of a monotone subset of $X \times X$.

A (possibly nonlinear) operator $A : D(A) \subset X \rightarrow X$ is called (maximally) monotone, if the graph of A , i.e., $\{(x, Ax) : x \in D(A)\}$, is (maximally) monotone. \square

Remark 15. *Let $A : D(A) \subset X \rightarrow X$ be a monotone operator. It follows from the definition of monotonicity that $I + \lambda A$ is injective for all $\lambda > 0$.*

Moreover, by [5, Theorem 2.2], the following three statements are equivalent:

- (i) A is maximally monotone,
- (ii) $I + \lambda A$ is surjective for some $\lambda > 0$,
- (iii) $I + \lambda A$ is surjective for all $\lambda > 0$.

Consequently, if A is maximally monotone, then $I + \lambda A$ is bijective for all $\lambda > 0$. The Cauchy-Schwarz inequality yields that

$$\|(I + \lambda A)x - (I + \lambda A)y\| \geq \|x - y\| \quad \forall x, y \in D(A),$$

whence $(I + \lambda A)^{-1} : X \rightarrow X$ is contractive.

Furthermore, $(I - \lambda A)(I + \lambda A)^{-1}$ is contractive. This follows with $\tilde{x} := (I + \lambda A)^{-1}x$ and $\tilde{y} := (I + \lambda A)^{-1}y$ from

$$\begin{aligned} \|x - y\|^2 - \|(I - \lambda A)(I + \lambda A)^{-1}x - (I - \lambda A)(I + \lambda A)^{-1}y\|^2 \\ = \|\tilde{x} - \tilde{y} + \lambda A\tilde{x} - \lambda A\tilde{y}\|^2 - \|\tilde{x} - \tilde{y} - (\lambda A\tilde{x} - \lambda A\tilde{y})\|^2 \\ = 4\lambda \langle \tilde{x} - \tilde{y}, A\tilde{x} - A\tilde{y} \rangle \geq 0. \end{aligned} \quad \square$$

5 Dynamic iteration scheme

Now we develop a dynamic iteration scheme for the DAE (2) fulfilling Assumption 5. To facilitate the decoupling, we split J as follows

$$J = \underbrace{\begin{bmatrix} J_1 & 0 & \cdots & 0 \\ 0 & \ddots & \ddots & \vdots \\ \vdots & \ddots & \ddots & 0 \\ 0 & \cdots & 0 & J_s \end{bmatrix}}_{=:J_d} + \underbrace{\begin{bmatrix} 0 & J_{12} & \cdots & J_{1s} \\ -J_{12}^\top & \ddots & \ddots & \vdots \\ \vdots & \ddots & \ddots & J_{s-1,s} \\ -J_{1s}^\top & \cdots & -J_{s-1,s}^\top & 0 \end{bmatrix}}_{=:J_o}. \quad (13)$$

such that $J_d = -J_d^\top$ and $J_o = -J_o^\top$ (compare with Rem. 6 c).

Let $\alpha \in [0, 1]$, $\mu, \omega \in \mathbb{R}$ with $0 \leq \mu \leq \omega$. We introduce the affine-linear operator M by:

$$M: D(M) \subset L_\omega^2([0, T], \mathbb{R}^n) \rightarrow L_\omega^2([0, T], \mathbb{R}^n), \quad (14a)$$

$$x \mapsto \frac{d}{dt}(Ex) - (J_d - \alpha R + \mu EQ^{-1})Qx - Bu \quad (14b)$$

with domain

$$D(M) = \{x \in L_\omega^2([0, T], \mathbb{R}^n) \mid Ex \in H^1([0, T], \mathbb{R}^n), Ex(0) = Ex_0\}, \quad (14c)$$

and the linear bounded multiplication operator N by

$$N: L_\omega^2([0, T], \mathbb{R}^n) \rightarrow L_\omega^2([0, T], \mathbb{R}^n), \quad (15a)$$

$$x \mapsto ((1 - \alpha)R + \mu EQ^{-1} - J_o)Qx. \quad (15b)$$

Remark 16. Notice that x is a solution of the DAE (2) if, and only if,

$$Mx + Nx = 0 \quad (16)$$

holds. □

Lemma 17. Let $\omega, \mu \in \mathbb{R}$ with $0 \leq \mu \leq \omega$, and let $\alpha \in [0, 1]$. Assume that the DAE (2) fulfills Assumption 5, and let the operator M be defined as in (14). Then MQ^{-1} is maximally monotone on $L_\omega^2([0, T], \mathbb{R}^n)$. More precisely, MQ^{-1} satisfies

$$\begin{aligned} & \langle MQ^{-1}v - MQ^{-1}w, v - w \rangle_{2,\omega} \\ &= \frac{1}{2}e^{-2T\omega} \left(\|(EQ^{-1})^{1/2}(v(T) - w(T))\|^2 \right) \\ & \quad (\omega - \mu)\|(EQ^{-1})^{1/2}(v - w)\|_{2,\omega}^2 + \alpha\|R^{1/2}(v - w)\|_{2,\omega}^2 \geq 0 \end{aligned}$$

for $v, w \in QD(M)$, and $I + \lambda MQ^{-1}$ is surjective for every $\lambda > 0$.

Proof. First of all, we have for $v, w \in QD(M)$

$$\begin{aligned}
& \langle MQ^{-1}v - MQ^{-1}w, v - w \rangle_{2,\omega} \\
&= \langle \frac{d}{dt}EQ^{-1}(v - w), v - w \rangle_{2,\omega} - \langle (J_d - \alpha R + \mu EQ^{-1})(v - w), v - w \rangle_{2,\omega} \\
&= \langle \frac{d}{dt}EQ^{-1}(v - w), v - w \rangle_{2,\omega} - \mu \langle EQ^{-1}(v - w), v - w \rangle_{2,\omega} + \langle \alpha R(v - w), v - w \rangle_{2,\omega} \\
&= \frac{1}{2}e^{-2T\omega} \left(\|(EQ^{-1})^{1/2}(v(T) - w(T))\|^2 \right) \\
&\quad + (\omega - \mu) \|(EQ^{-1})^{1/2}(v - w)\|_{2,\omega}^2 + \langle \alpha R(v - w), v - w \rangle_{2,\omega} \geq 0,
\end{aligned}$$

which shows that MQ^{-1} is monotone.

To prove that MQ^{-1} is maximally monotone, it suffices, by Remark 15, to prove that $I + \lambda MQ^{-1}$ is surjective for some $\lambda > 0$. Assume that $y \in L_\omega^2([0, T], \mathbb{R}^n)$. Consider the matrices $\tilde{E} = EQ^{-1}$, $\tilde{R} = \alpha R + \frac{1}{\lambda}I$ and $\tilde{Q} = I$. Then the DAE

$$\frac{d}{dt}\tilde{E}\tilde{v}(t) = (J_d - \tilde{R})\tilde{Q}\tilde{v}(t) + Be^{-\mu t}u(t) - \frac{1}{\lambda}e^{-\mu t}y(t), \quad \tilde{E}\tilde{v}(0) = \tilde{E}Qx_0, \quad (17)$$

This DAE clearly fulfills Assumption 5 (a)&(b). Moreover, by positive definiteness of \tilde{R} , we obtain that any matrix $Z \in \mathbb{R}^{n \times r}$ with full column rank and $\text{im } Z = \ker E$ fulfills $\ker \tilde{R}QZ = \{0\}$. This means that Assumption 5 (c) is trivially fulfilled by (17), and Proposition 8 implies that (17) has a unique solution $\tilde{v} \in L_\omega^2([0, T], \mathbb{R}^n)$ with $\tilde{E}\tilde{v} \in H^1([0, T], \mathbb{R}^n)$. Now consider $v \in L_\omega^2([0, T], \mathbb{R}^n)$ with $v(t) = e^{\mu t}\tilde{v}(t)$. Then $\tilde{E}v(0) = \tilde{E}\tilde{v}(0) = \tilde{E}Qx_0$, and the product rule for weak derivatives [2, Thm. 4.25] yields $\tilde{E}v \in H^1([0, T], \mathbb{R}^n)$ with

$$\begin{aligned}
\frac{d}{dt}\tilde{E}v &= \frac{d}{dt}e^{\mu t}\tilde{E}\tilde{v} \\
&= e^{\mu t}\frac{d}{dt}\tilde{E}\tilde{v} + \mu e^{\mu t}\tilde{E}\tilde{v} \\
&= e^{\mu t}(J_d - \tilde{R})\tilde{Q}\tilde{v} + e^{\mu t}Be^{-\mu t}u(t) - e^{\mu t}\frac{1}{\lambda}e^{-\mu t}y(t) + \mu e^{\mu t}\tilde{E}\tilde{v} \\
&= (J_d - \tilde{R})\tilde{Q}v + Bu(t) - \frac{1}{\lambda}y(t) + \mu\tilde{E}v,
\end{aligned}$$

and thus

$$v + \lambda \left(\frac{d}{dt}EQ^{-1}v - (J_d - \alpha R + \mu EQ^{-1})QQ^{-1}v + Bu \right) = y.$$

Since this means that $(I + \lambda MQ^{-1})v = y$, the result is shown. \square

Lemma 18. *Let $\lambda > 0$, $\mu \geq 0$, $\alpha \in [0, 1]$, and let $R, E, Q \in \mathbb{R}^{n \times n}$ with the properties as in Assumption 5. Then, for $K := ((1 - \alpha)R + \mu EQ^{-1} - J_o)$*

$$\begin{aligned}
& \|(I - \lambda K)(I + \lambda K)^{-1}x\|^2 - \|x\|^2 \\
&= -4\lambda \|((1 - \alpha)R + \mu EQ^{-1})^{1/2}(I + \lambda K)^{-1}x\|^2, \quad \forall x \in \mathbb{R}^n. \quad (18)
\end{aligned}$$

Moreover, if

$$\text{rk} [\mu E \quad (1 - \alpha)R] = n, \quad (19)$$

then $(1 - \alpha)R + \mu EQ^{-1} = K + J_o \in \mathbb{R}^{n \times n}$ is invertible, and

$$\|(I - \lambda K)(I + \lambda K)^{-1}x\| \leq q \|x\| \quad \forall x \in \mathbb{R}^n, \quad (20)$$

where $q \geq 0$ with

$$q^2 = 1 - \frac{4\lambda}{(1 + \lambda \|K\|)^2 \cdot \|(K + J_o)^{-1}\|} < 1. \quad (21)$$

Proof. By using that $K + K^\top \geq 0$, we see that $I + \lambda K$ is an invertible matrix. Let $x \in \mathbb{R}^n$ and $y := (I + \lambda K)^{-1}x$. Then

$$\begin{aligned} \|x\|^2 - \|(I - \lambda K)(I + \lambda K)^{-1}x\|^2 &= \|y + \lambda Ky\|^2 - \|y - \lambda Ky\|^2 = 4\lambda \langle y, (K + K^\top)y \rangle \\ &= 4\lambda \langle y, ((1 - \alpha)R + \mu EQ^{-1})y \rangle \end{aligned}$$

shows (18). To prove the remaining result, assume that (19) is fulfilled. Then it can be concluded from Assumption 5 (a) (i) that $(1 - \alpha)R + \mu EQ^{-1}$ is positive definite. Furthermore, by

$$\|x\| = \|(I + \lambda K)y\| \leq (1 + \lambda \|K\|)\|y\| = (1 + \lambda \|K\|)\|(I + \lambda K)^{-1}x\|,$$

we have

$$\|(I + \lambda K)^{-1}x\| \geq \frac{1}{1 + \lambda \|K\|} \|x\| \quad \forall x \in \mathbb{R}^n.$$

Plugging this into (18), we obtain for all $x \in \mathbb{R}^n$

$$\begin{aligned} \|(I - \lambda K)(I + \lambda K)^{-1}x\|^2 &= \|x\|^2 - 4\lambda \|((1 - \alpha)R + \mu EQ^{-1})^{1/2}(I + \lambda K)^{-1}x\|^2 \\ &\leq \|x\|^2 - 4\lambda \|((1 - \alpha)R + \mu EQ^{-1})^{-1}\|^{-1} \|(I + \lambda K)^{-1}x\|^2 \\ &\leq \|x\|^2 - 4\lambda \|((1 - \alpha)R + \mu EQ^{-1})^{-1}\|^{-1} \frac{1}{(1 + \lambda \|K\|)^2} \|x\|^2, \\ &= \left(1 - \frac{4\lambda}{\|((1 - \alpha)R + \mu EQ^{-1})^{-1}\| \cdot (1 + \lambda \|K\|)^2}\right) \|x\|^2, \end{aligned}$$

which completes the proof. \square

Remark 19. Condition (19) is equivalent to at least one of the following three statements being fulfilled:

- (i) $\text{rk} \begin{bmatrix} E & R \end{bmatrix} = n$, $\mu > 0$ and $\alpha < 1$,
- (ii) $\text{rk} E = n$ and $\mu > 0$, or
- (iii) $\text{rk} R = n$ and $\alpha < 1$

\square .

As a direct conclusion of Lemma 18, we can draw the following result.

Lemma 20. Let $\lambda, \mu > 0$, $\alpha \in [0, 1]$, let $R, E, Q \in \mathbb{R}^{n \times n}$ with the properties as in Assumption 5, and let the operator N be defined as in (15). The multiplication operator NQ^{-1} on $L_\omega^2([0, T], \mathbb{R}^n)$ is linear, bounded and satisfies

$$\langle x, NQ^{-1}x \rangle_{2,\omega} \leq 0,$$

i.e., NQ^{-1} is maximally monotone. Furthermore, the multiplication operator $x \mapsto (I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}x$ is a contraction on $L_\omega^2([0, T], \mathbb{R}^n)$ for $\lambda > 0$ satisfying

$$\|(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}x\|_{2,\omega} \leq \|x\|_{2,\omega} \quad \forall x \in L_\omega^2([0, T], \mathbb{R}^n).$$

Moreover, if $\text{im } E + \text{im } R = \mathbb{R}^n$ and $\alpha < 1$, then

$$\|(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}x\|_{2,\omega} \leq q\|x\|_{2,\omega} \quad \forall x \in L^2_\omega([0, T], \mathbb{R}^n).$$

for $q < 1$ as in (21).

Proof. The first statement follows directly and the remaining statements are implied by Lemma 18. \square

Our dynamic iteration scheme is built on Rem. 16. Following Lions and Mercier [19], we study the algorithms

$$x^{k+1} := Q^{-1}(I + \lambda MQ^{-1})^{-1}(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}(I - \lambda MQ^{-1})Qx^k. \quad (22)$$

with $x^0 \in D(M)$ arbitrary.

Remark 21. Note that equation (16) is equivalent to

$$(I + \lambda NQ^{-1})(I + \lambda MQ^{-1})Qx = (I - \lambda NQ^{-1})(I - \lambda MQ^{-1})Qx,$$

or equivalently,

$$x = Q^{-1}(I + \lambda MQ^{-1})^{-1}(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}(I - \lambda MQ^{-1})Qx. \quad \square$$

Remark 22. The iteration (22) is equivalent to

$$x^{k+1} := (Q + \lambda M)^{-1}(Q - \lambda N)(Q + \lambda N)^{-1}(Q - \lambda M)x^k. \quad (23)$$

Theorem 23. Let $\lambda > 0$, $\mu \geq 0$, and let $\alpha \in [0, 1]$. Assume that the DAE (2) fulfills Assumption 5, and let the operators M , N be defined as in (14) and (15). Let $\lambda > 0$ and $x^0 \in D(M)$. Let the sequence $(x^k)_k$ be defined by (22), and let x be the unique solution of (2). Then the following statements are fulfilled:

- (a) $(Ex^k)_k$ converges to Ex in $L^2([0, T], \mathbb{R}^n)$,
- (b) $(Ex^k)_k$ converges pointwise to Ex on $(0, T]$,
- (c) If $\alpha > 0$, then $(RQx^k)_k$ converges to RQx in $L^2([0, T], \mathbb{R}^n)$,
- (d) For the sequence $(z^k)_k$ given by

$$\forall k \in \mathbb{N}: \quad z^k := (I + \lambda MQ^{-1})Qx^k,$$

and the function $z := (I + \lambda MQ^{-1})Qx$, the real sequence $(\|z^k - z\|_{2,\omega})_k$ is monotonically decreasing, and

$$\forall k \in \mathbb{N}: \quad \|x^k - x\|_{2,\omega} \leq \|Q^{-1}\| \|z^k - z\|_{2,\omega}. \quad (24)$$

Proof. Let $\omega \in \mathbb{R}$ with $\mu < \omega$. We have

$$\begin{aligned} z^{k+1} &= (I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}(2I - (I + \lambda MQ^{-1}))(I + \lambda MQ^{-1})^{-1}z^k \\ &= (I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}[2Qx^k - z^k] \end{aligned} \quad (25)$$

and

$$z = (I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}(2Qx - z).$$

We set

$$\Delta x^k := x - x^k, \quad \Delta z^k := z - z^k.$$

Then using Lemma 20 and Lemma 17 we calculate

$$\begin{aligned} \|\Delta z^{k+1}\|_{2,\omega}^2 - \|\Delta z^k\|_{2,\omega}^2 &= \|z - z^{k+1}\|_{2,\omega}^2 - \|\Delta z^k\|_{2,\omega}^2 \\ &= \|(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}[(2Qx - z) - (2Qx^k - z^k)]\|_{2,\omega}^2 - \|\Delta z^k\|_{2,\omega}^2 \\ &\leq \|2Q\Delta x^k - \Delta z^k\|_{2,\omega}^2 - \|\Delta z^k\|_{2,\omega}^2 \\ &= 4\|Q\Delta x^k\|_{2,\omega}^2 - 4\langle Q\Delta x^k, \Delta z^k \rangle_{2,\omega} \\ &= 4\|Q\Delta x^k\|_{2,\omega}^2 - 4\langle Qx - Qx^k, (I + \lambda MQ^{-1})Qx - (I + \lambda MQ^{-1})Qx^k \rangle_{2,\omega} \\ &= -4\lambda\langle Qx - Qx^k, Mx - Mx^k \rangle_{2,\omega} \\ &= -2\lambda e^{-2T\omega} \|(EQ^{-1})^{1/2}Q\Delta x^k(T)\|^2 \\ &\quad - 4\lambda(\omega - \mu) \|(EQ^{-1})^{1/2}Q\Delta x^k\|_{2,\omega}^2 - 4\lambda\alpha \|R^{1/2}Q\Delta x^k\|_{2,\omega}^2. \end{aligned} \quad (26)$$

Thus the sequence $(\|\Delta z^k\|_{2,\omega})_k$ monotonically decreasing, and therefore it converges. Inequality (24) follows from Remark 15, which completes the proof of d. Furthermore, the latter inequality gives

$$\|(EQ^{-1})^{1/2}Q\Delta x^k\|_{2,\omega}^2 \leq \frac{1}{4\lambda(\omega - \lambda)} (\|\Delta z^k\|_{2,\omega}^2 - \|\Delta z^{k+1}\|_{2,\omega}^2), \quad (27)$$

$$\|R^{1/2}Q\Delta x^k\|_{2,\omega}^2 \leq \frac{1}{4\lambda\alpha} (\|\Delta z^k\|_{2,\omega}^2 - \|\Delta z^{k+1}\|_{2,\omega}^2). \quad (28)$$

Combining (28) with the fact that the norms $\|\cdot\|_{\omega,2}$ and $\|\cdot\|_2$ are equivalent, we are led to (c). Further, (27) together with $E = (EQ^{-1})^{1/2}(EQ^{-1})^{1/2}Q$ gives $(\|E\Delta x^k\|_{2,\omega}^2)_k$ converges to zero, and the equivalence between the norms $\|\cdot\|_{\omega,2}$ and $\|\cdot\|_2$ now implies (a).

It remains to prove (b), using (26) for $t \in (0, T]$ instead of T we obtain

$$\|(EQ^{-1})^{1/2}Q\Delta x^k(t)\|^2 \leq \frac{e^{2t\omega}}{2\lambda} (\|\Delta z^k\|_{2,\omega}^2 - \|\Delta z^{k+1}\|_{2,\omega}^2),$$

which shows that, for all $t \in (0, T]$, $E x^k(t) \rightarrow E x(t)$. \square

Remark 24. Though the sequence $(\|\Delta x^k\|_{2,\omega})_k$ is usually not monotone decreasing, it is bounded by the monotone decreasing sequence $(\|Q^{-1}\| \|z^k - z\|_{2,\omega})_k$ due to (24). \square

Remark 25. As the sequences $(x^k)_k, (z^k)_k$ are bounded in L^2 , each of them has a weakly convergent subsequence. \square

Theorem 26. *Let $\lambda > 0$, $\mu \geq 0$, and let $\alpha \in [0, 1]$. Assume that the DAE (2) fulfills Assumption 5, and let the operators M , N be defined as in (14) and (15). Let $\lambda > 0$ and $x^0 \in D(M)$. Let the sequence $(x^k)_k$ be defined by (22), and let x be the unique solution of (2). Then the following statements are fulfilled:*

(a) *If (19) holds, then the sequence (z^k) as defined in Theorem 23 (d) converges to $z := (I + \lambda MQ^{-1})Qx$ in $L^2([0, T], \mathbb{R}^n)$. Further, $(Ex^k)_k$ converges to Ex in $H^1([0, T], \mathbb{R}^n)$.*

(b) *If (19) or*

$$\text{rk} \begin{bmatrix} E & \alpha R \end{bmatrix} = n, \quad (29)$$

is fulfilled, then $(x^k)_k$ converges to x in $L^2([0, T], \mathbb{R}^n)$,

Proof. We start with the proof of (a): By (22) and Remark 21, we have

$$\begin{aligned} z^{k+1} &:= (I - \lambda MQ^{-1})(I + \lambda MQ^{-1})^{-1}(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}z^k, \\ z &:= (I - \lambda MQ^{-1})Q(I + \lambda MQ^{-1})^{-1}(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}z, \end{aligned}$$

and we define $\Delta z^k := z - z^k$. Assume that (19) holds. By invoking Remark 15, Lemma 17 and Lemma 20, we obtain, for $q < 1$ as in Lemma 18,

$$\begin{aligned} \|\Delta z^{k+1}\|_{2,\omega} &= \|(I - \lambda MQ^{-1})(I + \lambda MQ^{-1})^{-1}(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}z \\ &\quad - (I - \lambda MQ^{-1})(I + \lambda MQ^{-1})^{-1}(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}z^k\|_{2,\omega} \\ &\leq \|(I - \lambda NQ^{-1})(I + \lambda NQ^{-1})^{-1}\Delta z^k\|_{2,\omega} \\ &\leq q\|\Delta z^k\|_{2,\omega}. \end{aligned}$$

This implies that z^k converges in $L^2([0, T], \mathbb{R}^n)$ to z .

Next we prove that $(Ex^k)_k$ converges to Ex in $H^1([0, T], \mathbb{R}^n)$. We already know from Theorem 23 (a) that $(Ex^k)_k$ converges to Ex in $L^2([0, T], \mathbb{R}^n)$. Hence, it suffices to prove that $(\frac{d}{dt}Ex^k)_k$ converges to $\frac{d}{dt}Ex$ in $L^2([0, T], \mathbb{R}^n)$. By invoking that (z^k) converges to z in $L^2([0, T], \mathbb{R}^n)$, (24) yields that (x^k) converges to x in $L^2([0, T], \mathbb{R}^n)$. Now using the definition of x , z and M , we have

$$\begin{aligned} z^k &= Qx^k + \lambda\left(\frac{d}{dt}(Ex^k) - (J_d - \alpha R + \mu EQ^{-1})Qx^k - Bu\right), \\ z &= Qx + \lambda\left(\frac{d}{dt}(Ex) - (J_d - \alpha R + \mu EQ^{-1})Qx - Bu\right), \end{aligned}$$

which gives

$$\frac{d}{dt}(Ex) - \frac{d}{dt}(Ex^k) = \frac{1}{\lambda}(z - z^k) + \frac{1}{\lambda}Q(x - x^k) + (J_d - \alpha R + \mu EQ^{-1})Q(x - x^k).$$

Since (x^k) converges to x in $L^2([0, T], \mathbb{R}^n)$, and further, (z^k) converges to z in $L^2([0, T], \mathbb{R}^n)$, the above equation implies that $\frac{d}{dt}(Ex^k)$ converges in $L^2([0, T], \mathbb{R}^n)$ to $\frac{d}{dt}(Ex)$. Altogether, this means that (Ex^k) converges to Ex in $H^1([0, T], \mathbb{R}^n)$.

Next we prove (b). The case where (19) is fulfilled, the result follows by a combination of (a) with (24).

Assume that (29) holds: Then, by invoking Assumption 5(a)(i), the matrix $Q^\top E + \alpha Q^\top RQ$ is positive definite, and thus invertible. On the other hand, $((Q^\top E + Q^\top RQ)x^k)_k$ converges to $(Q^\top E + \alpha Q^\top RQ)x$ in $L^2([0, T], \mathbb{R}^n)$ by Theorem 23. Consequently, $(x^k)_k$ converges to x in $L^2([0, T], \mathbb{R}^n)$. \square

Based on the results of the previous section we develop the following iteration scheme. We recall that we choose $\omega > 0$ and we define

$$x^{k+1} := (Q + \lambda M)^{-1}(Q - \lambda N)(Q + \lambda N)^{-1}(Q - \lambda M)x^k,$$

with $x^0 \in D(M)$ arbitrary, and

$$z^k := (I + \lambda M Q^{-1})Qx^k.$$

Using (25) we obtain

$$z^{k+1} = (I - \lambda N Q^{-1})(I + \lambda N Q^{-1})^{-1}[2Qx^k - z^k].$$

Furthermore, relation $z^k = (Q + \lambda M)x^k$ corresponds to the DAEs

$$\frac{d}{dt}E_i x_i^k = (J_i - R_i + \mu E_i Q_i^{-1})Q_i x_i^k - \frac{1}{\lambda}Q_i x_i^k + B_i u + \frac{1}{\lambda}z_i^k, \quad i = 1, \dots, s,$$

with initial conditions $E_i x_i^n(0) = E_i x_{0,i}$ ($i = 1, \dots, s$).

Remark 27.

(a) If $\text{rk} \begin{bmatrix} E & R \end{bmatrix} < n$, then it is not possible to formulate any convergence results for (x^k) , in general. As an example, consider a system (2) with

$$E = R = 0_{2 \times 2}, \quad Q = I_2, \quad J = \begin{bmatrix} 0 & 1 \\ -1 & 0 \end{bmatrix}, \quad u = 0 \in L^2([0, T]; \mathbb{R}^2),$$

which belongs to the class specified in Assumption 5 with $s = 2$ and $n_1 = n_2 = 1$. The unique solution of (2) is clearly given by $x = 0$ (the specification of the initial value x_0 is obsolete by $E = 0$).

The above choice of E , R and Q leads to M in (14) being the zero operator, whereas N as in (15) corresponds to the multiplication with the skew-Hermitian matrix $-J$. Consequently, for $\lambda > 0$, the iteration (23) now reads

$$x^{k+1} := Ux^k, \quad \text{where } U = (I + \lambda J)(I - \lambda J)^{-1}.$$

By invoking Lemma 18, we see that U is a unitary matrix with $U \neq I_2$. Therefore, $\|x^{k+1}(t)\| = \|x^k(t)\|$ for all $k \in \mathbb{N}$, $t \in [0, T]$, and thus $\|x^{k+1}\|_2 = \|x^k\|_2$. It can be concluded that the sequence (x^k) does not converge in $L^2([0, T], \mathbb{R}^2)$ to $x = 0$. A closer look to the iteration yields that (x^k) does not even have a subsequence which weakly converges in $L^2([0, T], \mathbb{R}^2)$ to $x = 0$.

(b) Under Assumption 5, (19) is equivalent to E and R fulfilling $\text{rk} E = n$, or $\text{rk} \begin{bmatrix} E & R \end{bmatrix} = n$ and $\alpha > 0$.

(c) In the case of ordinary differential equations, i.e., $E = I$, then Theorem 26 simplifies to the following:

(i) If $\mu > 0$, or $\text{rk} R = n$ and $\alpha < 1$, then (z^k) converges to z in $L^2([0, T], \mathbb{R}^n)$, and $(x^k)_k$ converges to x in $H^1([0, T], \mathbb{R}^n)$.

(ii) $(x^k)_k$ converges to x in $L^2([0, T], \mathbb{R}^n)$. □

The above discussion results in a Lions-Mercier-type dynamic iteration for PHS, which give summarize in Alg. 1.

Algorithm 1: Lions-Mercier-type Dynamic Iteration for PHS

Require: problem data: $J_i, J_o, R_i, Q_i, E_i, B_i, u_i, x_{i,0}$ ($i = 1, \dots, s$)
Require: choose for $i = 1, \dots, s$ $z_i^0 \in L^2([0, T]; \mathbb{R}^{n_i})$ % initial guess
Require: choose parameters α, μ, λ

- 1: $R \leftarrow \text{diag}(R_1, \dots, R_s), E, Q$ analogously
- 2: $K \leftarrow (1 - \alpha)R + \mu EQ^{-1} - J_o$
- 3: $z^0 \leftarrow [(z_1^0)^\top, \dots, (z_s^0)^\top]^\top$
- 4: **for** $k = 0, 1, 2, \dots$ **do**
- 5: **for** $i = 1, 2, \dots, s$ **do**
- 6: solve for x_i^k

$$\frac{d}{dt} E_i x_i^k = (J_i - \alpha R_i + \mu E_i Q_i^{-1}) Q_i x_i^k - \frac{1}{\lambda} Q_i x_i^k + B_i u + \frac{1}{\lambda} z_i^k$$

with initial value $E_i x_i^k(0) = E_i x_{0,i}$

- 7: **end for**
- 8: $x^k \leftarrow [(x_1^k)^\top, \dots, (x_s^k)^\top]^\top$
- 9: $z^{k+1} \leftarrow (I - \lambda K)(I + \lambda K)^{-1} (2Qx^k - z^k)$
- 10: partition z^{k+1} into components $z_1^{k+1}, \dots, z_s^{k+1}$
- 11: **if** error small **then** return
- 12: **end if**
- 13: **end for**

6 Numerical results

We analyse the convergence rates for the new type of monotonic dynamic iterations (Lions-Mercier-type iteration). Then, we show numerical convergence results for the promising monotone convergence algorithms developed here.

6.1 Convergence rate discussion

For $0 < \alpha < 1$ and $K = ((1 - \alpha)R + \mu EQ^{-1} - J_o)$ the convergence rate is given by the contraction factor (21)

$$q^2 = 1 - \frac{4\lambda}{(1 + \lambda\|K\|)^2\|(K + J_o)^{-1}\|}.$$

The optimal λ^* will have the smallest error reduction factor. We find:

$$\lambda^*(\mu) = \frac{1}{\|K\|} \quad \text{and} \quad q^*(\mu, \lambda^*(\mu))^2 = 1 - \frac{1}{\|K\| \cdot \|(K + J_o)^{-1}\|}.$$

Remark 28 (Decoupled setting). *In the decoupled case, $J_o = 0$, and hence the optimal error reduction reads:*

$$q^*(\mu, \lambda^*(\mu))^2 = 1 - \frac{1}{\text{cond}(K)},$$

which is only small for nearly equilibrated matrices K . This is in contrast to (e.g.) Jacobi dynamic iteration procedures, where we have immediate convergence. \square

Considering ODEs with $E = I$ and setting $\alpha = 1$, we have $K = \mu Q^{-1} - J_o$.

Remark 29 (ODE case). *a) Transformation to $Q = I$: using the Cholesky factorization $Q = V^\top V$, we multiply (2) with V , which yields*

$$V \frac{d}{dt} x = V(J - R)(V^\top V)x + VBu(t) \quad \Leftrightarrow \quad \frac{d}{dt} \tilde{x} = (\tilde{J} - \tilde{R})\tilde{x} + \tilde{B}u(t)$$

with $\tilde{x} = Vx$, $\tilde{J} = VJV^\top$, $\tilde{R} = VRV^\top$ and $\tilde{B} = VB$ provides a remedy. Correspondingly, $y = B^\top Qx$ is transformed into $\tilde{y} = \tilde{B}^\top \tilde{x}$.

b) Decoupled setting ($J_o = 0$): The reduction factor is $q^ = 1 - \frac{1}{\text{cond}(Q)}$. Again, this is only small for scaling matrices Q with small condition number. The above transformation to $Q = I$ yields $q^* = 0$. An alternative is a shift with a matrix-valued λ in Alg. 1.*

c) Coupled setting: for $Q = I$ and the Euclidean norm this gives

$$\lambda^*(\mu) = \frac{1}{\sqrt{\mu^2 + \lambda_{\max}(J_o^\top J_o)}} \quad \text{and} \quad q^*(\mu, \lambda^*(\mu))^2 = 1 - \frac{1}{\sqrt{1 + \lambda_{\max}(J_o^\top J_o)/\mu^2}}. \quad (30)$$

6.2 Results for monotone Lions-Mercier-type algorithm

6.2.1 Example with Jacobi failure

For system (12) holds $Q = I$ and $\lambda_{\max}(J_o^\top J_o) = \nu^2$. This gives the optimal contraction constant via (30): $(q^*)^2 = 1 - \frac{1}{\sqrt{1+\nu^2/\mu^2}}$. We see the following:

Remark 30. a) *We have monotone convergence for the Lions-Mercier-type algorithm, Alg. 1.*

b) *In the limit of an undamped error bound $\omega \rightarrow 0^+$, the optimal convergence rate goes to one (for $\nu \neq 0$). This indicates an extremely slow convergence.*

c) *One can get arbitrarily small convergence rates q^* for $\mu \rightarrow \infty$. However, this corresponds to more and more damped error norms, which do not allow to estimate the numerically important undamped error.* \square

6.2.2 Simple 2x2 system with scaling

We introduce into the simple 2x2 example (12) a scaling matrix Q :

$$x' = (J-R)Qx, \quad x(0) = x_0, \quad \text{with } J-R = \begin{bmatrix} -\tau & \nu \\ -\nu & -\tau \end{bmatrix}, \quad Q = \begin{bmatrix} q_1 & 0 \\ 0 & q_2 \end{bmatrix}, \quad (31)$$

where $\tau, \nu > 0$ and $q_1 \geq q_2 > 0$. In the decoupled case, $\nu = 0$, the optimal reduction factor is given by (see Rem. 29b):

$$q(\lambda^*) = 1 - \frac{1}{\text{cond}(Q)} = 1 - \frac{q_2}{q_1}$$

Fig. 2 gives numerical results for the Lions-Mercier-type algorithm, showing that Q not being a multiple of I destroys the convergence in one step, although the system is fully decoupled.


Remark 31. *The convergence rates for the coupled cases – even for the optimal choice of λ should be improved to have more competitive dynamic iteration schemes.* \square

6.2.3 Two masses and three springs example with damping


Now, we consider two masses $m_1, m_2 > 0$, which are connected via massless springs $K_1, K_2, K_3 > 0$ to walls with damping $r_1, r_2 > 0$, see Fig. 3. To set up the system, we have positions q_1, q_2 and momenta p_1, p_2 for the masses m_1, m_2 , respectively. Then, the system can be modeled by the following Hamiltonian equation of motion:

$$\begin{aligned} \dot{q}_1 &= \frac{1}{m_1} p_1, & \dot{q}_2 &= \frac{1}{m_2} p_2, \\ \dot{p}_1 &= -(K+K_1)q_1 + Kq_2 - \frac{r_1}{m_1} p_1, & \dot{p}_2 &= -(K+K_2)q_2 + Kq_1 - \frac{r_2}{m_2} p_2. \end{aligned}$$

Notice, this is not yet given in our PHS-format (2) for the overall systems. Before we treat the overall system, we set up a description as coupled PH-subsystem as in Sec. 2.2, let $q = q_2$ denote




(a) decoupled, $Q = I$, non-optimal λ




(d) coupled, $Q = I$, non-optimal λ

Decoupled with optimal λ :
the error reduced directly to zero (no logarithmic plot).


(b) decoupled, $Q = I$, optimal λ



(e) coupled, $Q = I$, optimal λ



(c) decoupled, $Q \neq I$, optimal λ
 $q_1 = 1.5, q_2 = 1, q(\lambda^*) \approx 0.3333$



(f) coupled, $Q \neq I$, optimal λ
 $q_1 = 1.5, q_2 = 1, q(\lambda^*) \approx \frac{1}{3}$

Figure 2: Lions-Mercier-type iteration with (31): number of iterations (x) versus scaled error in coupling term v/z for various settings. First column provide the decoupled case ($\nu = 0$), and the right column the coupled case ($\nu = 1.5$). Always $\tau = -0.5$ and $\omega = 2.1$.




Figure 3: ODE two masses oscillator with damping. The coordinates q_1, q_2 describe the position of the masses.

the coupling variables, which we need for the first subsystem. Then, the two coupled PHS systems read:

$$\begin{aligned} \dot{x}_1 &= (J_1 - R_1)z_1 + B_1u_1, & \dot{x}_2 &= (J_2 - R_2)z_2 + B_2u_2, \\ y_1 &= B_1^\top z_1, & y_2 &= B_2^\top z_2, \\ & & u &= Cy, \end{aligned}$$

with quantities for the first subsystem: $x_1 = [p_1, q_1, q_1 - q]^\top$, $z_1 = Q_1x_1$,

$$Q_1 = \begin{bmatrix} \frac{1}{m_1} & 0 & 0 \\ 0 & K_1 & 0 \\ 0 & 0 & K \end{bmatrix}, \quad J_1 = \begin{bmatrix} 0 & -1 & -1 \\ 1 & 0 & 0 \\ 1 & 0 & 0 \end{bmatrix}, \quad R_1 = \begin{bmatrix} r_1 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \quad B_1 = \begin{bmatrix} 0 \\ 0 \\ -1 \end{bmatrix}$$

and for the second subsystem we have: $x_2 = [p_2, q_2]^\top$, $z_2 = Q_2x_2$

$$Q_2 = \begin{bmatrix} \frac{1}{m_2} & 0 \\ 0 & K_2 \end{bmatrix}, \quad J_2 = \begin{bmatrix} 0 & -1 \\ 1 & 0 \end{bmatrix}, \quad R_2 = \begin{bmatrix} r_2 & 0 \\ 0 & 0 \end{bmatrix}, \quad B_2 = \begin{bmatrix} 1 \\ 0 \end{bmatrix},$$

and the coupling interface reads:

$$u = \begin{bmatrix} u_1 \\ u_2 \end{bmatrix}, \quad y = \begin{bmatrix} y_1 \\ y_2 \end{bmatrix}, \quad C = \begin{bmatrix} 0 & 1 \\ -1 & 0 \end{bmatrix}.$$

Also the overall coupled system can be written in our pH-structure given in (2), with $F = \text{diag}(F_1, F_2)$ for $F \in \{J, R, Q, B\}$, cf. Rem. 7:

$$\begin{bmatrix} x_1 \\ x_2 \end{bmatrix}' = \left([J - BCB^\top] - R \right) \cdot Q \begin{bmatrix} x_1 \\ x_2 \end{bmatrix}. \quad (32)$$

Numerical results for the Lions-Mercier-type Alg. 1 are given in Fig. 4. These results show that the estimate $q^* \approx 0.975$ for the convergence rate (with an optimal choice leading to $q^* \approx 0.944$) is quite pessimistic in this case (for $\mu = 2$).




Figure 4: Convergence analysis for Lions-Mercier-type iteration ($\lambda = 1.5$, $\mu = 2$ (first row) $\mu = 0.1$ (second row), $\omega = 2.2$, $\alpha = 0.5$) for system (32) with $K_i = 2$, $m_i = 2$ ($i = 1, 2$), $K = 4$, $r_1 = 0.5$, $r_2 = 0.75$, initial values are zero apart from $p_{2,0} = 0.1$.

Remark 32. Including coupling and output quantities as variables, i.e., $\tilde{x}_i = [x_i, u_i, y_i]^\top$ yields a DAE, which has no damping (R) in the coupling or output equations. Thus it does not fit into our framework. \square

Finally, we like to discuss a DAE example. To have a DAE multibody system, a simple choice are holonomic constraints. However, such a constraint comes without dissipation. Hence $\text{rk}(E, R)$ is not full. Therefore, we change the field of applications.

6.3 Circuit example (DAE)

The electric circuit in Fig. 5 can be modelled as follows: for $x^\top = [u_1, u_2, u_3, j_1, u_4, u_5]$ and $E = \text{diag}(0, C_1, 0, L_1, 0, C_2)$ $B^\top = [1, 0, 0, 0, 0, 0]$

$$(Ex)' = Bv(t) + \left(\left[\begin{array}{ccc|cc} 0 & & & & \\ & 0 & & & \\ & & 0 & 1 & \\ & & -1 & 0 & 1 \\ \hline & & & -1 & 0 \\ & & & & 0 \end{array} \right] - \left[\begin{array}{ccc|cc} \frac{1}{R_1} & -\frac{1}{R_1} & & & \\ -\frac{1}{R_1} & \frac{1}{R_1} + \frac{1}{R_2} & & & \\ & -\frac{1}{R_2} & -\frac{1}{R_2} & & \\ \hline & & & 0 & \\ & & & & \frac{1}{R_4} & -\frac{1}{R_4} \\ & & & & -\frac{1}{R_4} & \frac{1}{R_4} + \frac{1}{R_5} \end{array} \right] \right) x.$$

This example fulfills the rank condition $\text{rk}(E, R) = n = 6$ and has block-diagonal R .




Figure 5: Example of a simple electric circuit; $R_i > 0$, $L_i > 0$, $C_i > 0$ and given $i \in L^2[0, T]$.

Numerical results for the Lions-Mercier-type Alg. 1 are given in Fig. 6. These results show that the estimate $q \approx 0.9998$ for the convergence rate (with an optimal choice leading to $q^* \approx 0.9980$) is quite pessimistic in this case, too.

Remark 33 (Rank condition for circuits). *We discuss circuit equation modelled by modified nodal analysis.*


- i) Let a circuit include one voltage sources. Then the model has a pure algebraic equation, which has no dissipation. Thus the rank condition is not satisfied.*
- ii) Electric circuits with current sources, capacitors, inductors and resistors can be made to fulfill the rank condition by adding sufficiently many resistors.*
- iii) The coupling—without auxiliary variables—can be facilitated via inductors.* □

7 Conclusions


For a general PHS setting, we have shown existence and uniqueness of weak solutions. Furthermore, the perspective of coupled systems and coupling variables are treated. Then, it is demonstrated that Jacobi-type of dynamic iteration may fail in practice due to finite precision. To circumvent this, a Mercier-Lions-type dynamic iteration scheme is developed, which guarantees monotone convergence in a related variable. The proof is based on properties of the Cayley transform. Numerical results demonstrate the monotone convergence. As a drawback, we observe that the currently achieved optimal convergence rates still need some improvements in order to pave the way for a broader application.

References


- [1] Giuseppe Ali, Andreas Bartel, Michael Günther, Vittorio Romano, and Sebastian Schöps. Simulation of coupled PDAEs: Dynamic iteration and multirate simulation. In Michael Günther, editor, *Coupled Multiscale Simulation and Optimization in Nanoelectronics*, pages 103–156. Springer Berlin Heidelberg, Berlin, Heidelberg, 2015.
- [2] Hans Wilhelm Alt. *Linear Functional Analysis*. Universitext. Springer-Verlag, London, 2016.



(a) error reduction: achieved precision vs. iteration count (left in x , center in z , right in z with weighted L^2 -norm);



(b) convergence in x_3 : we give results for iteration $l = 1, 10, 20, 30$;



(c) convergence in x_5 : we give results for iteration $l = 1, 10, 20, 30$.

Figure 6: Results for the academic circuit Fig. 5 using: $R_1 = R_2 = R_3 = R_4 = 0.5$, $R_5 = 5$, $C_1 = C_2 = 5 \cdot 10^{-4}$, $L = 20$, $i(t) = \sin(2\pi \cdot 50t) \cdot \sin(2\pi \cdot 500t)$. Lions-Mercier parameters: $\lambda = 1.2$, $\mu = 1$, $\omega = 2.2$, $\alpha = 0.2$. (a) shows the L^2 error reduction for different variables, (b) and (c) depict the convergence in a variable of the first subsystem x_3 and in the second subsystem x_5 , respectively.

- [3] Martin Arnold. Modular time integration of coupled problems in system dynamics. In Michael Günther and Wil Schilders, editors, *Novel Mathematics Inspired by Industrial Challenges*, pages 57–72. Springer International Publishing, Cham, 2022.
- [4] Martin Arnold and Michael Günther. Preconditioned dynamic iteration for coupled differential-algebraic systems. *BIT Numer. Math.*, 41:1–25, 2001.
- [5] V. Barbu. *Nonlinear Differential Equations of Monotone Types in Banach Spaces*. Springer Monographs in Mathematics. Springer-Verlag, New York, 2010.
- [6] Andreas Bartel, Markus Brunk, Michael Günther, and Sebastian Schöps. Dynamic iteration for coupled problems of electric circuits and distributed devices. *SIAM Journal on Scientific Computing*, 35(2):B315–B335, 2013.
- [7] Andreas Bartel, Markus Brunk, and Sebastian Schöps. On the convergence rate of dynamic iteration for coupled problems with multiple subsystems. *Journal of Computational and Applied Mathematics*, 262:14–24, 2014.
- [8] Andreas Bartel and Michael Günther. PDAEs in refined electrical network modeling. *SIAM Review*, 60(1):56–91, 2018.
- [9] C. Beattie, V. Mehrmann, H. Xu, and H. Zwart. Linear port-hamiltonian descriptor systems. *Math. Control Signals Systems*, 30(4):17, 2018.
- [10] Kevin Burrage. *Parallel and Sequential Methods for Ordinary Differential Equations*. Clarendon Press, Oxford, 1995.
- [11] J. Cervera, A. J. van der Schaft, and A. Baños. Interconnection of port-Hamiltonian systems and composition of Dirac structures. *Automatica*, 43(2):212–225, 2007.
- [12] H. Gernandt, F.E. Haller, and T. Reis. A linear relation approach to port-Hamiltonian differential-algebraic equations. *SIAM J. Matrix Anal. Appl.*, 42(2):1011–1044, 2020.
- [13] H. Gernandt, F.E. Haller, T. Reis, and A.J. van der Schaft. Port-Hamiltonian formulation of nonlinear electrical circuits. *J. Geom. Phys.*, 159:102959, 2020.
- [14] Michal Günther, Andreas Bartel, Birgit Jacob, and Timo Reis. Dynamic iteration schemes and port-Hamiltonian formulation in coupled DAE circuit simulation. *International Journal of Circuit Theory and Applications*, 49:430–452, 2021.
- [15] Z. Jackiewicz and M. Kwapisz. Convergence of waveform relaxation methods for differential-algebraic systems. *SIAM Journal on Numerical Analysis*, 33(6):2303–2317, 1996.
- [16] D. Jeltsema and A.J. van der Schaft. Port-Hamiltonian systems theory: An introductory overview. *Foundations and Trends in Systems and Control*, 1(2-3):173–387, 2014.
- [17] Peter Kunkel and Volker Mehrmann. *Differential-Algebraic Equations. Analysis and Numerical Solution*. EMS Publishing House, Zürich, Switzerland, 2006.

- [18] René Lamour, Roswitha März, and Caren Tischendorf. *Differential Algebraic Equations: A Projector Based Analysis*, volume 1 of *Differential-Algebraic Equations Forum*. Springer-Verlag, Heidelberg-Berlin, 2013.
- [19] P. L. Lions and B. Mercier. Splitting algorithms for the sum of two nonlinear operators. *SIAM Journal on Numerical Analysis*, 16(6):964–979, 1979.
- [20] B. Maschke and A.J. van der Schaft. Generalized port-Hamiltonian DAE systems. *System & Control Letters*, 121:31–37, 2018.
- [21] B. Maschke and A.J. van der Schaft. Dirac and Lagrange algebraic constraints in nonlinear port-Hamiltonian systems. *Vietnam J. Math.*, 48:929–939, 2020.
- [22] C. Mehl, V. Mehrmann, and M. Wojtylak. Linear algebra properties of dissipative Hamiltonian descriptor systems. *SIAM Journal on Matrix Analysis and Applications*, 39(3):1489–1519, 2018.
- [23] Volker Mehrmann and Riccardo Morandin. Structure-preserving discretization for port-Hamiltonian descriptor systems. In *2019 IEEE 58th Conference on Decision and Control (CDC)*, pages 6863–6868, 2019.
- [24] A.J. van der Schaft. Port-Hamiltonian systems: Network modeling and control of nonlinear physical systems. In K. Schlacher and H. Irschnik, editors, *Advanced Dynamics and Control of Structures and Machines*, volume 444 of *CISM courses and lectures*, pages 127–167. Springer, Vienna, 2004.
- [25] A.J. van der Schaft. Port-Hamiltonian differential-algebraic systems. In Achim Ilchmann and Timo Reis, editors, *Surveys in Differential-Algebraic Equations I*, *Differential-Algebraic Equations Forum*, pages 173–226. Springer, Berlin-Heidelberg, 2013.